

















POSSIBILITE DE BRANCHEMENT DES BORNES DE RACCORDEMENT

SERIE "ZETA plus"

REFERENCE	SECTION NOMINALE	Nb. DE VOIES par SECTION NOMINALE	POSSIBILITE de BRANCHEMENT DANS CHAQUE VOIE* Nb. de Conducteurs par Section	MARQUAGES et MARQUES
Z6-3 Z6-3D	6 ²	3 x 6 ²	1 x 6 ² R/S 1 x 4 ² R/S 1÷2 x 2,5 ² R/S 1÷2 x 1,5 ² R/S 1÷4 x 1 ² R/S	   
Z6-5 Z6-5D	6 ²	5 x 6 ²		
Z6-6 Z6-6D	6 ²	6 x 6 ²		
Z6-10 Z6-10D	6 ²	10 x 6 ²		
Z16-3 Z16-3D	16 ²	3 x 16 ²	1 x 16 ² R/S 1 x 10 ² R/S 1÷2 x 6 ² R/S 1÷3 x 4 ² R/S 1÷4 x 2,5 ² R/S 1÷8 x 1,5 ² R/S	   
Z16-4 Z16-4D	16 ²	4 x 16 ²	1 x 16 ² S 1 x 10 ² S 1÷2 x 6 ² S 1÷3 x 4 ² S 1÷4 x 2,5 ² S 1÷8 x 1,5 ² S	 
Z16-5N Z16-5ND	16 ²	5 x 16 ²	1 x 16 ² R/S 1 x 10 ² R/S 1÷2 x 6 ² R/S 1÷3 x 4 ² R/S 1÷4 x 2,5 ² R/S 1÷8 x 1,5 ² R/S	 
Z16-8 Z16-8D	16 ² /6 ²	2 x 16 ²	1 x 16 ² R/S 1 x 10 ² R/S 1÷2 x 6 ² R/S 1÷3 x 4 ² R/S 1÷4 x 2,5 ² R/S 1÷8 x 1,5 ² R/S	 
		6 x 6 ²	1 x 6 ² R/S 1 x 4 ² R/S 1÷2 x 2,5 ² R/S 1÷2 x 1,5 ² R/S 1÷4 x 1 ² R/S	
Z16-12 Z16-12D	16 ² /6 ²	2 x 16 ²	1 x 16 ² S 1 x 10 ² S 1÷2 x 6 ² S 1÷3 x 4 ² S 1÷4 x 2,5 ² S	 
		10 x 6 ²	1 x 6 ² S 1 x 4 ² S 1÷2 x 2,5 ² S 1÷2 x 1,5 ² S 1÷4 x 1 ² S	

*Il est aussi possible de connecter d'autres combinaisons de câbles, à la condition que la section totale obtenue ne soit pas supérieure à la section nominale

R = conducteur Rigide S = conducteur Souple