



**Automatización Eléctrica**

Especialistas en Automatización

At the end of this document you will find links to products related to this catalog. You can go directly to our shop by clicking [HERE](#)

## General Information

Extended Product Type:	MO132-1.0
Product ID:	1SAM360000R1005
EAN:	4013614400209
Catalog Description:	MO132-1.0 Manual Motor Starter Magnetic Only
Long Description:	The MO132-1.0 manual motor starter magnetic only is a compact 45 mm width devices with a rated operational current of $I_e = 1.00$ A. This device is used to manually switch on and off loads/motors and to protect them reliably and without the need for a fuse from short-circuits. The manual motor starter offers a rated service short-circuit breaking capacity $I_{cs} = 50$ kA at 400 VAC. A combination together with overload relays or motor controllers allows the protection of motors. Further features are the build-in disconnect function, trip-free mechanism and a rotary handle with a clear switch position indication. The manual motor starter magnetic only is suitable for three- and single-phase applications. The handle is lockable to protect against unauthorized changes. Auxiliary contacts, signalling contacts, undervoltage releases, shunt trips, 3-phase bus bars, power in-feed blocks are available as accessory.

## Categories

Products » Low Voltage Products and Systems » Circuit Breakers » Manual Motor Starters
Products » Low Voltage Products and Systems » Control Products » Manual Motor Starters » Manual Motor Starters

## Ordering

EAN:	4013614400209
Minimum Order Quantity:	1 piece
Customs Tariff Number:	85362010

## Dimensions

Product Net Width:	45 mm
Product Net Height:	90 mm
Product Net Depth:	86.75 mm
Product Net Weight:	0.215 kg

## Container Information

Package Level 1 Units:	1 piece
Package Level 1 Width:	92 mm
Package Level 1 Height:	50 mm
Package Level 1 Length:	95 mm
Package Level 1 Gross Weight:	0.23 kg
Package Level 2 Units:	40 piece
Package Level 2 Width:	280 mm
Package Level 2 Height:	210 mm
Package Level 2 Length:	395 mm
Package Level 2 Gross Weight:	9.586 kg
Package Level 2 EAN:	4013614443657

## Environmental

Ambient Air Temperature:	Around the Enclosure 0 ... +40 °C Operation -25 ... +60 °C Storage -50 ... +80 °C
Ambient Air Temperature Compensation:	No
Maximum Operating Altitude Permissible:	2000 m
Resistance to Shock acc. to IEC 60068-2-27:	11 ms Pulse 25g
Resistance to Vibrations acc. to IEC 60068-2-6:	5g / 3 ... 150 Hz
RoHS Status:	Following EU Directive 2002/95/EC August 18, 2005 and amendment

## Technical UL/CSA

Maximum Operating Voltage UL/CSA:	Main Circuit 600 V AC
Ampere Rating UL/CSA:	1 A
Horsepower Rating UL/CSA:	(550 ... 600 V AC) Three Phase 0.5 Hp
General Use Rating UL/CSA:	(600 V AC) 1 A

<b>Connecting Capacity Main Circuit UL/CSA:</b>	Flexible 1/2x 16 ... 12 AWG Stranded 1/2x 16 ... 12 AWG
<b>Tightening Torque UL/CSA:</b>	Main Circuit 10 in·lb

## Additional Information

<b>Actuator Type:</b>	Rotary Handle
<b>Connecting Capacity-Main Circuit:</b>	Flexible with Ferrule 1/2x 0.75 ... 2.5 mm <sup>2</sup> Flexible with Insulated Ferrule 1/2x 0.75 ... 2.5 mm <sup>2</sup> Flexible 1/2x 0.75 ... 2.5 mm <sup>2</sup> Rigid 1/2x 1 ... 4 mm <sup>2</sup>
<b>Conventional Free-air Thermal Current (I<sub>th</sub>):</b>	Main Circuit 1 A
<b>Degree of Protection:</b>	IP20
<b>Electrical Durability:</b>	50000 cycle
<b>Mechanical Durability:</b>	100000 cycle
<b>Mounting on DIN Rail:</b>	TH35-15 (35 x 15 mm Mounting Rail) acc. to IEC 60715 TH35-7.5 (35 x 7.5 mm Mounting Rail) acc. to IEC 60715
<b>Mounting Position:</b>	Position 1 to 6
<b>Number of Poles:</b>	3
<b>Number of Protected Poles:</b>	3
<b>Pollution Degree:</b>	3
<b>Power Loss:</b>	at Rated Operating Conditions per Pole 1.7 W
<b>Product Main Type:</b>	MO132
<b>Product Name:</b>	Manual Motor Starter Magnetic Only
<b>Rated Current (I<sub>n</sub>):</b>	1 A
<b>Rated Frequency (f):</b>	Main Circuit 50 Hz Main Circuit 60 Hz
<b>Rated Impulse Withstand Voltage (U<sub>imp</sub>):</b>	Main Circuit 6 kV
<b>Rated Instantaneous Short-Circuit Current Setting (I<sub>j</sub>):</b>	12.5 A
<b>Rated Insulation Voltage (U<sub>i</sub>):</b>	690 V
<b>Rated Operational Current (I<sub>e</sub>):</b>	1 A
<b>Rated Operational Current AC-3 (I<sub>e</sub>):</b>	1 A
<b>Rated Operational Power AC-3 (P<sub>e</sub>):</b>	(400 V) Three Phase 0.25 kW
<b>Rated Operational Voltage:</b>	Main Circuit 690 V AC
<b>Rated Service Short-Circuit Breaking Capacity (I<sub>cs</sub>):</b>	(230 V AC) 100 kA (400 V AC) 100 kA (440 V AC) 100 kA (500 V AC) 100 kA (690 V AC) 100 kA
<b>Rated Ultimate Short-Circuit Breaking Capacity (I<sub>cu</sub>):</b>	(230 V AC) 100 kA (400 V AC) 100 kA (440 V AC) 100 kA (500 V AC) 100 kA (690 V AC) 100 kA
<b>Rated Uninterrupted Current (I<sub>u</sub>):</b>	1 A
<b>Recommended Screw Driver:</b>	Pozidriv 2
<b>Remarks:</b>	For overload protection of the motors, an appropriate thermal or electronic overload relays must be used
<b>RoHS Date:</b>	0159
<b>Setting Range:</b>	None
<b>Standards:</b>	IEC/EN 60947-1 IEC/EN 60947-2 IEC/EN 60947-4-1 UL 60947-1 UL 60947-4-1
<b>Terminal Type:</b>	Screw Terminals
<b>Tightening Torque:</b>	Main Circuit 0.8 ... 1.2 N·m
<b>Wire Stripping Length:</b>	Main Circuit 9 mm

## Certificates and Declarations (Document Number)

<b>ABS Certificate:</b>	1SAA963001-0101
<b>BV Certificate:</b>	1SAA963001-0201
<b>CB Certificate:</b>	1SAA963002-2001
<b>CCC Certificate:</b>	1SAA963001-3804
<b>cUL Certificate:</b>	cUL_E137861 cUL_E345003

<b>Data Sheet, Technical Information:</b>	2CDC131035D0201
<b>Data Sheet, Technical Information (Part 2):</b>	1SAM300515F0005
<b>Declaration of Conformity - CE:</b>	1SAD938503-0183
<b>DNV Certificate:</b>	1SAA963001-0302
<b>EAC Certificate:</b>	1SAA963000-2701
<b>GL Certificate:</b>	1SAA963001-0401
<b>GOST Certificate:</b>	1SAA937000-2703
<b>LR Certificate:</b>	1SAA963001-0502
<b>RINA Certificate:</b>	1SAA963000-0802
<b>RMRS Certificate:</b>	1SAA918000-0703
<b>RoHS Information:</b>	1SAA963002-4405
<b>UL Certificate:</b>	UL_E137861 UL_E345003

Classifications

<b>eClass:</b>	7.0 27370401
<b>ETIM 4:</b>	EC000074 - Motor protective circuit-breaker
<b>ETIM 5:</b>	EC000074 - Motor protective circuit-breaker
<b>Object Classification Code:</b>	F
<b>UNSPSC:</b>	39121521





**Automatización Eléctrica**  
Especialistas en Automatización

Below is a list of articles with direct links to our shop Electric Automation Network where you can see:

- Quote per purchase volume in real time.
- Online documentation and datasheets of all products.
- Estimated delivery time enquiry in real time.
- Logistics systems for the shipment of materials almost anywhere in the world.
- Purchasing management, order record and tracking of shipments.

To access the product, [click on the green button](#).

Product	Code	Reference	Product link
MO132-1.0 Manual Motor Starter Magnetic Only	1SAM360000R1005	MO132-1	<a href="#">Buy on EAN</a>