

Circuit-breaker, 4p, 1600 A, fixed

Powering Business Worldwide™

Part no. IZMX40B4-A16F Article no. 149856

Catalog No. RES6164B22-NMNN2MN1X

Delivery programme

| | | Air circuit-breakers/switch-disconnectors |
|--------------------------|--|--|
| | | Open circuit-breakers |
| | | Up to 4000 A |
| | | System protection |
| | | Fixed |
| | | IZMX40 |
| | | Electronic release |
| | | IEC |
| | | 4 pole |
| | | IP20, IP55 with protective cover, IP41 door sealing frame |
| | | optionally fittable by user with comprehensive accessories |
| $I_n = I_u$ | Α | 1600 |
| I _{cu} | kA | 66 |
| Ics | kA | 66 |
| I _r | Α | 800 |
| Ir | Α | 1600 |
| $I_i = I_n \times \dots$ | | 2 - 12 |
| | | |
| | | |
| | | |
| | I _{cu} I _{cs} I _r | I _{cu} kA I _{cs} kA I _r A |

Technical data

Rated impulse withstand voltage

Rated operational voltage

| General | | | |
|---|----------------|----|---|
| Standards | | | IEC/EN 60947 |
| Ambient temperature | | | |
| Storage | 9 | °C | -40 - +70 |
| Operating (open) | | °C | -25 - +70 |
| Mounting position | | | 30° 30° |
| | | | 30° 30° |
| Utilization category | | | В |
| Degree of Protection | | | IP20, IP55 with protective cover, IP41 door sealing frame |
| Direction of incoming supply | | | as required |
| Main conducting paths | | | |
| Rated current = rated uninterrupted current | $I_n = I_u$ | Α | 1600 |
| Rated uninterrupted current at 50 °C | Iu | Α | 1600 |
| Rated uninterrupted current at 60 °C | Iu | Α | 1600 |
| Rated uninterrupted current at 70 °C | I _u | Α | 1600 |

V AC

V AC

12000

690

 $\,U_{imp}\,$

| Use in IT electrical power networks up to U = 440 V | I _{IT} | kA | 36 |
|---|-----------------|----|---|
| Overvoltage category/pollution degree | | | III/3 |
| Rated insulation voltage | Ui | V | 1000 |
| Switching capacity | | | |
| Rated short-circuit making capacity | I _{cm} | | |
| up to 440 V 50/60 Hz | I _{cm} | kA | 145 |
| up to 690 V 50/60 Hz | I _{cm} | kA | 145 |
| Rated short-time withstand current 50/60 Hz | | | |
| t=1s | I _{cw} | kA | 66 |
| t = 3 s | I _{cw} | kA | 53 |
| Rated short-circuit breaking capacity I _{cn} | I _{cn} | | |
| IEC/EN 60947 operating sequence I _{cu} 0-t-C0 | | | |
| up to 240 V 50/60 Hz | I _{cu} | kA | 66 |
| up to 440 V 50/60 Hz | I _{cu} | kA | 66 |
| up to 690 V 50/60 Hz | I _{cu} | kA | 66 |
| IEC/EN 60947 operating sequence I _{cs} 0-t-CO-t-CO | ·cu | | |
| | | LΛ | CC CC |
| up to 240 V 50/60 Hz | I _{cs} | kA | 66 |
| up to 440 V 50/60 Hz | I _{cs} | kA | 66 |
| up to 690 V 50/60 Hz | I _{cs} | kA | 66 |
| Operating times | | | |
| Closing delay via spring release | | ms | 35 |
| Total opening delay via shunt release | | ms | 22 |
| Total opening delay via undervoltage release | | ms | 37 |
| | | | |
| Total opening delay on non-delayed short-circuit release (up to complete arc quenching) | | ms | 45 |
| Maximum operating frequency | Operations/h | | 60 |
| Heat dissipation at rated current I _n | | | |
| Fixed mounting | | W | 140 |
| Weight | | | |
| Fixed mounting | | | |
| 3-pole | | kg | 43 |
| 4-pole | | kg | 56 |
| Terminal capacities Copper bar | | | |
| Fixed mounting | | | |
| Black | | mm | 1 x 80 x 10 |
| Liden | | | These are values used in separate switchgear. The actual values will depend on the temperature around the circuit-breaker, which is influenced by the ambient temperature, the degree of protection (IP), the mounting height, the partitions, and any external ventilation. Depending on the specific switchgear design, this may result in derating, which can then be compensated for by increasing the cross-sectional area. Temperature rise tests in the specific switchgear can provide specific and detailed information. |
| | | | Permissible continuous current for circuit-breakers operating in switchboards at various internal ambient temperatures. The switchboard's internal ambient temperature should be estimated using the calculation methods of IEC regulation. |

Design verification as per IEC/EN 61439

| Technical data for design verification | | | |
|--|------------------|----|--|
| Rated operational current for specified heat dissipation | In | Α | 1600 |
| Equipment heat dissipation, current-dependent | P_{vid} | W | 140 |
| Operating ambient temperature min. | | °C | -25 |
| Operating ambient temperature max. | | °C | 70 |
| IEC/EN 61439 design verification | | | |
| 10.2 Strength of materials and parts | | | |
| 10.2.2 Corrosion resistance | | | Meets the product standard's requirements. |
| 10.2.3.1 Verification of thermal stability of enclosures | | | Meets the product standard's requirements. |

| 10.2.3.2 Verification of resistance of insulating materials to normal heat | Meets the product standard's requirements. |
|--|--|
| · · | |
| 10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects | Meets the product standard's requirements. |
| 10.2.4 Resistance to ultra-violet (UV) radiation | Meets the product standard's requirements. |
| 10.2.5 Lifting | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.2.6 Mechanical impact | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.2.7 Inscriptions | Meets the product standard's requirements. |
| 10.3 Degree of protection of ASSEMBLIES | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.4 Clearances and creepage distances | Meets the product standard's requirements. |
| 10.5 Protection against electric shock | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.6 Incorporation of switching devices and components | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.7 Internal electrical circuits and connections | Is the panel builder's responsibility. |
| 10.8 Connections for external conductors | Is the panel builder's responsibility. |
| 10.9 Insulation properties | |
| 10.9.2 Power-frequency electric strength | Is the panel builder's responsibility. |
| 10.9.3 Impulse withstand voltage | Is the panel builder's responsibility. |
| 10.9.4 Testing of enclosures made of insulating material | Is the panel builder's responsibility. |
| 10.10 Temperature rise | The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. |
| 10.11 Short-circuit rating | Is the panel builder's responsibility. The specifications for the switchgear must observed. |
| 10.12 Electromagnetic compatibility | Is the panel builder's responsibility. The specifications for the switchgear must observed. |
| 10.13 Mechanical function | The device meets the requirements, provided the information in the instruction leaflet (IL) is observed. |

Technical data ETIM 6.0

Low-voltage industrial components (EG000017) / Power circuit-breaker for trafo/generator/installation prot. (EC000228)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Circuit breaker for power transformer, generator and system protection (ecl@ss8.1-27-37-04-09 [AJZ716010])

| Rated voltage Rated short-circuit breaking capacity leu at 400 V, 50 Hz Avious de lease current setting Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit release Adjustment range unde | | | |
|--|---|----|--|
| Rated short-circuit breaking capacity lcu at 400 V, 50 Hz Overload release current setting A a 800 - 1600 Adjustment range short-term delayed short-circuit release A 0 - 0 Adjustment range undelayed short-circuit release A 3200 - 19200 Integrated earth fault protection Type of electrical connection of main circuit Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional A 800 - 1600 No 9 200 - 19200 No No No A 8ail connection No No A O - 0 A 3200 - 19200 No No A 801 - 10200 No No A 902 - 19200 No No A 902 - 19200 No No A 903 - 19200 No No A 903 - 19200 No No A 902 - 19200 No | Rated permanent current lu | Α | 1600 |
| Overload release current setting Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit release Built-in device fixed built-in technique Adjustment range undelayed short-circuit Anone range undelayed short-circuit release Adjustment facility device fixed built-in technique Adjustment device | Rated voltage | V | 690 - 690 |
| Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit release A 200 - 19200 No Rail connection Built-in device fixed built-in technique Built-in device fixed built-in technique Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release With under voltage release No Number of poles Position of connection for main current circuit Agents Suitched-device with protection unit Yes Motor drive integrated Motor drive integrated Motor drive optional | Rated short-circuit breaking capacity Icu at 400 V, 50 Hz | kA | 66 |
| Adjustment range undelayed short-circuit release A 3200 - 19200 Integrated earth fault protection No Type of electrical connection of main circuit Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release With under voltage release No Number of poles Position of connection for main current circuit Suppleted evice with protection unit Motor drive integrated Motor drive integrated Motor drive optional Motor drive optional | Overload release current setting | Α | 800 - 1600 |
| Integrated earth fault protection Type of electrical connection of main circuit Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release With under voltage release Number of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional No | Adjustment range short-term delayed short-circuit release | Α | 0 - 0 |
| Type of electrical connection of main circuit Device construction Built-in device fixed built-in technique No No DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional No Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release With under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional | Adjustment range undelayed short-circuit release | Α | 3200 - 19200 |
| Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional No Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release With under voltage release No Number of poles Position of connection for main current circuit Back side Type of control element Complete device with protection unit Motor drive integrated Motor drive optional | Integrated earth fault protection | | No |
| Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact 0 Number of auxiliary contacts as normally open contact 0 Number of auxiliary contacts as change-over contact 0 Number of auxiliary contacts as change-over contact 2 Switched-off indicator available With under voltage release No Number of poles Position of connection for main current circuit Back side Type of control element Complete device with protection unit Motor drive integrated No Motor drive optional No | Type of electrical connection of main circuit | | Rail connection |
| DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available Yes With under voltage release With under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional No Motor drive optional | Device construction | | Built-in device fixed built-in technique |
| Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact Switched-off indicator available Yes With under voltage release No Number of poles 4 Position of connection for main current circuit Back side Type of control element Complete device with protection unit Yes Motor drive integrated Motor drive optional O O Number of poles Ves No Yes | Suitable for DIN rail (top hat rail) mounting | | No |
| Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional O Q Q Q Q Q Q Q Q Q Q Q Q | DIN rail (top hat rail) mounting optional | | No |
| Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release With under of poles No Number of poles Position of connection for main current circuit Suppe of control element Complete device with protection unit Motor drive integrated Motor drive optional 2 Yes A No No Yes No Yes | Number of auxiliary contacts as normally closed contact | | 0 |
| Switched-off indicator available With under voltage release No Number of poles A Position of connection for main current circuit Back side Type of control element Complete device with protection unit Motor drive integrated Motor drive optional Yes Yes Yes Yes Yes Yes Yes Ye | Number of auxiliary contacts as normally open contact | | 0 |
| With under voltage release No Number of poles 4 Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated No Motor drive optional No | Number of auxiliary contacts as change-over contact | | 2 |
| Number of poles 4 Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional 4 Back side Push button Yes No Yes | Switched-off indicator available | | Yes |
| Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive optional Back side Push button Yes No Yes | With under voltage release | | No |
| Type of control element Complete device with protection unit Motor drive optional Push button Yes No Yes | Number of poles | | 4 |
| Complete device with protection unit Yes Motor drive integrated No Motor drive optional Yes | Position of connection for main current circuit | | Back side |
| Motor drive integrated No Yes | Type of control element | | Push button |
| Motor drive optional Yes | Complete device with protection unit | | Yes |
| | Motor drive integrated | | No |
| Degree of protection (IP) | Motor drive optional | | Yes |
| 11 20 | Degree of protection (IP) | | IP20 |