DATASHEET - IZMX16B4-P10W



Circuit-breaker 4p, 1000A, withdrawable

Part no. IZMX16B4-P10W Catalog No. IZ3233

•

EL-Nummer (Norway) 4357177



Delivery program

Delivery program			
Product range			Air circuit-breakers/switch-disconnectors
Product range			Open circuit-breakers
Current Range			Up to 4000 A
Protective function			Professional protection
Installation type			Withdrawable
			Cassette must be separately ordered.
			IZMX-DTP-PTM external voltage measuring module required
Construction size			IZMX16
Release system			Electronic release
Standard/Approval			IEC
Number of poles			4 pole
Degree of Protection			IP20, IP55 with protective cover, IP41 door sealing frame
			suitable for zone selectivity suitable for communication with integrated system monitor with integrated test possibility with graphic LCD color display optionally fittable by user with comprehensive accessories
Rated current = rated uninterrupted current	$I_n = I_u$	Α	1000
up to 440 V 50/60 Hz	I _{cu}	kA	42
up to 440 V 50/60 Hz	I _{cs}	kA	42
Overload release, min.	I _r	Α	500
Overload release, max.	I _r	Α	1000
Non-delayed	$I_i = I_n x \dots$		2 - 12, OFF
Delayed >	$I_{sd} = I_r x \dots$		2 - 10

Technical data

General

General			
Standards			IEC/EN 60947
Ambient temperature			
Storage	9	°C	-25 - +70 (device with LCD-display -20 - +70)
Operating (open)		°C	-25 - +70 (device with LCD-display -20 - +70)
Mounting position			30° 30°
Utilization category			30° 30°
Degree of Protection			IP20, IP55 with protective cover, IP41 door sealing frame
*			• • • •

Direction of incoming supply			as required
Main conducting paths			as required
Rated current = rated uninterrupted current	$I_n = I_u$	Α	1000
Rated uninterrupted current at 50 °C	I _u	Α	1000
Rated uninterrupted current at 60 °C	Iu	Α	1000
Rated uninterrupted current at 70 °C	Iu	Α	1000
Rated impulse withstand voltage	U _{imp}	V AC	12000
Rated operational voltage	U _e	V AC	690
Use in IT electrical power networks up to U = 440 V		kA	23
	I _{IT}	KA.	
Overvoltage category/pollution degree		V	111/3
Rated insulation voltage Switching capacity	Ui	V	1000
Rated short-circuit making capacity	I _{cm}		
up to 440 V 50/60 Hz	I _{cm}	kA	88
up to 690 V 50/60 Hz		kA	88
	I _{cm}	NA.	
Rated short-time withstand current 50/60 Hz t = 1 s		kA	42
	I _{cw}	NA.	74
Rated short-circuit breaking capacity I _{cn}	I _{cn}		
IEC/EN 60947 operating sequence I _{cu} 0-t-C0			
up to 240 V 50/60 Hz	I _{cu}	kA	42
up to 440 V 50/60 Hz	I _{cu}	kA	42
up to 690 V 50/60 Hz	I _{cu}	kA	42
IEC/EN 60947 operating sequence I_{cs} 0-t-C0-t-C0			
up to 240 V 50/60 Hz	I _{cs}	kA	42
up to 440 V 50/60 Hz	I _{cs}	kA	42
up to 690 V 50/60 Hz	I _{cs}	kA	42
Operating times			
Closing delay via spring release		ms	30
Total opening delay via shunt release		ms	25
Total opening delay via undervoltage release		ms	50
Total opening delay on non-delayed short-circuit release (up to complete arc quenching)		ms	25
•		c	
Lifespan	Curitohina	S	12500
Lifespan, mechanical	Switching cycles (ON/		12500
	OFF)		
Lifespan, mechanical with maintenance	Switching cycles (ON/		20000
	OFF)		
Lifespan, electrical	Switching cycles (ON/		10000
	OFF)		
Lifespan, electrical with maintenance	Switching		10000
	cycles (ON/ OFF)		
Maximum operating frequency	Operations/h		60
Heat dissipation at rated current I _n			
Withdrawable units (switch with cassette)		W	125
Weight			
Withdrawable			
3-pole		kg	28
4-pole		kg	33
Cassette			
3 pole		kg	18
4 pole		kg	21
Terminal capacities Copper bar			
ooppei uai			

Fixed mounting		
Black	mm	2 x 5 x 60
Withdrawable units		
Black	mm	2 x 5 x 60
		These are values used in separate switchgear. The actual values will depend on the temperature around the circuit-breaker, which is influenced by the ambient temperature, the degree of protection (IP), the mounting height, the partitions, and any external ventilation. Depending on the specific switchgear design, this may result in derating, which can then be compensated for by increasing the cross-sectional area. Temperature rise tests in the specific switchgear can provide specific and detailed information.
		Permissible continuous current for circuit-breakers operating in switchboards at various internal ambient temperatures. The switchboard's internal ambient temperature should be estimated using the calculation methods of IEC regulation.
Notes		IZMX-DTP-PTM external voltage measuring module required

Design verification as per IEC/EN 61439

Technical data for design verification			
Rated operational current for specified heat dissipation	In	Α	1000
Equipment heat dissipation, current-dependent	P _{vid}	W	125
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	70
IEC/EN 61439 design verification			
10.2 Strength of materials and parts			
10.2.2 Corrosion resistance			Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures			Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat			Meets the product standard's requirements.
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects			Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation			Meets the product standard's requirements.
10.2.5 Lifting			Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact			Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions			Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES			Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances			Meets the product standard's requirements.
10.5 Protection against electric shock			Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components			Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections			Is the panel builder's responsibility.
10.8 Connections for external conductors			Is the panel builder's responsibility.
10.9 Insulation properties			
10.9.2 Power-frequency electric strength			Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage			Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material			Is the panel builder's responsibility.
10.10 Temperature rise			The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating			Is the panel builder's responsibility. The specifications for the switch gear must be observed. $\label{eq:constraint}$
10.12 Electromagnetic compatibility			Is the panel builder's responsibility. The specifications for the switch gear must be observed. $\label{eq:constraint}$
10.13 Mechanical function			The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 6.0

 $Low-voltage\ industrial\ components\ (EG000017)\ /\ Power\ circuit-breaker\ for\ trafo/generator/installation\ prot.\ (EC000228)$

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Circuit breaker for power transformer, generator and system protection (ecl@ss8.1-27-37-04-09 [AJZ716010])

protection (eci@sss.1-2/-5/-04-03 [AJ2/10010])		
Rated permanent current lu	Α	1000
Rated voltage	V	690 - 690
Rated short-circuit breaking capacity Icu at 400 V, 50 Hz	kA	42
Overload release current setting	Α	500 - 1000

Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit release Adjustment range undelayed short-circuit release Integrated earth fault protection Type of electrical connection of main circuit Device construction Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Switched-off indicator available With under voltage release With under voltage release No No No No No No No No No N			
Integrated earth fault protection Type of electrical connection of main circuit Rail connection Built-in device slide-in technique (withdrawable) Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release No Number of poles Position of connection for main current circuit Type of control element No No No Rail connection Rail conne	Adjustment range short-term delayed short-circuit release	Α	2000 - 10000
Type of electrical connection of main circuit Device construction Built-in device slide-in technique (withdrawable) No DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional No Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact Switched-off indicator available Ves With under voltage release No Number of poles Position of connection for main current circuit Type of control element Rail connection Built-in device slide-in technique (withdrawable) No No No No No Pes With under of auxiliary contacts as normally closed contact O Number of auxiliary contacts as change-over contact 2 Switched-off indicator available Yes With under voltage release No No Number of poles 4 Position of connection for main current circuit Push button	Adjustment range undelayed short-circuit release	Α	2000 - 12000
Device construction Built-in device slide-in technique (withdrawable) Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release No Number of poles Position of connection for main current circuit Type of control element Built-in device slide-in technique (withdrawable) No No Built-in device slide-in technique (withdrawable) No No Built-in device slide-in technique (withdrawable) No No Built-in device slide-in technique (withdrawable) No DIN rail (top hat rail) mounting No DIN rail (top hat rail) mounting No O Sumber of auxiliary contacts as normally closed contact O Number of auxiliary contacts as normally closed contact O Number of auxiliary contacts as normally closed contact O Number of auxiliary contacts as normally closed contact O Number of auxiliary contacts as normally closed contact O Number of auxiliary contacts as normally closed contact O Number of auxiliary contacts as normally closed contact O Number of auxiliary contacts as normally closed contact O Number of auxiliary contacts as normally closed contact O Number of auxiliary contacts as normally closed contact O Suitched-off indicator available Ves Number of auxiliary contacts as normally closed contact O Suitched-off indicator available Ves Number of auxiliary contacts as normally closed contact O Suitched-off indicator available No Number of auxiliary contacts as normally closed contact O Suitched-off indicator av	Integrated earth fault protection		No
Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional No Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release No Number of poles Position of connection for main current circuit Type of control element No No Push button	Type of electrical connection of main circuit		Rail connection
DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact 2 Switched-off indicator available With under voltage release No Number of poles 4 Position of connection for main current circuit Type of control element No Number of poles Push button	Device construction		Built-in device slide-in technique (withdrawable)
Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release No Number of poles 4 Position of connection for main current circuit Type of control element 0 0 4 Push button	Suitable for DIN rail (top hat rail) mounting		No
Number of auxiliary contacts as normally open contact 2 Switched-off indicator available With under voltage release No Number of poles Position of connection for main current circuit Type of control element O Ves Yes No Back side Push button	DIN rail (top hat rail) mounting optional		No
Number of auxiliary contacts as change-over contact 2 Switched-off indicator available With under voltage release With under of poles Ves No Number of poles 4 Position of connection for main current circuit Type of control element Push button	Number of auxiliary contacts as normally closed contact		0
Switched-off indicator available With under voltage release No Number of poles 4 Position of connection for main current circuit Type of control element Yes No 4 Push button	Number of auxiliary contacts as normally open contact		0
With under voltage release No Number of poles 4 Position of connection for main current circuit Type of control element No Push button	Number of auxiliary contacts as change-over contact		2
Number of poles 4 Position of connection for main current circuit Back side Type of control element Push button	Switched-off indicator available		Yes
Position of connection for main current circuit Type of control element Back side Push button	With under voltage release		No
Type of control element Push button	Number of poles		4
	Position of connection for main current circuit		Back side
Complete device with protection unit Yes	Type of control element		Push button
	Complete device with protection unit		Yes
Motor drive integrated No	Motor drive integrated		No
Motor drive optional Yes	Motor drive optional		Yes
Degree of protection (IP)	Degree of protection (IP)		IP20