



Closing release 24 VDC

Part no. **+IZMX-SR24DC**  
 Catalog No. **123735**

### Delivery program

Product range			Accessories
Accessories			Remote switching
Accessories			closing release
			Without latch check switch.
Maximum operating frequency	Actuations/ minute		3
			Limited to 3/min due to the high pick-up current for 35 ms. Please note - the circuit-breaker's switching frequency = 60/h
Rated control voltage	$U_s$	V	24 V DC
Operating range	$x U_s$	Factor	0,85 - 1,1
max. pick-up current (35ms)	$I_n$	A	19
max. pull-in power (35ms)	AC/DC	VA/W	500
Circuit-breaker total switching time	@ $U_s=100\%$	ms	35
For use with			IZMX16..., IZMX40... INX16..., INX40...

**Notes**

Suitable for continuous commands (100% DF)

The ON command can only be accepted if the circuit-breaker is OFF and ready to be switched. If, for example, there is a 100% DF signal at the closing release and the circuit-breaker interlock is then removed, the circuit-breaker will not switch ON. However, this can be ensured automatically by connecting it in series with an LCS auxiliary contact.

### Design verification as per IEC/EN 61439

Technical data for design verification			
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	70

### Technical data ETIM 7.0

Low-voltage industrial components (EG000017) / Shunt release (for power circuit breaker) (EC001023)			
Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Full load current trip (ecl@ss10.0.1-27-37-04-18 [AKF016013])			
Rated control supply voltage $U_s$ at AC 50HZ		V	0 - 0
Rated control supply voltage $U_s$ at AC 60HZ		V	0 - 0
Rated control supply voltage $U_s$ at DC		V	24 - 24
Voltage type for actuating			DC
Voltage type for actuating			DC
Initial value of the undelayed short-circuit release - setting range		A	0
End value adjustment range undelayed short-circuit release		A	0
Type of electric connection			Flat plug-in connection
Number of contacts as normally open contact			0
Number of contacts as normally closed contact			0
Number of contacts as change-over contact			0
Suitable for power circuit breaker			Yes
Suitable for off-load switch			Yes
Suitable for motor safety switch			No
Suitable for overload relay			No