Transformer-protective circuit-breaker, 3p, Ir=4-6.3A, screw connection



Part no. PKZM0-6,3-T

088915

EL Number 4315158

(Norway)

(Norway)	
General specifications	
Product name	Eaton Moeller® series PKZM0 Transformer-protective circuit-breaker
Part no.	PKZM0-6,3-T
EAN	4015080889151
Product Length/Depth	76 millimetre
Product height	93 millimetre
Product width	45 millimetre
Product weight	0.293 kilogram
Certifications	IEC/EN 60947 VDE 0660
Product Tradename	PKZM0
Product Type	Transformer-protective circuit-breaker
Product Sub Type	None
Catalog Notes	IE3-ready devices are identified by the logo on their packaging.
Features & Functions	
Actuator type	Turn button
Features	Phase-failure sensitivity (according to IEC/EN 60947-4-1, VDE 0660 Part 102) Complete device with protection unit
Fitted with:	Switched-off indicator
Functions	Transformer protection For the protection of transformers with a high inrush current
Number of poles	Three-pole
General information	
Connection	Screw terminals
Degree of protection	Terminals: IP00 IP20
Lifespan, electrical	100,000 operations
Lifespan, mechanical	100,000 Operations
Mounting position	Can be snapped on to IEC/EN 60715 top-hat rail with 7.5 or 15 mm height.
Operating frequency	40 Operations/h
Overvoltage category	III
Pollution degree	3
Product category	Transformer protective circuit breaker
Protection	Finger and back-of-hand proof, Protection against direct contact when actuated from front (EN 50274)
Rated impulse withstand voltage (Uimp)	6000 V AC
Shock resistance	25 g, Mechanical, according to IEC/EN 60068-2-27, Half-sinusoidal shock 10 ms
Suitable for	Also motors with efficiency class IE3 DIN rail (top hat rail) mounting
Temperature compensation	≤ 0.25 %/K, residual error for T > 40° -5 - 40 °C to IEC/EN 60947, VDE 0660 -25 - 55 °C, Operating range
Climatic environmental conditions	
Altitude	Max. 2000 m
Ambient operating temperature - min	-25 °C
Ambient operating temperature - max	55 °C
Ambient operating temperature (enclosed) - min	25 °C
Ambient operating temperature (enclosed) - max	40 °C
Ambient storage temperature - min	40 °C
Ambient storage temperature - max	80 °C
Climatic proofing	Damp heat, cyclic, to IEC 60068-2-30

	Damp heat, constant, to IEC 60068-2-78
Terminal capacities	
Terminal capacity (flexible with ferrule)	1 x (1 - 6) mm ² , ferrule to DIN 46228
	2 x (1 - 6) mm², ferrule to DIN 46228
Terminal capacity (solid)	2 x (1 - 6) mm ² 1 x (1 - 6) mm ²
Terminal capacity (solid/stranded AWG)	18 - 10
Stripping length (main cable)	10 mm
Tightening torque	1.7 Nm, Screw terminals, Main cable 1 Nm, Screw terminals, Control circuit cables
Electrical rating	
Rated frequency - min	50 Hz
Rated frequency - max	60 Hz
Rated operational current (Ie)	6.3 A
Rated operational voltage (Ue) - min	690 V
Rated operational voltage (Ue) - max	690 V
Rated uninterrupted current (Iu)	6.3 A
Short-circuit rating	
Rated short-circuit breaking capacity Icu at 400 V AC	150 kA
Rated short-circuit breaking capacity Ics at 400 V AC	150 kA
Rated short-circuit breaking capacity Icu at 440 V AC	150 kA
Rated short-circuit breaking capacity Ics at 440 V AC	150 kA
Rated short-circuit breaking capacity Icu at 500 V AC	42 kA
Rated short-circuit breaking capacity Ics at 500 V AC	42 kA
Rated short-circuit breaking capacity Icu at 690 V AC	3 kA
Rated short-circuit breaking capacity Ics at 690 V AC	2 kA
Short-circuit current	60 kA DC, up to 250 V DC, Main conducting paths
Short-circuit release	± 20% tolerance, Trip blocks 141 A, Irm, Setting range max. Basic device, fixed 20 x Iu, Trip Blocks
Switching capacity	
Switching capacity	6.3 A, AC-3 up to 690 V 6.3 A (3 contacts in series), DC-5 up to 250V
Contacts	
Number of auxiliary contacts (change-over contacts)	0
Number of auxiliary contacts (normally closed contacts)	0
Number of auxiliary contacts (normally open contacts)	0
Trip blocks	
Overload release current setting - min	4 A
Overload release current setting - max	6.3 A
Design verification	
Equipment heat dissipation, current-dependent Pvid	4.94 W
Heat dissipation capacity Pdiss	0 W
Heat dissipation per pole, current-dependent Pvid	1.65 W
Rated operational current for specified heat dissipation (In)	6.3 A
Static heat dissipation, non-current-dependent Pvs	0 W
10.2.2 Corrosion resistance	Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures	Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat	Meets the product standard's requirements.
10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects	Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation	Meets the product standard's requirements.
10.2.5 Lifting	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions	Meets the product standard's requirements.
10.3 Degree of protection of assemblies	Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances	Meets the product standard's requirements.
10.5 Protection against electric shock	Does not apply, since the entire switchgear needs to be evaluated.

10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 9.0

Low-voltage industrial components (EG000017) / Power circuit-breaker for trafo/generator/installation protection (EC000228)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Circuit breaker for power transformer, generator and system protection (ecl@ss13-27-37-04-09 [AJZ716018])

Rated voltage Rated short-circuit breaking capacity lou at 400 V, 50 Hz Overload release current setting Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit release Adjustment range und			
Rated short-circuit breaking capacity lou at 400 V, 50 Hz Overload release current setting Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit release Adjustment range undelayed short-circuit release Al 141-141 Power loss Wu 4,94 Device construction Integrated earth fault protection Type of electrical connection of main circuit Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact With switched-off indicator With switched-off indicator With integrated under voltage release Noin Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit	Rated permanent current lu	Α	6.3
Overload release current setting Al 4-6.3 Adjustment range short-term delayed short-circuit release Al 0-0 Adjustment range undelayed short-circuit release Al 141-141 Power loss Built-in device fixed built-in technique Built-in device fixed b	Rated voltage	V	690 - 690
Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit release Adjustment range undelayed short-circuit release Power loss Built-in device fixed built-in technique Device construction Integrated earth fault protection Type of electrical connection of main circuit Suitable for DIN rail (top hat rail) mounting IN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact With switched-off indicator With switched-off indicator Number of poles Number of poles Position of connection for main current circuit Complete device with protection unit A	Rated short-circuit breaking capacity Icu at 400 V, 50 Hz	kA	150
Adjustment range undelayed short-circuit release Power loss W 4.94 Device construction Device construction Integrated earth fault protection Type of electrical connection of main circuit Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact Vith integrated under voltage release With integrated under voltage release Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit	Overload release current setting	Α	4 - 6.3
Power loss Device construction Device construc	Adjustment range short-term delayed short-circuit release	Α	0 - 0
Device construction Integrated earth fault protection Type of electrical connection of main circuit Suitable for DIN rail (top hat rail) mounting Ves DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact With switched-off indicator With integrated under voltage release Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit	Adjustment range undelayed short-circuit release	Α	141 - 141
Integrated earth fault protection Type of electrical connection of main circuit Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Vith switched-off indicator With integrated under voltage release Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit	Power loss	W	4.94
Type of electrical connection of main circuit Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of pulcator With switched-off indicator With integrated under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Yes	Device construction		Built-in device fixed built-in technique
Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact With switched-off indicator With integrated under voltage release With integrated under voltage release No Number of connection for main current circuit Type of control element Complete device with protection unit Yes Yes Yes No Other Turn button Turn button Yes	Integrated earth fault protection		No
DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact Ves With switched-off indicator With integrated under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Yes Yes Yes Yes Yes Yes Yes Ye	Type of electrical connection of main circuit		Screw connection
Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact Number of indicator Number of poles No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Number of auxiliary contacts as normally closed contact O O O O Number of auxiliary contacts as normally open contact No O O Number of auxiliary contacts as normally open contact O O Ves	Suitable for DIN rail (top hat rail) mounting		Yes
Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact With switched-off indicator With integrated under voltage release With integrated under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit O O O O O O O O O O O O O	DIN rail (top hat rail) mounting optional		Yes
Number of auxiliary contacts as change-over contact With switched-off indicator With integrated under voltage release With integrated under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit O O O O O O O O O O O O O	Number of auxiliary contacts as normally closed contact		0
With switched-off indicator With integrated under voltage release With integrated under voltage release No Number of poles Socition of connection for main current circuit Type of control element Complete device with protection unit Yes No Other Turn button Yes	Number of auxiliary contacts as normally open contact		0
With integrated under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit No Other Turn button Yes	Number of auxiliary contacts as change-over contact		0
Number of poles 3 3 Position of connection for main current circuit 0ther Type of control element 1cmplete device with protection unit 1cmplete device with 1cmplete with 1cmplete with 1cmplete with	With switched-off indicator		Yes
Position of connection for main current circuit Type of control element Complete device with protection unit Other Turn button Yes	With integrated under voltage release		No
Type of control element Complete device with protection unit Turn button Yes	Number of poles		3
Complete device with protection unit Yes	Position of connection for main current circuit		Other
	Type of control element		Turn button
Motor drive integrated No	Complete device with protection unit		Yes
	Motor drive integrated		No
Motor drive optional No	Motor drive optional		No
Degree of protection (IP) IP20	Degree of protection (IP)		IP20