Drive, on rear, 3p, lockable





Eaton Moeller series NZM operating element accessory
NZM2-XRAV
4015081070206
184 millimetre
165 millimetre
136 millimetre
0.94 kilogram
IEC UL/CSA RoHS conform
IEC60947 UL (Category Control Number DIHS) CSA certified CSA-C22.2 No. 5-09 CSA (Class No. 1437-01) UL listed UL (File No. E140305) CSA (File No. 22086) UL489 CE marking
NZM
Accessories
Operating element accessory
Accessory On rear drive
Lockable
For direct rear connection of the switch to the side of the control panel or control panel door. Switch actuation on rear through side plate or control panel door. For switch with toggle lever
NZM2
Padlock
Power circuit breaker Switch disconnector
NZM2, N2, NS2, PN2
Black
IP66 4X. 12
Lockable on the 0 position on the handle using up to 3 padlocks
For direct rear connection of the switch to the side of the control panel or control panel door. Switch actuation on rear through side plate or control panel door. For switch with toggle lever
Meets the product standard's requirements.
Does not apply, since the entire switchgear needs to be evaluated.
Does not apply, since the entire switchgear needs to be evaluated.
Meets the product standard's requirements.
Does not apply, since the entire switchgear needs to be evaluated.
•
Meets the product standard's requirements.

10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must b observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must b observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 9.0

Low-voltage industrial compone	ents (EG000017) / Handle for	power circuit breaker	(EC000229)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Handle for switch devices (ecl@ss13-27-37-04-14 [AKF012019])

Electric diginating, datamation, process contain diginating flow voltage switch technology / of our treatment (LV \ 1 kV)/ manual of switch devices (colession 27 or of 14 [Art 012013])		
With restart blockage	No	
With key lock	No	
Padlock locking	Yes	
Colour	Black	
Suitable for emergency stop	No	
With extension shaft	No	
Suitable for power circuit breaker	Yes	
Suitable for switch disconnector	Yes	
Degree of protection (NEMA)	4X, 12	