

Control transformer, 0.2 kVA, Rated input voltage 208 – 600 V, Rated output voltage 2 x 115 V

Part no. **UT10,2-115**
206924

General specifications	
Product name	Eaton Moeller® series UTI Control transformer
Part no.	UT10,2-115
EAN	4015082069247
Product Length/Depth	82 millimetre
Product height	112 millimetre
Product width	106 millimetre
Product weight	3 kilogram
Certifications	UL File No.: E167225 VDE 0570 Part 2-2/2-6 (safety transformer) UL Category Control No.: XPTQ2, XPTQ8 CSA-C22.2 No. 66 UL Recognized VDE 0570 Part 2-4 (isolating transformer) CSA-C22.2 No. 66.1-06 UL 5085-2 VDE 0550 UL 506 UL report applies to both US and Canada IEC/EN 61558-2-2 IEC/EN 60204-1, ÖVE-EN 13 Certified by UL for use in Canada CSA-C22.2 No. 66.2-06 CE UL5085-1 IEC/EN 61558-2-2/2-4/2-6 VDE 0113, VDE 0100 Part 410
Product Tradename	UTI
Product Type	Control transformer
Product Sub Type	None
Catalog Notes	Electrical characteristics: all details for no-load loss, short-circuit loss (copper losses), short-circuit voltage and efficiency values relate to a temperature of 20 °C
Features & Functions	
Features	Reinforced insulation Separate windings Fully Vacuum-impregnated
General information	
Ambient operating temperature - min	-25 °C
Ambient operating temperature - max	40 °C
Connection type	Terminations
Degree of protection	IP00
Duty factor	100 %
Insulation class	B
Primary tapping	± 20 %
Product category	Single-phase UTI multi-winding transformers
Suitable for	Branch circuits, (UL/CSA)
Electrical rating	
Efficiency	87.3 %
No-load losses	10 W
Rated frequency - min	50 Hz
Rated frequency - max	60 Hz
Rated power	0.2 V-A
Relative short-circuit voltage	6.5 %
Short-circuit losses	19 W
Voltage rating - max	600 V
Design verification	

Equipment heat dissipation, current-dependent Pvid		0 W
Heat dissipation capacity Pdis		0 W
Heat dissipation per pole, current-dependent Pvid		0 W
Rated operational current for specified heat dissipation (In)		0 A
Static heat dissipation, non-current-dependent Pvs		29 W
10.2.2 Corrosion resistance		Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures		Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat		Meets the product standard's requirements.
10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects		Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation		Meets the product standard's requirements.
10.2.5 Lifting		Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact		Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions		Meets the product standard's requirements.
10.3 Degree of protection of assemblies		Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances		Meets the product standard's requirements.
10.5 Protection against electric shock		Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components		Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections		Is the panel builder's responsibility.
10.8 Connections for external conductors		Is the panel builder's responsibility.
10.9.2 Power-frequency electric strength		Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage		Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material		Is the panel builder's responsibility.
10.10 Temperature rise		The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating		Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility		Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function		The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 9.0

Low-voltage industrial components (EG000017) / One-phase control transformer (EC002486)		
Electric engineering, automation, process control engineering / Transformer, converter, coil / Control transformer / One-phase control transformer (ec @ss13-27-03-13-02 [AAB620020])		
Built as safety transformer		Yes
Built as isolating transformer		Yes
Built as energy saving transformer		No
Primary voltage 1	V	208 - 600
Primary voltage 2	V	0 - 0
Primary voltage 3	V	0 - 0
Primary voltage 4	V	0 - 0
Primary voltage 5	V	0 - 0
Primary voltage 6	V	0 - 0
Primary voltage 7	V	0 - 0
Primary voltage 8	V	0 - 0
Primary voltage 9	V	0 - 0
Primary voltage 10	V	0 - 0
Secondary voltage 1	V	115 - 115
Secondary voltage 2	V	115 - 115
Secondary voltage 3	V	0 - 0
Secondary voltage 4	V	0 - 0
Secondary voltage 5	V	0 - 0
Secondary voltage 6	V	0 - 0
Secondary voltage 7	V	0 - 0
Secondary voltage 8	V	0 - 0
Secondary voltage 9	V	0 - 0
Secondary voltage 10	V	0 - 0

Rated apparent power	VA	200
Power	W	
Power consumption in standby mode	W	24
Type of insulation material according to IEC 85		B
Short-circuit-proof		No
Relative short circuit voltage	%	6.5
Width	mm	106
Height	mm	112
Depth	mm	82
Degree of protection (IP)		IP00
Ring core		No
Suitable for mounting on PCB		No
Modular version		No
Conductor material		Copper