



**Signalling switch ON-OFF, 2W**

**Part no.** IZMX-AS22-40  
**Catalog No.** 156599  
**Alternate Catalog No.** NRXAUXKIT2  
**EL-Nummer (Norway)** 0004357773

**Delivery program**

|                     |  |  |   |
|---------------------|--|--|---|
| Product range       |  |  | Accessories   |
| Accessories         |  |  | Auxiliary contact   |
| Accessories         |  |  | Standard auxiliary switch for On-Off signaling  |
|                     |  |  | Standard auxiliary switch for On-Off signaling.<br>The basic device already contains two changeover contacts.<br>Two additional changeover contacts possible.   |
| For use with        |  |  | IZMX40...<br>INX40...   |
| <b>Instructions</b> |  |  | Retrofit kit for IZMX40 circuit-breakers<br>For retrofitting, three additional control circuit terminal units are required.<br>For fixed mounting circuit-breakers → #156593 and withdrawable unit circuit-breakers → #156590 |
|                     |  |  | 2 changeover contacts   |

**Technical data**

**Rated breaking capacity**

|                |  |   |      |
|----------------|--|---|------|
| Inductive load |  |   |      |
| 250 V AC       |  | A | 10   |
| 125 V DC       |  | A | 0.5  |
| 250 V DC       |  | A | 0.25 |

**Design verification as per IEC/EN 61439**

|  |  |    |     |
|--|--|----|-----|
| Technical data for design verification |  |    |     |
| Operating ambient temperature min.     |  | °C | -25 |
| Operating ambient temperature max.     |  | °C | 70  |

**Technical data ETIM 7.0**

|  |  |   |                         |
|--|--|---|-------------------------|
| Low-voltage industrial components (EG000017) / Auxiliary contact block (EC000041)  |  |   |                         |
| Electric engineering, automation, process control engineering / Low-voltage switch technology / Component for low-voltage switching technology / Auxiliary switch block (ecl@ss10.0.1-27-37-13-02 [AKN342013]) |  |   |                         |
| Number of contacts as change-over contact  |  |   | 2                       |
| Number of contacts as normally open contact  |  |   | 0                       |
| Number of contacts as normally closed contact  |  |   | 0                       |
| Number of fault-signal switches  |  |   |                         |
| Rated operation current I <sub>e</sub> at AC-15, 230 V   |  | A | 10                      |
| Type of electric connection  |  |   | Flat plug-in connection |
| Model  |  |   | Integrable              |
| Mounting method  |  |   | Other                   |
| Lamp holder  |  |   |                         |