



Undervoltage release, 60 V DC

Part no. NZM2/3-XU60DC
Catalog No. 259513

Similar to illustration

Delivery program

| | | | |
|-----------------------|-------|---|---|
| Product range | | | Accessories |
| Accessories | | | Undervoltage release |
| Accessories | | | Undervoltage releases |
| Standard/Approval | | | UL/CSA, IEC |
| Construction size | | | NZM2/3 |
| Description | | | Non-delayed disconnection of NZM circuit-breaker or N switch-disconnector when the control voltage sinks below 35 – 70% U_s . For use with emergency-stop devices in connection with an emergency-stop button. When the under-voltage trip is switched off, accidental contact with the circuit breaker's primary contacts is prevented when switched on. Undervoltage releases cannot be installed simultaneously with NZM...-XHIV... early-make auxiliary contact or NZM...-XA... shunt release. |
| Connection type | | | With bolt connection |
| Auxiliary contacts | | | without auxiliary contact |
| Rated control voltage | U_s | V | 60 V DC |
| For use with | | | NZM2(-4), N2(-4) NZM3(-4), N3(-4) |

Technical data

Undervoltage release

| | | | |
|-----------------------|-------|---|---------|
| Rated control voltage | U_s | V | |
| Rated control voltage | U_s | V | 60 V DC |

Design verification as per IEC/EN 61439

| | | | |
|--|--|--|--|
| IEC/EN 61439 design verification | | | |
| 10.2 Strength of materials and parts | | | |
| 10.2.2 Corrosion resistance | | | Meets the product standard's requirements. |
| 10.2.3.1 Verification of thermal stability of enclosures | | | Meets the product standard's requirements. |
| 10.2.3.2 Verification of resistance of insulating materials to normal heat | | | Meets the product standard's requirements. |
| 10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects | | | Meets the product standard's requirements. |
| 10.2.4 Resistance to ultra-violet (UV) radiation | | | Meets the product standard's requirements. |
| 10.2.5 Lifting | | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.2.6 Mechanical impact | | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.2.7 Inscriptions | | | Meets the product standard's requirements. |
| 10.3 Degree of protection of ASSEMBLIES | | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.4 Clearances and creepage distances | | | Meets the product standard's requirements. |
| 10.5 Protection against electric shock | | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.6 Incorporation of switching devices and components | | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.7 Internal electrical circuits and connections | | | Is the panel builder's responsibility. |
| 10.8 Connections for external conductors | | | Is the panel builder's responsibility. |
| 10.9 Insulation properties | | | |
| 10.9.2 Power-frequency electric strength | | | Is the panel builder's responsibility. |
| 10.9.3 Impulse withstand voltage | | | Is the panel builder's responsibility. |

| | | | |
|--|--|--|--|
| 10.9.4 Testing of enclosures made of insulating material | | | Is the panel builder's responsibility. |
| 10.10 Temperature rise | | | The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. |
| 10.11 Short-circuit rating | | | Is the panel builder's responsibility. The specifications for the switchgear must be observed. |
| 10.12 Electromagnetic compatibility | | | Is the panel builder's responsibility. The specifications for the switchgear must be observed. |
| 10.13 Mechanical function | | | The device meets the requirements, provided the information in the instruction leaflet (IL) is observed. |

Technical data ETIM 7.0

| | | | |
|--|---|--|------------------|
| Low-voltage industrial components (EG000017) / Under voltage coil (EC001022) | | | |
| Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Undervoltage trip (ecl@ss10.0.1-27-37-04-17 [AKF015013]) | | | |
| Rated control supply voltage Us at AC 50HZ | V | | 0 - 0 |
| Rated control supply voltage Us at AC 60HZ | V | | 0 - 0 |
| Rated control supply voltage Us at DC | V | | 60 - 60 |
| Voltage type for actuating | | | DC |
| Type of electric connection | | | Screw connection |
| Number of contacts as normally open contact | | | 0 |
| Number of contacts as normally closed contact | | | 0 |
| Number of contacts as change-over contact | | | 0 |
| Delayed | | | No |
| Suitable for power circuit breaker | | | Yes |
| Suitable for off-load switch | | | Yes |
| Suitable for motor safety switch | | | No |
| Suitable for overload relay | | | No |

Approvals

| | | | |
|-----------------------------|--|--|---|
| Product Standards | | | UL489; CSA-C22.2 No. 5-09; IEC60947, CE marking |
| UL File No. | | | E140305 |
| UL Category Control No. | | | DIHS |
| CSA File No. | | | 022086 |
| CSA Class No. | | | 1437-01 |
| North America Certification | | | UL listed, CSA certified |