



PE-(PEN-) rail for fuse enclosure

**Part no.** PEN43RS18  
**Catalog No.** 070108

**EL-Nummer (Norway)** 0002502282

**Delivery program**

Product range			Ci insulated enclosures
Basic function			Prepared enclosures
Product function			Modular busbar system
Accessories			PE (PEN) busbars
Single unit/Complete unit			Modular system
<b>Conductor cross-section</b>			
Solid		mm <sup>2</sup>	2 x 2.5 - 35 12 x 1.5 - 16
Stranded		mm <sup>2</sup>	2 x 2.5 - 25 12 x 1.5 - 16
For use with			SE-RS-I43 (I44) RS18/I43 (I44)

**Technical data ETIM 7.0**

Energy distribution systems (EG000015) / Rail terminal bar (EC000275)			
Electric engineering, automation, process control engineering / Electrical insulation and connecting material / Energy distribution system / Rail terminal bar clamp (ecI@ss10.0.1-27-40-06-03 [ACO369011])			
Number of poles			1
Nominal current		A	63
Connection type			Screwing
Mounting method			Screw
Number of connections total			14
Number of connections < 6 mm <sup>2</sup>			0
Number of connections 10 mm <sup>2</sup>			0
Number of connections 16 mm <sup>2</sup>			12
Number of connections 25 mm <sup>2</sup>			0
Number of connections > 25 mm <sup>2</sup>			2
Number of connections < AWG 6			0
Number of connections AWG 6			0
Number of connections AWG 4			0
Number of connections AWG 2			0
Number of connections AWG 4/0			0
Number of connections 250 kcmil			0
Number of connections > 250 kcmil			0
Contact safe			Yes
Height		mm	0
Width		mm	300
Depth		mm	50

**Additional product information (links)**

Declaration of conformity	<a href="https://es-assets.eaton.com/DOCUMENTATION/PDF/ci_ce.pdf">https://es-assets.eaton.com/DOCUMENTATION/PDF/ci_ce.pdf</a>
allowInterrupt=1&RevisionSelectionMethod=LatestReleased&noSaveAs=0&RenderModelCertification xEnergy Safety Ci	<a href="http://www.eaton.eu/DE/ecm/idcplg?IdcService=GET_FILE&amp;model certification xEnergy Safety Ci">http://www.eaton.eu/DE/ecm/idcplg?IdcService=GET_FILE&amp;model certification xEnergy Safety Ci</a>
allowInterrupt=1&RevisionSelectionMethod=LatestReleased&noSaveAs=0&RenderSave time – we assist you with expert pre-assembly	<a href="http://www.eaton.eu/DE/ecm/idcplg?IdcService=GET_FILE&amp;Save time – we assist you with expert pre-assembly">http://www.eaton.eu/DE/ecm/idcplg?IdcService=GET_FILE&amp;Save time – we assist you with expert pre-assembly</a>
allowInterrupt=1&RevisionSelectionMethod=LatestReleased&noSaveAs=0&Render product information xEnergy Safety Ci	<a href="http://www.eaton.eu/DE/ecm/idcplg?IdcService=GET_FILE&amp;product information xEnergy Safety Ci">http://www.eaton.eu/DE/ecm/idcplg?IdcService=GET_FILE&amp;product information xEnergy Safety Ci</a>

tool for calculating the power loss for switching device combinations	<a href="http://www.eaton.eu/DE/Europe/Electrical/CustomerSupport/ConfigurationTools/TCool/index.htm">http://www.eaton.eu/DE/Europe/Electrical/CustomerSupport/ConfigurationTools/TCool/index.htm</a>
configurator - xEnergy family	<a href="http://www.eaton.eu/DE/Europe/Electrical/CustomerSupport/ConfigurationTools/xEnergyMainSupport/index.htm">http://www.eaton.eu/DE/Europe/Electrical/CustomerSupport/ConfigurationTools/xEnergyMainSupport/index.htm</a>