

Control transformer, 0.8 kVA, Rated input voltage 208 – 600 V, Rated output voltage 2 x 115 V



**Part no. UTI0,8-115
206928**

General specifications		
Product name		Eaton Moeller® series UTI Control transformer
Part no.		UTI0,8-115
EAN		4015082069285
Product Length/Depth		124 millimetre
Product height		150 millimetre
Product width		151 millimetre
Product weight		9.6 kilogram
Compliances		CE Marked
Certifications		VDE VDE 0113, VDE 0100 Part 410 IEC/EN 61558-2-2/2-4/2-6 UL Category Control No.: XPTQ2, XPTQ8 CE VDE 0550 VDE 0570 Part 2-4 (isolating transformer) CSA-C22.2 No. 66.2-06 UL report applies to both US and Canada UL5085-1 UL 5085-2 Certified by UL for use in Canada IEC/EN 60204-1, ÖVE-EN 13 UL 506 VDE 0570 Part 2-2/2-6 (safety transformer) CSA-C22.2 No. 66 UL File No.: E167225 UL Recognized IEC/EN 61558-2-2 CSA-C22.2 No. 66.1-06
Product Tradename		UTI
Product Type		Control transformer
Product Sub Type		None
Catalog Notes		Electrical characteristics: all details for no-load loss, short-circuit loss (copper losses), short-circuit voltage and efficiency values relate to a temperature of 20 °C
Features & Functions		
Features		Separate windings Fully Vacuum-impregnated Reinforced insulation
General information		
Ambient operating temperature - min		-25 °C
Ambient operating temperature - max		40 °C
Connection type		Terminations
Degree of protection		IP00
Duty factor		100 %
Insulation class		B
Primary tapping		± 20 %
Product category		Single-phase UTI multi-winding transformers
Suitable for		Branch circuits, (UL/CSA)
Electrical rating		
Efficiency		92.8 %
No-load losses		33 W
Rated frequency - min		50 Hz
Rated frequency - max		60 Hz
Rated power		0.8 V-A
Relative short-circuit voltage		2.8 %
Short-circuit losses		29 W

Voltage rating - max			600 V
Design verification			
Equipment heat dissipation, current-dependent Pvid			0 W
Heat dissipation capacity Pdis			0 W
Heat dissipation per pole, current-dependent Pvid			0 W
Rated operational current for specified heat dissipation (In)			0 A
Static heat dissipation, non-current-dependent Pvs			62 W
10.2.2 Corrosion resistance			Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures			Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat			Meets the product standard's requirements.
10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects			Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation			Meets the product standard's requirements.
10.2.5 Lifting			Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact			Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions			Meets the product standard's requirements.
10.3 Degree of protection of assemblies			Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances			Meets the product standard's requirements.
10.5 Protection against electric shock			Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components			Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections			Is the panel builder's responsibility.
10.8 Connections for external conductors			Is the panel builder's responsibility.
10.9.2 Power-frequency electric strength			Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage			Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material			Is the panel builder's responsibility.
10.10 Temperature rise			The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating			Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility			Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function			The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 9.0

Low-voltage industrial components (EG000017) / One-phase control transformer (EC002486)			
Electric engineering, automation, process control engineering / Transformer, converter, coil / Control transformer / One-phase control transformer (ecl@ss13-27-03-13-02 [AAB620020])			
Built as safety transformer			Yes
Built as isolating transformer			Yes
Built as energy saving transformer			No
Primary voltage 1		V	208 - 600
Primary voltage 2		V	0 - 0
Primary voltage 3		V	0 - 0
Primary voltage 4		V	0 - 0
Primary voltage 5		V	0 - 0
Primary voltage 6		V	0 - 0
Primary voltage 7		V	0 - 0
Primary voltage 8		V	0 - 0
Primary voltage 9		V	0 - 0
Primary voltage 10		V	0 - 0
Secondary voltage 1		V	115 - 115
Secondary voltage 2		V	115 - 115
Secondary voltage 3		V	0 - 0
Secondary voltage 4		V	0 - 0
Secondary voltage 5		V	0 - 0
Secondary voltage 6		V	0 - 0
Secondary voltage 7		V	0 - 0
Secondary voltage 8		V	0 - 0

Secondary voltage 9	V	0 - 0
Secondary voltage 10	V	0 - 0
Rated apparent power	VA	800
Power	W	
Power consumption in standby mode	W	7
Type of insulation material according to IEC 85		B
Short-circuit-proof		No
Relative short circuit voltage	%	2.8
Width	mm	151
Height	mm	150
Depth	mm	124
Degree of protection (IP)		IP00
Ring core		No
Suitable for mounting on PCB		No
Modular version		No
Conductor material		Copper