



**Motor operator 110-125 VAC/DC**

**Part no.** IZMX-M40-110AD  
**Catalog No.** 124297

**EL-Nummer (Norway)** 0004357403

**Delivery program**

Product range			Accessories
Accessories			Remote switching
Accessories			Motor operator
			DC
Maximum operating frequency	Actuations/ minute		3
			Please note - the circuit-breaker's switching frequency = 60/h
Rated control voltage	$U_s$	V	110 - 127 V AC 50/60 Hz 110 - 125 V DC
Operating range	$x U_s$	Factor	0,85 - 1,1
max. holding current	$I_n$	A	3 AC / 2 DC
max. pick-up current (35ms)	$I_n$	A	9 AC / 7.5 DC
max. continuous power	AC/DC	VA/W	425 AC / 275 DC
max. pull-in power (35ms)	AC/DC	VA/W	3
For use with			IZMX40... INX40...
<b>Instructions</b>			An additional control circuit terminal block is required for retrofitting. For fixed mounting circuit-breakers→#156593 and withdrawable unit circuit-breakers →#156590
Information about equipment supplied			A signaling switch for the labeled "Spring-operated stored energy mechanism tensioned" message is included as standard.

**Technical data**

Necessary time required for charging the spring-operated stored energy mechanism at $1 x U_s$			3 s AC 50/60 Hz 3 s DC
Rated operational current	$I_n$	A	3 A AC 50/60 Hz 2 A DC
Starting current		A	6 A AC 50/60 Hz 8 A DC
Power consumption			450 VA AC 50/60 Hz 200 W DC

**Design verification as per IEC/EN 61439**

Technical data for design verification			
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	70

**Technical data ETIM 7.0**

Low-voltage industrial components (EG000017) / Motor operator for power circuit-breaker (EC001030)			
Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Electrical drive for circuit breakers (ecl@ss10.0.1-27-37-04-12 [AKF010013])			
Type of switch drive			Motor drive
Rated control supply voltage $U_s$ at AC 50HZ		V	110 - 127
Rated control supply voltage $U_s$ at AC 60HZ		V	110 - 127
Rated control supply voltage $U_s$ at DC		V	110 - 125

