#### DATASHEET - M22-XLED60

Series element, 42-60VAC/DC, for LED 12-30V





Part no. M22-XLED60 Catalog No. 231078 Alternate Catalog M22-XLED60Q No. EL-Nummer 4355797 (Norway)

#### **Delivery program**

Derivery program			
Basic function accessories			LED elements
Function			for connecting 12 - 30 V LED elements
Description			LED resistor
Connection technique			Screw terminals
Rated operational voltage	Ue	V	42 60 V AC/DC
Degree of Protection			IP20
Connection to SmartWire-DT			no
Approval			LED
Connection technique			Screw terminals
Notes For pushbutton actuators, indicator lights, illuminated pushbuttons and illuminated selector switch actuators, the following applies: M22R only in combination with M22-LEDR M22G only in combination with M22-LEDG M22W only in combination with M22-LEDW			

M22...-Y only in combination with M22-LED...-W

M22...-B in combination with M22-LED...-W or M22-LED...-B

# Technical data

General		
Degree of Protection		IP20
Ambient temperature		
Open	°C	-25 - +70
Storage	°C	- 40 - + 80

### Design verification as per IEC/EN 61439

I <sub>n</sub>	А	0
P <sub>vid</sub>	W	0
P <sub>vid</sub>	W	0
P <sub>vs</sub>	W	0.5
P <sub>diss</sub>	W	0
	°C	-25
	°C	70
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Meets the product standard's requirements.
	P <sub>vid</sub> P <sub>vid</sub> P <sub>vs</sub> P <sub>diss</sub>	P <sub>vid</sub> W P <sub>vid</sub> W P <sub>vs</sub> W P <sub>diss</sub> W C C C C C C C

10.2.4 Resistance to ultra-violet (UV) radiation	Meets the product standard's requirements.
10.2.5 Lifting	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions	Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances	Meets the product standard's requirements.
10.5 Protection against electric shock	Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9 Insulation properties	
10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

## Technical data ETIM 7.0

Low-voltage industrial components (EG000017) / Accessories for control circuit devices (EC002024)		
Type of electrical accessory	Resistor block	
Type of mechanical accessory	Other	

Approvals	
Product Standards	IEC/EN 60947-5; UL 508; CSA-C22.2 No. 14-05; CSA-C22.2 No. 94-91; CE marking
UL File No.	E29184
UL Category Control No.	NKCR
CSA File No.	012528
CSA Class No.	3211-03
North America Certification	UL listed, CSA certified
Degree of Protection	UL/CSA Type: -

## Dimensions

Pushbutton with M22-(C)K... Pushbutton with M22-(C) LED... + M22-XLED...