DATASHEET - +NZM3-XKCU



Box terminal, 3p, bottom up to 630A

Part no. +NZM3-XKCU Catalog No. 262245

EL-Nummer (Norway)

4315557

Similar to illustration



Delivery program

Delivery program			
Number of conductors			3 pole
Accessories			Box terminal
Rated current	In	Α	≦ 630
For use with			NZM3(-4), PN3(-4), N(S)3(-4)
Mounting position			Fitted at the bottom
Terminal capacities			
Type of conductor			
Cu/Al cable			Cu cable
Terminal capacities			
flexible		mm ²	1 x 35 240 2 x 16 120
AWG/kcmil		mm^2	1 x 2 500
Terminal capacities			
Cu strip (number of segments x width x segment thickness)		mm ²	up to 500 A: min. 6 x 16 x 0.8 max. 10 x 24 x 1.0 Or max. 11 x 21 x 1.0 630 A: 10 x 24 x 1.0 + 5 x 24 x 1.0 oder (2 x) 8 x 24 x 1.0

Notes

Type suffix and type contain parts for a circuit-breaker side at top or bottom for 3 or 4-pole circuit-breakers.

Conversion kit for circuit-breaker with screw connection.

Fitted within the switch housing

0 =for fitting at the top

U = for fitting at the bottom

U_e ≥ 525 V AC:

• Use NZM3(-4)-XKSA cover.

Use with flexible and highly flexible conductors ferrules, note the max. terminal capacity when using ferrules.

Technical data General

Mounting position	Fitted at the bottom

Design verification as per IEC/EN 61439

Meets the product standard's requirements.
Meets the product standard's requirements.
Does not apply, since the entire switchgear needs to be evaluated.
Does not apply, since the entire switchgear needs to be evaluated.
Meets the product standard's requirements.
Does not apply, since the entire switchgear needs to be evaluated.
Meets the product standard's requirements.

10.5 Protection against electric shock	Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9 Insulation properties	
10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (II) is observed

Technical data ETIM 7.0

Low-voltage industrial components (EG000017) / Wiring set for power circuit breaker (EC002050)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Wiring set for circuit breaker (ecl@ss10.0.1-27-37-04-24 [ACN957011])

Suitable for number of poles

Model

Other

Approvals

Product Standards	UL489; CSA-C22.2 No. 5-09; IEC60947, CE marking
UL File No.	E31593
UL Category Control No.	DIHS
CSA File No.	022086
North America Certification	UL listed, CSA certified
Suitable for	Refer to main component information

Dimensions

