DATASHEET - NZM4-XUVHIV

Part no.

Catalog No.

Entropy of the second s

Undervoltage release, 2early N/O, for delay unit

NZM4-XUVHIV 266596



Similar to illustration

Delivery program

Product range	Accessories
Accessories	Undervoltage release
Accessories	Undervoltage release for use with delay unit UVU
Standard/Approval	IEC
Construction size	NZM4
Description	Combination of separate delay unit and special releases. For use with emergency-stop devices in connection with an emergency-stop button. not UL/CSA approved Special releases for combining with separate delay time. UVU-NZM delay unit is additionally required. Cannot be installed simultaneously with separate NZMXHIV early-make auxiliary contact or NZMXA shunt release. Cannot be used in conjunction with NZMXR remote operator. Early make of auxiliary contact on switching on (manual operation): approx. 90 ms.
Connection type	With bolt connection
Auxiliary contacts	with 2 early-make auxiliary contacts
For use with	NZM4(-4) N(S)4(-4)

Technical data

Undervoltage releases, off-delayed

ondorronago rorodoto, on abrajoa			
Rated operational voltage	U _e	V	
	Ue	V DC	18
Terminal capacities		mm ²	
Solid or flexible conductor, with ferrule		mm ²	1 x (0,75 - 2,5) 2 x (0,75 - 2,5)
		AWG	1 x (18 14) 2 x (18 14)

Design verification as per IEC/EN 61439

Meets the product standard's requirements.
Meets the product standard's requirements.
Does not apply, since the entire switchgear needs to be evaluated.
Does not apply, since the entire switchgear needs to be evaluated.
Meets the product standard's requirements.
Does not apply, since the entire switchgear needs to be evaluated.
Meets the product standard's requirements.
Does not apply, since the entire switchgear needs to be evaluated.
Does not apply, since the entire switchgear needs to be evaluated.
Is the panel builder's responsibility.
Is the panel builder's responsibility.

10.9 Insulation properties	
10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 7.0

Low-voltage industrial components (EG000017) / Under voltage coil (EC001022)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Undervoltage trip (ecl@ss10.0.1-27-37-04-17 [AKF015013])				
Rated control supply voltage Us at AC 50HZ	V		0 - 0	
Rated control supply voltage Us at AC 60HZ	V		0 - 0	
Rated control supply voltage Us at DC	V		0 - 0	
Voltage type for actuating			DC	
Type of electric connection			Screw connection	
Number of contacts as normally open contact			1	
Number of contacts as normally closed contact			0	
Number of contacts as change-over contact			0	
Delayed			Yes	
Suitable for power circuit breaker			Yes	
Suitable for off-load switch			Yes	
Suitable for motor safety switch			No	
Suitable for overload relay			No	

Approvals

- PP	
Product Standards	UL489; CSA-C22.2 No. 5-09; IEC60947, CE marking
UL File No.	E140305
UL Category Control No.	DIHS
CSA File No.	022086
CSA Class No.	1437-01
North America Certification	UL listed, CSA certified