



**Automatización Eléctrica**

Especialistas en Automatización

At the end of this document you will find links to products related to this catalog. You can go directly to our shop by clicking [HERE](#)

### General Information

Extended Product Type:	E6H 6300 PR121/P-LI In=6300A 3p W MP
Product ID:	1SDA057024R1
EAN:	8015644583644
Catalog Description:	E6H 6300 PR121/P-LI In=6300A 3p W MP
Long Description:	SACE EMAX MOVING PART FOR CIRCUIT-BREAKER E6H 6300A THREE-POLE OVERCURRENT RELEASE PR121/P-LI R6300 FITTED WITH: 4 AUXILIARY CONTACT AND C.BREAKER IN POSITION OPEN-CLOSED

### Categories

Products » Low Voltage Products and Systems » Circuit Breakers » Air Circuit Breakers » Emax

### Ordering

EAN:	8015644583644
Minimum Order Quantity:	1 piece
Customs Tariff Number:	85362090

### Dimensions

Product Net Width:	810 mm
Product Net Height:	461 mm
Product Net Depth:	396.5 mm
Product Net Weight:	116 kg

### Container Information

Package Level 1 Units:	1 piece
Package Level 1 Width:	51000 mm
Package Level 1 Height:	63000 mm
Package Level 1 Length:	97000 mm
Package Level 1 Gross Weight:	138 kg
Package Level 1 EAN:	8015644583644

### Additional Information

Electrical Durability:	1500 cycle 10 cycles per hour
Mechanical Durability:	12000 cycle 60 cycles per hour
Number of Poles:	3
Power Loss:	at Rated Operating Conditions per Pole 1100 W
Product Main Type:	SACE Emax
Product Name:	Automatic Circuit Breaker
Product Type:	CBMP
Rated Current ( $I_n$ ):	6300 A
Rated Impulse Withstand Voltage ( $U_{imp}$ ):	12 kV
Rated Insulation Voltage ( $U_i$ ):	1000 V
Rated Operational Current ( $I_e$ ):	6300 A
Rated Operational Voltage:	690 V AC
Rated Service Short-Circuit Breaking Capacity ( $I_{cs}$ ):	(220 V AC) 100 kA (230 V AC) 100 kA (380 V AC) 100 kA (400 V AC) 100 kA (415 V AC) 100 kA (440 V AC) 100 kA (500 V AC) 100 kA (660 V AC) 100 kA (690 V AC) 100 kA
Rated Short-time Withstand Current ( $I_{cw}$ ):	for 1 s 100 kA for 3 s 100 kA
Rated Ultimate Short-Circuit Breaking Capacity ( $I_{cu}$ ):	(220 V AC) 100 kA (230 V AC) 100 kA (380 V AC) 100 kA (400 V AC) 100 kA (415 V AC) 100 kA (440 V AC) 100 kA (500 V AC) 100 kA

(525 V AC) 100 kA  
(660 V AC) 100 kA  
(690 V AC) 100 kA

<b>Rated Uninterrupted Current (I<sub>u</sub>):</b>	6300 A
<b>Rated Voltage (U<sub>r</sub>):</b>	690 V
<b>Release Type:</b>	EL
<b>Standards:</b>	IEC 60947
<b>Sub-type:</b>	E6
<b>Terminal Connection Type:</b>	Withdrawable Circuit-Breakers
<b>Version:</b>	W

### Certificates and Declarations (Document Number)

<b>Data Sheet, Technical Information:</b>	1SDC200006D0209
<b>Declaration of Conformity - CE:</b>	1SDL000165R0017

### Classifications

<b>ETIM 4:</b>	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
<b>ETIM 5:</b>	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
<b>Object Classification Code:</b>	Q





Below is a list of articles with direct links to our shop Electric Automation Network where you can see:

- Quote per purchase volume in real time.
- Online documentation and datasheets of all products.
- Estimated delivery time enquiry in real time.
- Logistics systems for the shipment of materials almost anywhere in the world.
- Purchasing management, order record and tracking of shipments.

To access the product, [click on the green button.](#)

<b>Product</b>	<b>Code</b>	<b>Reference</b>	<b>Product link</b>
E6H 6300 PR121/P-LI In=6300A 3p W MP	1SDA057024R1	E6H6300	<a href="#">Buy on EAN</a>