



Automatización Eléctrica
Especialistas en Automatización

At the end of this document you will find links to products related to this catalog. You can go directly to our shop by clicking HERE. [HERE](#)

VLT® Advanced Active Filter AAF 006

A flexible and adaptable solution for central or de-central harmonic mitigation.



E-frame

Danfoss Advanced Active Filters can compensate for individual VLT® drives or can be installed as a compact stand-alone solution at a common point of coupling, compensating for several loads simultaneously.

Consequently the filter ensures optimal harmonic suppression independent of the number of loads and their individual load profile. In addition the active filter corrects the power factor and balances the phase load providing an optimal energy utilization.

This improves the system efficiency and increases the grid robustness to avoid downtime.

The extensive re-use of proven VLT® components and the modular construction ensures a high reliability and at the same time offers high energy efficiency, back-channel cooling and high enclosure grades without size encrease.

The VLT® Advanced Active Filter is easily controlled via the user-friendly LCP, sharing design and programming structure with the VLT® drives series.

Without dismounting existing installation, the VLT® Advanced Active Filters are easily retrofitted to the existing installation, where harmonics are increased because of enlarged employment of non-linear loads such as variable speed drives.

Voltage range

380 – 480 V AC 50 – 60 Hz

Current range

190 A, 250 A, 310 A, 400 A.

Up to 4 units can be paralleled for higher power.

Enclosure degree

- IP 21/NEMA Type 1
- IP 54/NEMA Type 12

Perfect

match for:

- Industrial automation
- High dynamic applications
- Safety installations

Feature	Benefit
Reliable	Maximum uptime
<ul style="list-style-type: none"> – 100% factory tested – Coated PCBs – >90% components re-used from proven VLT® FC series 	<ul style="list-style-type: none"> – Low failure rate
<ul style="list-style-type: none"> – Innovative cooling concept 	<ul style="list-style-type: none"> – Prolonged lifetime of electronics
User-friendly and flexible	Saves commissioning and operating cost
<ul style="list-style-type: none"> – Innovative programming possibilities – Modular design 	<ul style="list-style-type: none"> – Low running expenses – Easy serviceability
<ul style="list-style-type: none"> – Wide range of options 	<ul style="list-style-type: none"> – Low initial investment – High degree of customisation
Energy saving	Lower operation costs
<ul style="list-style-type: none"> – High efficiency – Sleep mode and progressive switching freq. – Power factor correction 	<ul style="list-style-type: none"> – Low running expenses

Options

The following options are available:

- RFI filters
- Disconnect
- Fuses
- Mains shielding

PC software

VLT® MCT 10 Setup Software

VLT® MCT 10 offers advanced programming functionality for all Danfoss drive products, greatly reducing programming and set-up time.

VLT® MCT 10 Basic (available free of charge from www.danfoss.com) allows access to a finite number of drives with limited functionality. The advanced edition, offering a higher level of functionality, is available from your Danfoss sales partner.

VLT® MCT 31 Harmonics Calculation Software

With VLT® MCT 31, you can determine whether harmonics will be an issue in your installation when drives are added.

VLT® MCT 31 estimates the benefits of adding various harmonic mitigation solutions from the Danfoss product portfolio and calculates system harmonic distortion. Furthermore the software provides quick indication of whether the installation complies with the most recognised harmonic norms and recommendations.

From www.danfoss.com you can download the free tool VLT® Harmonic Calculation MCT 31 – the most up-to-date version of the calculation software.

Specifications

THiD* at:	
– 40% load	< 7%
– 70% load	< 5.5%
– 100% load	< 5%
Efficiency* at:	
– 40% load	> 95%
– 70% load	> 98%
– 100% load	> 98%
True power factor* at:	
– 40% load	> 0.98
– 70% load	> 0.98
– 100% load	> 0.98
Ambient temperature	45° C
Cooling	Back-channel air cooling

* Measured at balanced grid without pre-distortion and with VLT® drive matching full load demand

Norms and recommendations	Compliance
IEEE519	Application and load dependent
IEC61000-3-2 (up to 16 A)	Out of scope
IEC61000-3-12 (between 16 and 75 A)	Out of scope
IEC61000-3-4 (above 75 A)	Out of scope



400 V AC (380 – 480 V AC)					
Total Current [A]	Max. Reactive [A]	Max. Harmonic [A]	Frame	Dimensions H x W x D mm [Inches]	Weight Kg [Lbs]
190	190	170	D14	1740 x 600 x 380 [68.2 x 33.5 x 15.0]	283 [623]
250	250	225	E1	2000 x 600 x 500 [78.7 x 33.5 x 19.4]	476 [1047]
310	310	280			498 [1096]
400	400	360			

Total Current [A]	Max. individual harmonic compensation [A]							
	I ₅	I ₇	I ₁₁	I ₁₃	I ₁₇	I ₁₉	I ₂₃	I ₂₅
190	119	85	55	48	34	31	27	24
250	158	113	72	63	45	40	36	32
310	196	140	90	78	56	50	45	40
400	252	180	115	100	72	65	58	50

Below is a list of articles with direct links to our shop Electric Automation Network where you can see:

- Quote per purchase volume in real time.
- Online documentation and datasheets of all products.
- Estimated delivery time enquiry in real time.
- Logistics systems for the shipment of materials almost anywhere in the world.
- Purchasing management, order record and tracking of shipments.

To access the product, click on the green button.

Product	Code	Reference	Product link
Advanced Active Filter 380-480 VAC, 250Amp correction, IP21 / With mains shield, RFI class A1, Mains Disconnect + fuse AAF006A250T4E2MH4XGC3XXSXXXXAXBXCFXXDX0	131Z5578		Buy on EAN
Advanced Active Filter 380-480 VAC, 400Amp correction, IP54 / Type 12, RFI Class A2, Fuse AAF006A400T4E54H2XGC7XXSXXXXAXBXCFXXDX	131Z9450		Buy on EAN
Advanced Active Filter 380-480 VAC, 400Amp correction, IP54/Type12+mains shield, RFI class A1, Mains Disconnect + fuse AAF006A400T4E5MH4XGC3XXSXXXXAXBXCFXXDX	131Z9841		Buy on EAN
Advanced Active Filter 380-480 VAC, 400Amp correction, IP54 / Type 12, RFI class A1, Mains Disconnect + fuse AAF006A400T4E54H4XGC3XXSXXXXAXBXCFXXDX0	134F5171		Buy on EAN
Advanced Active Filter 380-480 VAC, 190Amp correction, IP54/Type12+mains shield, RFI class A1, Mains Disconnect + fuse AAF006A190T4E5MH4XGC3XXSXXXXAXBXCFXXDX	134F1754		Buy on EAN
Advanced Active Filter 380-480 VAC, 250Amp correction, IP54 / Type 12, No RFI Filter, Fuse AAF006A250T4E54HXXGC7XXSXXXXAXBXCFXXDX	134G3433		Buy on EAN