

Circuit-breaker 4p, 1600A, AF

Part no. IZMX16N4-V16W Article no. 123250



Delivery programme

| Delivery programme | | | |
|---|------------------------|----|--|
| Product range | | | Air circuit-breakers/switch-disconnectors |
| Product range | | | Open circuit-breakers |
| Current Range | | | Up to 4000 A |
| Protective function | | | Selective operation |
| Installation type | | | Withdrawable |
| Construction size | | | IZMX16 |
| Release system | | | Electronic release |
| Standard/Approval | | | IEC |
| Number of poles | | | 4 pole |
| Degree of Protection | | | IP20, IP55 with protective cover, IP41 door sealing frame |
| | | | suitable for zone selectivity optionally fittable by user with comprehensive accessories |
| Rated current = rated uninterrupted current | $I_n = I_u$ | Α | 1600 |
| Breaking capacity Icu = Ics to 440 V 50/60 Hz | I _{cu} | kA | 50 |
| Breaking capacity Ics to 440 V 50/60 Hz | I _{cs} | kA | 50 |
| Overload release, min. | I _r | Α | 800 |
| Overload release, max. | I _r | Α | 1600 |
| Non-delayed | $I_i = I_n x \dots$ | | 2 - 12, OFF |
| Delayed > | $I_{sd} = I_r x \dots$ | | 2 - 10 |
| Notes | | | |
| Main terminals not included, need to be ordered separately. | | | |
| Note concerning the product | | | |
| Cassette needs to be ordered separately. | | | |
| | | | |

Technical data

Genera

| General | | | |
|---|-------------|----|---|
| Standards | | | IEC/EN 60947 |
| Ambient temperature | | | |
| Storage | 9 | °C | -40 - +70 |
| Operating (open) | | °C | -25 - +70 |
| Mounting position | | | 30° 30° |
| | | | 30° 30° |
| Utilization category | | | В |
| Degree of Protection | | | IP20, IP55 with protective cover, IP41 door sealing frame |
| Direction of incoming supply | | | as required |
| Main conducting paths | | | |
| Rated current = rated uninterrupted current | $I_n = I_u$ | Α | 1600 |

| u J _{imp} | A A | 1600 1600 |
|---|---|---|
| J _{imp} | | 1600 |
| J _{imp} | | |
| p | V AC | 12000 |
| 10 | V AC | 690 |
| | kA | 23 |
| IT | KA | |
| | V | 111/3 |
| J _i | V | 1000 |
| om. | | |
| | kΔ | 105 |
| ··· | | |
| cm | KA | 88 |
| | | 10 |
| • | KA | 42 |
| cn | | |
| | | |
| cu | kA | 85 |
| cu | kA | 50 |
| cu | kA | 42 |
| | | |
| cs | kA | 50 |
| cs | kA | 50 |
| | kA | 42 |
| us . | | |
| | ms | 30 |
| | | 25 |
| | | 50 |
| | | |
| | ms | 25 |
| | S | |
| Switching cycles (ON/ DFF) | | 12500 |
| Switching cycles (ON/ DFF) | | 20000 |
| Switching cycles (ON/ DFF) | | 10000 |
| Switching cycles (ON/ DFF) | | 10000 |
| Operations/h | | 60 |
| | | |
| | W | 320 |
| | | |
| | | |
| | kg | 28 |
| | kg | 33 |
| | | |
| | kg | 18 |
| | kg | 21 |
| | | |
| | | |
| | | |
| | mm | 2 x 5 x 100 |
| | | |
| | cm cm cm cm cw cau cu | em kA kA em |

| Black | mm | 2 x 5 x 100 |
|-------|----|---|
| | | These are values used in separate switchgear. The actual values will depend on the temperature around the circuit-breaker, which is influenced by the ambient temperature, the degree of protection (IP), the mounting height, the partitions, and any external ventilation. Depending on the specific switchgear design, this may result in derating, which can then be compensated for by increasing the cross-sectional area. Temperature rise tests in the specific switchgear can provide specific and detailed information. |
| | | Permissible continuous current for circuit-breakers operating in switchboards at various internal ambient temperatures. The switchboard's internal ambient temperature should be estimated using the calculation methods of IEC regulation. |

Design verification as per IEC/EN 61439

| 200.g.: 1010ao ao por 120, 211 01 100 | | | |
|--|------------------|----|--|
| Technical data for design verification | | | |
| Rated operational current for specified heat dissipation | In | Α | 1600 |
| Equipment heat dissipation, current-dependent | P _{vid} | W | 320 |
| Operating ambient temperature min. | | °C | -25 |
| Operating ambient temperature max. | | °C | 70 |
| IEC/EN 61439 design verification | | | |
| 10.2 Strength of materials and parts | | | |
| 10.2.2 Corrosion resistance | | | Meets the product standard's requirements. |
| 10.2.3.1 Verification of thermal stability of enclosures | | | Meets the product standard's requirements. |
| 10.2.3.2 Verification of resistance of insulating materials to normal heat | | | Meets the product standard's requirements. |
| 10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects | | | Meets the product standard's requirements. |
| 10.2.4 Resistance to ultra-violet (UV) radiation | | | Meets the product standard's requirements. |
| 10.2.5 Lifting | | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.2.6 Mechanical impact | | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.2.7 Inscriptions | | | Meets the product standard's requirements. |
| 10.3 Degree of protection of ASSEMBLIES | | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.4 Clearances and creepage distances | | | Meets the product standard's requirements. |
| 10.5 Protection against electric shock | | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.6 Incorporation of switching devices and components | | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.7 Internal electrical circuits and connections | | | Is the panel builder's responsibility. |
| 10.8 Connections for external conductors | | | Is the panel builder's responsibility. |
| 10.9 Insulation properties | | | |
| 10.9.2 Power-frequency electric strength | | | Is the panel builder's responsibility. |
| 10.9.3 Impulse withstand voltage | | | Is the panel builder's responsibility. |
| 10.9.4 Testing of enclosures made of insulating material | | | Is the panel builder's responsibility. |
| 10.10 Temperature rise | | | The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. |
| 10.11 Short-circuit rating | | | Is the panel builder's responsibility. The specifications for the switch gear must be observed. $\label{eq:constraint}$ |
| 10.12 Electromagnetic compatibility | | | Is the panel builder's responsibility. The specifications for the switch gear must be observed. $\label{eq:constraint}$ |
| 10.13 Mechanical function | | | The device meets the requirements, provided the information in the instruction leaflet (IL) is observed. $\label{eq:continuous}$ |

Technical data ETIM 6.0

Low-voltage industrial components (EG000017) / Power circuit-breaker for trafo/generator/installation prot. (EC000228)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Circuit breaker for power transformer, generator and system protection (ecl@ss8.1-27-37-04-09 [AJZ716010])

| protection (ecl@ss8.1-27-37-04-09 [AJZ716010]) | | |
|---|----|-----------------|
| Rated permanent current lu | Α | 1600 |
| Rated voltage | V | 690 - 690 |
| Rated short-circuit breaking capacity Icu at 400 V, 50 Hz | kA | 50 |
| Overload release current setting | Α | 800 - 1600 |
| Adjustment range short-term delayed short-circuit release | Α | 3200 - 16000 |
| Adjustment range undelayed short-circuit release | Α | 3200 - 19200 |
| Integrated earth fault protection | | No |
| Type of electrical connection of main circuit | | Rail connection |

| Built-in device slide-in technique (withdrawable) |
|--|
| Duilt-iii device Siide-iii technique (withul awable) |
| No |
| No |
| 0 |
| 0 |
| 2 |
| Yes |
| No |
| 4 |
| Back side |
| Push button |
| Yes |
| No |
| Yes |
| IP20 |
| |

Dimensions

