SWITCHING WITH 2-CHANNEL-CEILING-MOUNTED MOTION DETECTORS

(MOTION DETECTORS FOR INDOOR USE)

LUXOMAT® PD3N-2C-FC/-FM












- Remote controllable ceiling-mounted motion detectors LUXOMAT® PD3N-2C in ceiling-mount and flush-mount version with circular detection area
- Two switching channels, one to switch the lighting, the second to switch other loads e.g. HVAC by potential free relay of the detector
- Switching for all types of light fixtures by high performance relay
- Optical system, designed for highest sensitivity
- Serial impulse function (gong)
- Typical applications: monitoring of smaller areas like stairwells, private garages, galleries, wash rooms
















■ TECHNICAL DATA



230 V~ ±10 %



O 360°



Ø 10.00 m across towards Ø 6.00 m

FC = IP23; FM = IP20 / IP 🗆 Class II / C€

FC Ø 83 x H 81 mm FM Ø 106 x H 63 mm



-25°C to +50°C



Housing UV- and shockresistant polycarbonate



IR-PD3N-2C, IR-PD-Mini

Channel 1 (Control the lighting)

2300 W, $\cos \varphi = 1$; 1150 VA, $\cos \varphi = 0.5$



30 sec. - 30 min. or impulse



10 - 2000 Lux

Channel 2 (Control devices)


dry contact type NO, 3Å, 230 V, $\cos \varphi = 1$



5 - 120 min.



- ▶ Remote controls on page 123, 126!
- Wiring diagrams on page 146!
- For maximum number of connectable lights, see page 22!
- Installation note Arc extinction kit: on page 36!



- 1 Walking towards
- 2 Walking across
- 3 Smaller movements

ACCESSORY (OPTIONAL)



separately)





(to order







Blinds see page 36!



Arc extinction kit see page 36!

Description	Colour	Part number
PD3N-2C-FC	white	92198
PD3N-2C-FM	white	92188
Accessory (optional)		
LUXOMAT® IR-PD3N-2C	grey	92115
LUXOMAT® IR-PD-Mini	grey	92159
Wire basket BSK	white	92199