


LUXOMAT® PD4-M-1C-SM/-FC/-FM



For monitoring
large areas




SM




FC




FM



SM



FC



FM

■ TECHNICAL DATA

- 230V~ ±10%
- 360°
- seated Ø 6.40 m
- across Ø 24.00 m
- towards Ø 8.00 m
- SM/FC/FM = IP20 / Class II / Cc
- SM Ø 98 x H 65 mm
- FC Ø 97 x H 103 mm
- FM Ø 97 x H 84 mm
- 25°C to +50°C
- Housing UV- and shock-resistant polycarbonate
- IR-PD-1C, IR-PD-Mini


Channel 1 (Control the lighting)

- 2300 W, cosφ = 1;
1150 VA, cosφ = 0.5
- 15 sec. - 30 min. or impulse
- 10 - 2000 Lux

- ▶ Remote controls on page 126, 127!
- ▶ Wiring diagrams on page 148!
- ▶ For maximum number of connectable lights, see page 38!
- ▶ Installation note - Arc extinction kit: on page 102!

■ PRODUCT INFORMATION

- Remote controllable occupancy detector for inside use LUXOMAT® PD4-M-1C as Master version for surface, false ceiling and flush mounting with circular detection area
- One channel to switch the lighting (potential-free)
- Switching for all types of light fixtures by high performance relay
- Optical system, designed for highest sensitivity
- The connection of a unlimited number of Slaves for reasonable extension is possible!
- Serial impulse function
- **Typical applications:** monitoring of large areas like underground garages, gyms, warehouses, loading ramps, halls



- 1 Walking towards
- 2 Walking across
- 3 Seated activity

■ ACCESSORY (OPTIONAL)

IR-PD-1C




(to order separately)

IR-PD-Mini



(to order separately)

Wire basket



Socket IP54



SM-Socket IP65



Blinds
see page 102!

Arc extinction kit
see page 102!

Slaves PD4-S
see page 83!

Description	Colour	Part number
PD4-M-1C-SM	white	92580
PD4-M-1C-FC	white	92585
PD4-M-1C-FM	white	92575
Accessory (optional)		
Wire basket BSK	white	92199
LUXOMAT® IR-PD-1C	grey	92520
LUXOMAT® IR-PD-Mini	grey	92159
Socket IP54 for PD4-SM	white	92161
SM-Socket IP65 for PD4-SM (IP20)	white	92375