### SWITCHING WITH 1-CHANNEL OCCUPANCY DETECTOR AS MASTER VERSION FOR **HIGH ELEVATIONS** (MOTION DETECTOR FOR INSIDE USE)

#### **LUXOMAT® PD4-M-1C-GH-SM**



# 98 98

=

switched live (L'),

potential-free

#### **TECHNICAL DATA**

230 V~ ±10 %

○ 360°

across Ø 44.00 m

IP 🗆 SM = IP20 / Class II / (€

**SM** Ø 98 x H 65 mm [·.

-25°C to +50°C

Housing UV- and shockresistant polycarbonate

IR-PD4-GH, IR-PD-Mini

#### **Channel 1 (Control the lighting)**

2300 W,  $\cos \varphi = 1$ ; 1150 VA,  $\cos \varphi = 0.5$ 

15 sec. - 30 min. or impulse


10 - 2000 Lux

- Remote controls on page 129, 126!
- Wiring diagrams on page 148!
- Application examples on page 178!
- For maximum number of connectable lights, see page 38!
- Installation note Arc extinction kit: on page 102!

## (i) PRODUCT INFORMATION

 Remote controllable occupancy detector for inside use LUXOMAT® PD4-M-1C-GH-SM as Master version for surface mounting with oval detection area and a range up to 44m ideal for high-bay storages

- One channel to switch the lighting (potential-free)
- Switching for all types of light fixtures by high performance relay with limitation of switch current for EBs
- The connection of a unlimited number of Slaves for reasonable extension is possible!
- The product is programmed for immediate use
- Switch on and off of the lighting plus adjustments with remote control **LUXOMAT® IR-PD4-GH**
- Typical applications: monitoring of warehouses, high-bay storages, wherever at a great mounting height is necessary



#### ACCESSORY (OPTIONAL)

With jumper

Without jumper =



(to order separately)

IR-PD-Mini



separately)

Wire basket



Socket IP54



SM-Socket IP65





see page 102!

Arc extinction kit see page 102!



Slaves PD4-S-GH see page 85!

Description	Colour	Part number
PD4-M-1C-GH-SM	white	92245
Accessory (optional)		
LUXOMAT® IR-PD4-GH	grey	92215
LUXOMAT® IR-PD-Mini	grey	92159
Wire basket BSK	white	92199
Socket IP54	white	92161
SM-Socket IP65 for PD4-SM (IP20)	white	92375