



Signalling switch tripped, 2W

Part no. +IZMX-OTS
Catalog No. 123888

Delivery program

Product range			Accessories
Accessories			Trip indication / Reset options
Accessories			Trip-indicating auxiliary switch
			Overcurrent trip switch (OTS) with two changeover contacts.
For use with			IZMX16..., IZMX40...
Notes			
Three additional control circuit terminal blocks are required for retrofitting. -> 124166			

Technical data

Rated breaking capacity

Inductive load			
250 V AC		A	10
125 V DC		A	0.5
250 V DC		A	0.25

Design verification as per IEC/EN 61439

Technical data for design verification			
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	70

Technical data ETIM 7.0

Low-voltage industrial components (EG000017) / Trip indicator (EC001025)			
Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Trip indicator (ecl@ss10.0.1-27-37-04-20 [AKF018013])			
Function			Power-cut-out switch
Number of contacts as normally open contact			0
Number of contacts as normally closed contact			0
Number of contacts as change-over contact			2
Type of electric connection			Flat plug-in connection