



Fuse-disconnector with flashing light, 25A DC, 10x38 mm

**Part no.** FCFDC10DI-1L-SOL  
**Catalog No.** 137258

Similar to illustration

## Delivery program

Product range			Fuse disconnector
Application field			Residential buildings Utility buildings Open areas
Description			String protection of the PV generator The trip indication signals the tripped fuse link: 50 - 400 V flashing, 400 - 1000 V continuous for cylindrical fuse links for photovoltaic application sealable
Connection			With flashing function
Rated operational voltage	$U_e$	V	1000
Rated operational current 240 V	$I_e$	A	25
Size			10 x 38
Number of poles			1 pole

## Technical data

Rated operational voltage	$U_e$	V	1000
---------------------------	-------	---	------

## Technical data ETIM 7.0

Low-voltage industrial components (EG000017) / Fuse switch disconnector (EC001040)			
Electric engineering, automation, process control engineering / Low-voltage switch technology / Off-load switch, circuit breaker, control switch / Fuse switch disconnector (ecl@ss10.0.1-27-37-14-01 [AKF058013])			
Version as main switch			No
Version as safety switch			Yes
Max. rated operation voltage $U_e$ AC		V	0
Rated permanent current $I_u$		A	25
Rated operation power at AC-23, 400 V		kW	0
Conditioned rated short-circuit current $I_q$		kA	10
Rated short-time withstand current $I_{cw}$		kA	0
Suitable for fuses			Shape C1-C3
Number of poles			1
With error protection			No
Type of electrical connection of main circuit			Screw connection
Cable entry			
Equipped with connectors			
Suitable for ground mounting			No
Suitable for front mounting 4-hole			No
Suitable for busbar mounting			No
Type of control element			Other
Position control element			Front side
Motor drive optional			No
Motor drive integrated			No
Version as emergency stop installation			No
Degree of protection (IP), front side			IP20