## **DATASHEET - IZMX40H3-P40F**



Circuit-breaker, 3p, 4000 A, fixed

Part no. IZMX40H3-P40F

Catalog No. 149756

Eaton Catalog No. RESC403B12RNMNN2MN1X



Delivery program			
Product range			Air circuit-breakers/switch-disconnectors
Product range			Open circuit-breakers
Current Range			Up to 4000 A
Protective function			Professional protection
Installation type			Fixed
Construction size			IZMX40
Release system			Electronic release
Standard/Approval			IEC
Number of poles			3 pole
Degree of Protection			IP20, IP55 with protective cover, IP41 door sealing frame
			suitable for zone selectivity suitable for communication with integrated system monitor with integrated test possibility with graphic LCD color display optionally fittable by user with comprehensive accessories
Rated current = rated uninterrupted current	$I_n = I_u$	Α	4000
up to 440 V 50/60 Hz	I <sub>cu</sub>	kA	105
up to 440 V 50/60 Hz	I <sub>cs</sub>	kA	105
Overload release, min.	I <sub>r</sub>	Α	2000
Overload release, max.	I <sub>r</sub>	Α	4000
Non-delayed	$I_i = I_n x \dots$		2 - 12, OFF
Delayed X12	$I_{sd} = I_r x \dots$		2 - 10

## Technical data

General			
Standards			IEC/EN 60947
Ambient temperature			
Storage	9	°C	-25 - +70 (device with LCD-display -20 - +70)
Operating (open)		°C	-25 - +70 (device with LCD-display -20 - +70)
Mounting position			30° 30°
			30° 30°
Utilization category			В
Degree of Protection			IP20, IP55 with protective cover, IP41 door sealing frame
Direction of incoming supply			as required
Main conducting paths			
Rated current = rated uninterrupted current	$I_n = I_u$	Α	4000

Rated uninterrupted current at 50 °C	l <sub>u</sub>	Α	4000
Rated uninterrupted current at 60 °C	I <sub>u</sub>	Α	3650
Rated uninterrupted current at 70 °C	I <sub>u</sub>	Α	75
Rated impulse withstand voltage	$U_{imp}$	V AC	12000
Rated operational voltage	U <sub>e</sub>	V AC	690
Use in IT electrical power networks up to U = 440 V	I <sub>IT</sub>	kA	57.6
Overvoltage category/pollution degree			III/3
Rated insulation voltage	Ui	٧	1000
Switching capacity			
Rated short-circuit making capacity	I <sub>cm</sub>		
up to 440 V 50/60 Hz	I <sub>cm</sub>	kA	231
up to 690 V 50/60 Hz	I <sub>cm</sub>	kA	166
Rated short-time withstand current 50/60 Hz			
t = 1 s	I <sub>cw</sub>	kA	85
t = 3 s	I <sub>cw</sub>	kA	66
Rated short-circuit breaking capacity I <sub>cn</sub>	I <sub>cn</sub>		
IEC/EN 60947 operating sequence I <sub>CII</sub> 0-t-CO			
up to 240 V 50/60 Hz	I <sub>cu</sub>	kA	105
up to 440 V 50/60 Hz	I <sub>cu</sub>	kA	105
up to 690 V 50/60 Hz	I <sub>cu</sub>	kA	75
·	'CU	NA.	13
IEC/EN 60947 operating sequence I <sub>cs</sub> 0-t-C0-t-C0			.005
up to 240 V 50/60 Hz	I <sub>cs</sub>	kA	105
up to 440 V 50/60 Hz	I <sub>cs</sub>	kA	105
up to 690 V 50/60 Hz	I <sub>cs</sub>	kA	75
Operating times			
Closing delay via spring release		ms	35
Total opening delay via shunt release		ms	22
Total opening delay via undervoltage release		ms	37
			_
Total opening delay on non-delayed short-circuit release (up to complete arc quenching)		ms	45
Maximum operating frequency	Operations/h		60
Heat dissipation at rated current I <sub>n</sub>			
Fixed mounting		W	600
Weight			
Fixed mounting			
3-pole		kg	43
4-pole Terminal capacities		kg	56
Copper bar			
Fixed mounting			
Black		mm	4 x 100 x 10
			These are values used in separate switchgear. The actual values will depend on the temperature around the circuit-breaker, which is influenced by the ambient temperature, the degree of protection (IP), the mounting height, the partitions, and any external ventilation. Depending on the specific switchgear design, this may result in derating, which can then be compensated for by increasing the cross-
			sectional area. Temperature rise tests in the specific switchgear can provide specific and detailed information.  Permissible continuous current for circuit-breakers operating in switchboards at various internal ambient temperatures. The switchboard's internal ambient temperature should be estimated using the calculation methods of IEC regulation.
			With vertical universal connection.
Notes			IZMX-DTP-PTM external voltage measuring module required

## Design verification as per IEC/EN 61439

Rated operational current for specified heat dissipation	In	Α	4000
Equipment heat dissipation, current-dependent	P <sub>vid</sub>	W	600
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	70
IEC/EN 61439 design verification			
10.2 Strength of materials and parts			
10.2.2 Corrosion resistance			Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures			Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat			Meets the product standard's requirements.
$10.2.3.3\ Verification\ of\ resistance\ of\ insulating\ materials\ to\ abnormal\ heat\ and\ fire\ due\ to\ internal\ electric\ effects$			Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation			Meets the product standard's requirements.
10.2.5 Lifting			Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact			Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions			Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES			Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances			Meets the product standard's requirements.
10.5 Protection against electric shock			Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components			Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections			Is the panel builder's responsibility.
10.8 Connections for external conductors			Is the panel builder's responsibility.
10.9 Insulation properties			
10.9.2 Power-frequency electric strength			Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage			Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material			Is the panel builder's responsibility.
10.10 Temperature rise			The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating			Is the panel builder's responsibility. The specifications for the switch gear must be observed. $\label{eq:constraint}$
10.12 Electromagnetic compatibility			Is the panel builder's responsibility. The specifications for the switch gear must be observed. $\label{eq:constraint}$
10.13 Mechanical function			The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

## **Technical data ETIM 6.0**

Low-voltage industrial components (EG000017) / Power circuit-breaker for trafo/generator/installation prot. (EC000228)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Circuit breaker for power transformer, generator and system protection (ecl@ss8.1-27-37-04-09 [AJZ716010])

Rated voltage Rated voltage Rated short-circuit breaking capacity Icu at 400 V, 50 Hz Rated short-circuit breaking capacity Icu at 400 V, 50 Hz Rated short-circuit breaking capacity Icu at 400 V, 50 Hz Rated short-circuit release Adjustment range short-term delayed short-circuit release Adjustment range undelayed Adjustment range undelayed short-circuit release Adjustment range			
Rated short-circuit breaking capacity Icu at 400 V, 50 Hz  Overload release current setting  Adjustment range short-term delayed short-circuit release  Adjustment range undelayed short-circuit release  Adjustment range undelayed short-circuit release  Ad 8000 - 40000  Adjustment range undelayed short-circuit release  Ad 8000 - 48000  Integrated earth fault protection  Type of electrical connection of main circuit  Device construction  Suitable for DIN rail (top hat rail) mounting  DIN rail (top hat rail) mounting  DIN rail (top hat rail) mounting optional  Number of auxiliary contacts as normally closed contact  Number of auxiliary contacts as normally open contact  Number of auxiliary contacts as change-over contact  Switched-off indicator available  With under voltage release  Number of poles  Position of connection for main current circuit  kA 2000 - 40000  Ad 8000 - 40000  No  Rail connection  No  Rail connection  No  No  O  C  O  O  O  O  O  O  O  O  O  O  O	Rated permanent current lu	Α	4000
Overload release current setting Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit release Adjustment range short-term delayed short-circuit release Adjustment range short-circuit release Adjustment range short-term delayed short-circuit release Adjustment range short	Rated voltage	V	690 - 690
Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit release Adjustment range undelase Adjustment r	Rated short-circuit breaking capacity Icu at 400 V, 50 Hz	kA	105
Adjustment range undelayed short-circuit release A 8000 - 48000 Integrated earth fault protection No Type of electrical connection of main circuit Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact  Number of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release With under voltage release Number of poles Position of connection for main current circuit  A 8000 - 48000 No Rail connection Ra	Overload release current setting	Α	2000 - 4000
Integrated earth fault protection Type of electrical connection of main circuit Rail connection Device construction Built-in device fixed built-in technique Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional No No Number of auxiliary contacts as normally closed contact Output of auxiliary contacts as normally open contact Output of auxiliary contacts as change-over contact Switched-off indicator available With under voltage release With under voltage release No Number of poles Position of connection for main current circuit Back side	Adjustment range short-term delayed short-circuit release	Α	8000 - 40000
Type of electrical connection of main circuit  Device construction  Suitable for DIN rail (top hat rail) mounting  DIN rail (top hat rail) mounting optional  No  No  No  Number of auxiliary contacts as normally closed contact  Number of auxiliary contacts as normally open contact  Number of auxiliary contacts as change-over contact  Number of auxiliary contacts as change-over contact  Switched-off indicator available  With under voltage release  No  Number of poles  Position of connection for main current circuit  Rail connection  Built-in device fixed built-in technique  No  No  No  No  Switched-off indicator available  Yes  No  Back side	Adjustment range undelayed short-circuit release	Α	8000 - 48000
Device construction  Built-in device fixed built-in technique  No  No  DIN rail (top hat rail) mounting optional  No  Number of auxiliary contacts as normally closed contact  Number of auxiliary contacts as normally open contact  Number of auxiliary contacts as change-over contact  Number of auxiliary contacts as change-over contact  Switched-off indicator available  Ves  With under voltage release  No  Number of poles  Position of connection for main current circuit  Built-in device fixed built-in technique  No  No  No  Built-in device fixed built-in technique  No  No  No  Suddenting the pole in th	Integrated earth fault protection		No
Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact 0 Number of auxiliary contacts as normally open contact 0 Number of auxiliary contacts as change-over contact 2 Switched-off indicator available With under voltage release With under voltage release No No Number of poles Position of connection for main current circuit No	Type of electrical connection of main circuit		Rail connection
DIN rail (top hat rail) mounting optional  No Number of auxiliary contacts as normally closed contact  Number of auxiliary contacts as normally open contact  Number of auxiliary contacts as change-over contact  Number of auxiliary contacts as change-over contact  Switched-off indicator available  With under voltage release  No Number of poles  Position of connection for main current circuit  No  Back side	Device construction		Built-in device fixed built-in technique
Number of auxiliary contacts as normally closed contact  Number of auxiliary contacts as normally open contact  Number of auxiliary contacts as change-over contact  Switched-off indicator available  With under voltage release  No  Number of poles  Position of connection for main current circuit  O  Number of auxiliary contacts as normally open contact  2  Switched-off indicator available  Yes  No  Back side	Suitable for DIN rail (top hat rail) mounting		No
Number of auxiliary contacts as normally open contact  Number of auxiliary contacts as change-over contact  Switched-off indicator available  With under voltage release  No  Number of poles  Position of connection for main current circuit  O  Ves  No  Back side	DIN rail (top hat rail) mounting optional		No
Number of auxiliary contacts as change-over contact  Switched-off indicator available  With under voltage release  No  Number of poles  Position of connection for main current circuit  2  Switched-off indicator available  Yes  No  Back side	Number of auxiliary contacts as normally closed contact		0
Switched-off indicator available  Yes  With under voltage release  No  Number of poles  Position of connection for main current circuit  No  Back side	Number of auxiliary contacts as normally open contact		0
With under voltage release No Number of poles 3 Position of connection for main current circuit Back side	Number of auxiliary contacts as change-over contact		2
Number of poles 3 Position of connection for main current circuit Back side	Switched-off indicator available		Yes
Position of connection for main current circuit  Back side	With under voltage release		No
	Number of poles		3
Type of control element Push button	Position of connection for main current circuit		Back side
1,75	Type of control element		Push button

Complete device with protection unit	Yes
Motor drive integrated	No
Motor drive optional	Yes
Degree of protection (IP)	IP20