### **DATASHEET - T0-3-15680/XZ**



On-Off switch, T0, 20 A, rear mounting, Basic switch, 3 contact unit(s), 3 pole + N, 1 N/O, 1 N/C



Part no. Catalog No. T0-3-15680/XZ 013046

#### Similar to illustration

Delivery program			
Product range			On-Off switch
Part group reference			ТО
Number of poles			3 pole + N
Auxiliary contacts			
1		N/0	1
7		N/C	1
Design			rear mounting Basic switch
Contact sequence			
Switching angle		0	90
Design number			15680
Front plate no.			FS 908
Motor rating AC-23A, 50 - 60 Hz			
400 V	Р	kW	5.5
Rated uninterrupted current	lu	А	20
Note on rated uninterrupted current !u			Rated uninterrupted current $\boldsymbol{I}_{\boldsymbol{u}}$ is specified for max. cross-section.
Number of contact units		contact unit(s)	3
Technical data General			
Standards			IEC/EN 60947, VDE 0660, IEC/EN 60204 Switch-disconnector according to IEC/EN 60947-3
Climatic proofing			Damp heat, constant, to IEC 60068-2-78 Damp heat, cyclic, to IEC 60068-2-30
Ambient temperature			
Open		°C	-25 - +50
Enclosed		°C	-25 - +40

Overvoltage category/pollution degree Rated impulse withstand voltage

Mechanical shock resistance

Mounting position

Contacts Mechanical variables Number of poles U<sub>imp</sub>

III/3

6000

15

As required

3 pole + N

V AC

g

Auxiliary contacts			
		N/0	1
		N/C	1
Electrical characteristics			
Rated operational voltage	Ue	V AC	690
Rated uninterrupted current	lu	A	20
Note on rated uninterrupted current !u			Rated uninterrupted current I <sub>u</sub> is specified for max. cross-section.
Load rating with intermittent operation, class 12			
AB 25 % DF		x l <sub>e</sub>	2
AB 40 % DF		x l <sub>e</sub>	1.6
AB 60 % DF		x l <sub>e</sub>	1.3
Short-circuit rating		× .6	
Fuse		A gG/gL	20
Rated short-time withstand current (1 s current)	I <sub>cw</sub>	A <sub>rms</sub>	320
Note on rated short-time withstand current lcw	-0.00	- 1115	Current for a time of 1 second
Rated conditional short-circuit current	l <sub>q</sub>	kA	6
Switching capacity	·ų		
cos φ rated making capacity as per IEC 60947-3		А	130
Rated breaking capacity $\cos \phi$ to IEC 60947-3		A	
230 V		A	100
400/415 V		А	110
500 V		А	80
690 V		А	60
Safe isolation to EN 61140			
between the contacts		V AC	440
Current heat loss per contact at l <sub>e</sub>		W	0.6
Current heat loss per auxiliary circuit at $\rm I_e$ (AC-15/230 V)		C0	0.6
Lifespan, mechanical	Operations	x 10 <sup>6</sup>	> 0.4
Maximum operating frequency	Operations/h		1200
AC			
AC-3			
Rating, motor load switch	Р	kW	
	Р	kW kW	3
Rating, motor load switch 220 V 230 V 230 V Star-delta	P P	kW kW	5.5
Rating, motor load switch 220 V 230 V 230 V Star-delta 400 V 415 V	P P P	kW kW kW	5.5 5.5
Rating, motor load switch 220 V 230 V 230 V Star-delta 400 V 415 V 400 V Star-delta	P P P P	kW kW kW kW	5.5 5.5 7.5
Rating, motor load switch220 V 230 V230 V Star-delta400 V 415 V400 V Star-delta500 V	P P P P P	kW kW kW kW kW	5.5 5.5 7.5 5.5
Rating, motor load switch220 V 230 V230 V Star-delta400 V 415 V400 V Star-delta500 V500 V Star-delta	P P P P P P P	kW kW kW kW kW	5.5         5.5         7.5         5.5         7.5
Rating, motor load switch220 V 230 V230 V Star-delta400 V 415 V400 V Star-delta500 V500 V Star-delta690 V	P P P P P P P P P	kW kW kW kW kW kW	5.5         5.5         7.5         5.5         7.5         4
Rating, motor load switch220 V 230 V230 V Star-delta400 V 415 V400 V Star-delta500 V500 V Star-delta690 V690 V Star-delta	P P P P P P P	kW kW kW kW kW	5.5         5.5         7.5         5.5         7.5
Rating, motor load switch220 V 230 V230 V Star-delta400 V 415 V400 V Star-delta500 V500 V Star-delta690 V690 V Star-deltaRated operational current motor load switch	P P P P P P P P P	kW kW kW kW kW kW kW	5.5         5.5         7.5         5.5         7.5         4         5.5
Rating, motor load switch220 V 230 V230 V Star-delta400 V 415 V400 V Star-delta500 V500 V Star-delta690 V690 V Star-deltaRated operational current motor load switch230 V	P P P P P P P P P P P P	kW kW kW kW kW kW kW kW	5.5         5.5         7.5         5.5         7.5         4         5.5         11.5
Rating, motor load switch220 V 230 V230 V Star-delta400 V 415 V400 V Star-delta500 V500 V Star-delta690 V690 V Star-deltaRated operational current motor load switch230 V230 V star-delta	P P P P P P P P P P P P P P P P P	kW kW kW kW kW kW kW A A	5.5         5.5         7.5         5.5         7.5         4         5.5         11.5         20
Rating, motor load switch220 V 230 V230 V Star-delta400 V 415 V400 V Star-delta500 V500 V Star-delta690 V690 V Star-deltaRated operational current motor load switch230 V230 V Star-delta400 V Star-delta400 V Star-delta400 V Star-delta400 V Star-delta400 V Star-delta	P P P P P P P P P P P P P P P P P P P	kW k	5.5         5.5         7.5         5.5         7.5         4         5.5         11.5         20         11.5
Rating, motor load switch220 V 230 V230 V Star-delta400 V 415 V400 V Star-delta500 V500 V Star-delta690 V690 V Star-delta230 V Star-delta230 V Star-delta400 V Star-delta400 V Star-delta690 V Star-delta690 V Star-delta690 V Star-delta400 V Star-delta400 V Star-delta400 V Star-delta400 V Star-delta400 V Star-delta	P P P P P P P P P P I I I I I I I I I I	kW	5.5         5.5         7.5         5.5         7.5         4         5.5         11.5         20         11.5         20
Rating, motor load switch220 V 230 V230 V Star-delta400 V 415 V400 V Star-delta500 V500 V Star-delta690 V690 V Star-delta890 V Star-delta230 V230 V230 V400V 415 V400 V 415 V400 V 415 V400 V star-delta500 V500 V	P P P P P P P P P P P P P P P P P P P	kW k	5.5         5.5         7.5         5.5         7.5         4         5.5         11.5         20         11.5         20         11.5         20         11.5         20         11.5         20         11.5         20         11.5         20         21         22         3
Rating, motor load switch220 V 230 V230 V Star-delta400 V 415 V400 V Star-delta500 V500 V Star-delta690 V690 V Star-delta690 V Star-delta230 V Star-delta230 V Star-delta400 V star-delta500 V500 V Star-delta500 V Star-delta	P         P <td< td=""><td>kW           kW           kW           kW           kW           kW           kW           kW           kW           A           A           A           A           A           A           A           A           A           A</td><td>5.5         5.5         7.5         5.5         7.5         4         5.5         11.5         20         11.5         20         11.5         20         11.5         20         5.5         5.6</td></td<>	kW           kW           kW           kW           kW           kW           kW           kW           kW           A           A           A           A           A           A           A           A           A           A	5.5         5.5         7.5         5.5         7.5         4         5.5         11.5         20         11.5         20         11.5         20         11.5         20         5.5         5.6
Rating, motor load switch220 V 230 V230 V Star-delta400 V 415 V400 V Star-delta500 V500 V Star-delta690 V690 V Star-delta690 V230 V230 V230 V230 V star-delta690 V Star-delta500 V Star-delta690 V500 V Star-delta690 V500 V Star-delta500 V500 V star-delta690 V690 V Star-delta690 V690 V Star-delta500 V Star-delta500 V500 V star-delta690 V	P P P P P P P P P P P P P P P P P P P	kW	5.5         5.5         7.5         7.5         4         5.5         11.5         20         11.5         20         11.5         20         15.6         4.9
Rating, motor load switch220 V 230 V230 V Star-delta400 V 415 V400 V Star-delta500 V500 V Star-delta690 V Star-delta690 V Star-delta230 V Star-delta230 V Star-delta230 V230 V star-delta500 V Star-delta690 V500 V Star-delta690 V690 V Star-delta690 V690 V star-delta690 V star-delta690 V star-delta690 V star-delta690 V star-delta690 V star-delta690 V690 V star-delta690 V690 V star-delta690 V	P         P <td< td=""><td>kW           kW           kW           kW           kW           kW           kW           kW           kW           A           A           A           A           A           A           A           A           A           A</td><td>5.5         5.5         7.5         5.5         7.5         4         5.5         11.5         20         11.5         20         11.5         20         11.5         20         5.5         5.6</td></td<>	kW           kW           kW           kW           kW           kW           kW           kW           kW           A           A           A           A           A           A           A           A           A           A	5.5         5.5         7.5         5.5         7.5         4         5.5         11.5         20         11.5         20         11.5         20         11.5         20         5.5         5.6
Rating, motor load switch         220 V 230 V         230 V Star-delta         400 V 415 V         400 V Star-delta         500 V         500 V Star-delta         690 V         690 V Star-delta         690 V         230 V Star-delta         690 V         230 V Star-delta         230 V         230 V         230 V         230 V star-delta         400V 415 V         400 V star-delta         500 V         500 V         500 V         500 V star-delta         690 V         690 V star-delta         690 V         690 V star-delta         690 V         500 V star-delta         690 V         690 V star-delta         690 V star-delta	P P P P P P P P P P P P P P P P P P P	kW	5.5         5.5         7.5         7.5         4         5.5         11.5         20         11.5         20         11.5         20         15.6         4.9
Rating, motor load switch220 V 230 V230 V Star-delta400 V 415 V400 V Star-delta500 V500 V Star-delta690 V690 V Star-delta690 V230 V230 V230 V230 V500 V Star-delta690 V690 V Star-delta690 V690 V Star-delta690 V690 V500 V500 V690 V star-delta690 V star-delta </td <td>P P P P P P P P P P P P P P P P P P P</td> <td>kW       kW       kW       kW       kW       kW       kW       A</td> <td>5.5         5.5         7.5         5.5         7.5         4         5.5         11.5         20         11.5         20         9         15.6         4.9         8.5</td>	P P P P P P P P P P P P P P P P P P P	kW       kW       kW       kW       kW       kW       kW       A	5.5         5.5         7.5         5.5         7.5         4         5.5         11.5         20         11.5         20         9         15.6         4.9         8.5
Rating, motor load switch220 V 230 V230 V Star-delta400 V 415 V400 V Star-delta500 V500 V Star-delta690 V690 V Star-delta230 V230 V230 V230 V star-delta690 V690 V star-delta690 V star-delta <td>P P P P P P P P P P P P P P P P P P P</td> <td>kW                                      </td> <td>5.5         5.5         7.5         4         5.5         11.5         20         11.5         20         11.5         20         15.6         4.9</td>	P P P P P P P P P P P P P P P P P P P	kW	5.5         5.5         7.5         4         5.5         11.5         20         11.5         20         11.5         20         15.6         4.9
Rating, motor load switch220 V 230 V230 V Star-delta400 V 415 V400 V Star-delta500 V500 V Star-delta690 V690 V Star-delta690 V Star-delta230 V230 V star-delta400V 415 V400 V star-delta690 V500 V star-delta690 V690 V Star-delta690 V690 V star-delta690 V500 V star-delta690 V	P P P P P P P P P P P P P P P P P P P	kW       kW       kW       kW       kW       kW       kW       A	5.5         5.5         7.5         5.5         7.5         4         5.5         11.5         20         11.5         20         9         15.6         4.9         8.5

230 V	Р	kW	3
400 V 415 V	Р	kW	5.5
500 V	Р	kW	7.5
690 V	Р	kW	5.5
Rated operational current motor load switch			
230 V	le	A	13.3
400 V 415 V		A	13.3
	l <sub>e</sub>		
500 V	l <sub>e</sub>	A	13.3
690 V	le	A	7.6
DC			
DC-1, Load-break switches L/R = 1 ms			
Rated operational current	Ie	А	10
Voltage per contact pair in series		V	60
DC-21A	I <sub>e</sub>	А	
Rated operational current	Ι <sub>e</sub>	A	1
Contacts		Quantity	1
DC-23A, motor load switch L/R = 15 ms			
24 V			
Rated operational current	le	A	10
Contacts	C	Quantity	
48 V		Quantity	
Rated operational current	1	A	10
	l <sub>e</sub>		
Contacts		Quantity	2
60 V			
Rated operational current	le	A	10
Contacts		Quantity	3
120 V			
Rated operational current	I <sub>e</sub>	А	5
Contacts		Quantity	3
240 V			
Rated operational current	I <sub>e</sub>	А	5
Contacts		Quantity	5
DC-13, Control switches L/R = 50 ms			
Rated operational current	I <sub>e</sub>	А	10
Voltage per contact pair in series		V	32
Control circuit reliability at 24 V DC, 10 mA	Fault probability	H <sub>F</sub>	< 10 <sup>-5</sup> ,< 1 failure in 100,000 switching operations
Terminal capacities			
Solid or stranded		mm <sup>2</sup>	1 x (1 - 2,5) 2 x (1 - 2,5)
Flexible with ferrules to DIN 46228		mm <sup>2</sup>	1 x (0.75 - 2.5) 2 x (0.75 - 2.5)
Terminal screw			M3.5
Tightening torque for terminal screw		Nm	1
Technical safety parameters:			
Notes			B10 <sub>d</sub> values as per EN ISO 13849-1, table C1
Rating data for approved types			
Terminal capacity			
			M3.5

# Design verification as per IEC/EN 61439

Technical data for design verification			
Rated operational current for specified heat dissipation	I <sub>n</sub>	А	20
Heat dissipation per pole, current-dependent	P <sub>vid</sub>	W	0.6
Equipment heat dissipation, current-dependent	P <sub>vid</sub>	W	0
Static heat dissipation, non-current-dependent	P <sub>vs</sub>	W	0

Heat dissipation capacity	P <sub>diss</sub>	W	0
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	50
EC/EN 61439 design verification			
10.2 Strength of materials and parts			
10.2.2 Corrosion resistance			Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures			Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat			Meets the product standard's requirements.
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects			Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation			UV resistance only in connection with protective shield.
10.2.5 Lifting			Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact			Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions			Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES			Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances			Meets the product standard's requirements.
10.5 Protection against electric shock			Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components			Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections			Is the panel builder's responsibility.
10.8 Connections for external conductors			Is the panel builder's responsibility.
10.9 Insulation properties			
10.9.2 Power-frequency electric strength			Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage			Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material			Is the panel builder's responsibility.
10.10 Temperature rise			The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating			Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility			Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function			The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

### **Technical data ETIM 7.0**

Low-voltage industrial components (EG000017) / Switch disconnector (EC000216)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Off-load switch, circuit breaker, control switch / Switch disconnector (ecl@ss10.0.1-27-37-14-03 [AKF060013])

Version as main switch		No
Version as maintenance-/service switch		No
Version as safety switch		No
Version as emergency stop installation		No
Version as reversing switch		No
Number of switches		1
Max. rated operation voltage Ue AC	V	690
Rated operating voltage	V	690 - 690
Rated permanent current lu	А	20
Rated permanent current at AC-23, 400 V	А	13.3
Rated permanent current at AC-21, 400 V	А	20
Rated operation power at AC-3, 400 V	kW	5.5
Rated short-time withstand current lcw	kA	0.32
Rated operation power at AC-23, 400 V	kW	5.5
Switching power at 400 V	kW	5.5
Conditioned rated short-circuit current Iq	kA	6
Number of poles		4
Number of auxiliary contacts as normally closed contact		1
Number of auxiliary contacts as normally open contact		1
Number of auxiliary contacts as change-over contact		0
Motor drive optional		No

Motor drive integrated	No
Voltage release optional	No
Device construction	Built-in device fixed built-in technique
Suitable for ground mounting	Yes
Suitable for front mounting 4-hole	No
Suitable for front mounting centre	No
Suitable for distribution board installation	No
Suitable for intermediate mounting	Yes
Colour control element	Black
Type of control element	Toggle
Interlockable	No
Type of electrical connection of main circuit	Screw connection
Degree of protection (IP), front side	IP00
Degree of protection (NEMA)	Other

# Assets (links)

#### Declaration of CE Conformity 00003075

## Additional product information (links)

Display flip catalog page.	http://ecat.moeller.net/flip-cat/?edition=K115A&startpage=40
Ordering form for SOND switches and SOND front plates(DE_EN)	ftp://ftp.moeller.net/DOCUMENTATION/PDF/MZ008005ZU_Orderform_Customized_Switch.pdf
Ordering form for SOND switches and SOND front plates(DE_EN)	ftp://ftp.moeller.net/DOCUMENTATION/PDF/MZ008006ZU_Orderform_Customized_Switch.pdf