Main switch, P3, 100 A, rear mounting, 3 pole + N, Emergency switching off function, With red rotary handle and yellow locking ring, Lockable in the 0 (Off) position $\frac{1}{2}$



Part no. P3-100/V/SVB/N

024636

EL Number 1417019

(Norway)

(Norway)	
General specifications	
Product name	Eaton Moeller® series P3 Main switch
Part no.	P3-100/V/SVB/N
EAN	4015080246367
Product Length/Depth	150 millimetre
Product height	114 millimetre
Product width	90 millimetre
Product weight	0.488 kilogram
Certifications	IEC/EN 60947-3 UL 60947-4-1 IEC/EN 60947 CSA Class No.: 3211-05 UL File No.: E36332 UL UL UL Category Control No.: NLRV CSA File No.: 012528 CSA-C22.2 No. 60947-4-1-14 VDE 0660 CSA IEC/EN 60204 CSA-C22.2 No. 94 CE
Product Tradename	P3
Product Type	Main switch
Product Sub Type	None
Catalog Notes	Rated Short-time Withstand Current (Icw) for a time of 1 second
Features & Functions	
Features	Version as main switch Version as maintenance-/service switch Version as emergency stop installation
Fitted with:	Red rotary handle and yellow locking ring
Functions	Interlockable Emergency switching off function
Locking facility	Lockable in the 0 (Off) position
Number of poles	4
General information	
Accessories	Auxiliary contact fitted by user.
Degree of protection	NEMA 12
Degree of protection (front side)	IP65
Lifespan, mechanical	100,000 Operations
Mounting method	Rear mounting
Mounting position	As required
Operating frequency	1200 Operations/h
Overvoltage category	III
Pollution degree	3
Rated impulse withstand voltage (Uimp)	6000 V AC
Safe isolation	440 V AC, Between the contacts, According to EN 61140
Safety parameter (EN ISO 13849-1)	B10d values as per EN ISO 13849-1, table C.1
Shock resistance	15 g, Mechanical, According to IEC/EN 60068-2-27, Half-sinusoidal shock 20 ms
Suitable for	Branch circuits, suitable as motor disconnect, (UL/CSA)
Climatic environmental conditions	
Ambient operating temperature - min	-25 °C
• •	

Ambient operating temperature - max	50 °C
Ambient operating temperature (enclosed) - min	-25 °C
Ambient operating temperature (enclosed) - max	40 °C
Climatic proofing	Damp heat, constant, to IEC 60068-2-78
Terminal capacities	Damp heat, cyclic, to IEC 60068-2-30
Terminal capacity	1 x (2.5 - 35) mm², solid or stranded
тепнила сарасцу	2 x (1.5 - 6) mm², flexible with ferrules to DIN 46228 1 x (1.5 - 25) mm², flexible with ferrules to DIN 46228 2 x (2.5 - 10) mm², solid or stranded 14 - 2 AWG, solid or flexible with ferrule
Screw size	M5, Terminal screw
Tightening torque	3 Nm, Screw terminals 26.5 lb-in, Screw terminals
Electrical rating	
Rated breaking capacity at 220/230 V (cos phi to IEC 60947-3)	760 A
Rated breaking capacity at 400/415 V (cos phi to IEC 60947-3)	740 A
Rated breaking capacity at 500 V (cos phi to IEC 60947-3)	880 A
Rated breaking capacity at 660/690 V (cos phi to IEC 60947-3)	520 A
Rated operational current (le) at AC-3, 220 V, 230 V, 240 V	71 A
Rated operational current (le) at AC-3, 380 V, 400 V, 415 V	71 A
Rated operational current (le) at AC-3, 500 V	65 A
Rated operational current (le) at AC-3, 660 V, 690 V	23.8 A
Rated operational current (Ie) at AC-21, 440 V	100 A
Rated operational current (Ie) at AC-23A, 230 V	100 A
Rated operational current (Ie) at AC-23A, 400 V, 415 V	100 A
Rated operational current (Ie) at AC-23A, 500 V	96 A
Rated operational current (Ie) at AC-23A, 690 V	68 A
Rated operational current (Ie) at DC-1, load-break switches I/r = 1 ms	100 A
Rated operational current (Ie) at DC-23A, 24 V	50 A
Rated operational current (Ie) at DC-23A, 48 V	50 A
Rated operational current (Ie) at DC-23A, 60 V	50 A
Rated operational current (Ie) at DC-23A, 120 V	25 A
Rated operational power at AC-3, 380/400 V, 50 Hz	37 kW
Rated operational power at AC-3, 415 V, 50 Hz	37 kW
Rated operational power at AC-3, 500 V, 50 Hz	45 kW
Rated operational power at AC-3, 690 V, 50 Hz	37 kW
Rated operational power at AC-23A, 220/230 V, 50 Hz	30 kW
Rated operational power at AC-23A, 400 V, 50 Hz	55 kW
Rated operational power at AC-23A, 500 V, 50 Hz	55 kW
Rated operational power at AC-23A, 690 V, 50 Hz	55 kW
Rated operational voltage (Ue) at AC - max	690 V
Rated uninterrupted current (Iu)	100 A
Uninterrupted current	Rated uninterrupted current lu is specified for max. cross-section.
Short-circuit rating	
Rated conditional short-circuit current (Iq)	4 kA (Load side) 80 kA (Supply side)
Rated short-time withstand current (Icw)	2 kA
Short-circuit current rating (basic rating)	150A, max. Fuse, SCCR (UL/CSA)
Short-circuit protection rating	10 kA, SCCR (UL/CSA) 100 A gG/gL, Fuse, Contacts
Switching capacity	
Load rating	1.6 x l# (with intermittent operation class 12, 40 % duty factor) 1.3 x l# (with intermittent operation class 12, 60 % duty factor) $2 \times l$ # (with intermittent operation class 12, 25 % duty factor)
Number of contacts in series at DC-23A, 24 V	1
Number of contacts in series at DC-23A, 48 V	2
Number of contacts in series at DC-23A, 60 V	2
Number of contacts in series at DC-23A, 120 V	3

Switching capacity tourillary contracts, general used) Switching capacity tourillary contracts, general used) Switching capacity tour 60V (xos phi to ECEN 10947-3) Switching capacity to 160V (xos phi to ECEN 10947-3) Switching capacity to 160V (xos phi to ECEN 10947-3) Switching capacity to 160V (xos phi to ECEN 10947-3) Switching capacity to 160V (xos phi to ECEN 10947-3) Switching capacity to 160V (xos phi to ECEN 10947-3) Switching capacity to 160V (xos phi to ECEN 10947-3) Switching capacity to 160V (xos phi to ECEN 10947-3) Switching capacity to 160V (xos phi to ECEN 10947-3) Switching capacity and 1517-200 (xos phi to ECEN 10947-3) Switchin	Switching capacity (main contacts, general use)	90 A, Rated uninterrupted current max. (UL/CSA)
Spritching capacity (soutilary contacts, pilet duty) Retermaking capacity to 1080Y foce pile to ECCN 6984-73 Voltage are contact pair in enters Spritching capacity to 1080Y foce pile to ECCN 6984-73 Voltage are contact pair in enters Spritching capacity to 1080Y foce pile to ECCN 6984-73 Assigned motor power at 100/100 (6) Hz, 1-place Assigned motor power at 200/100 (6) H		
Rated making capacity up to 680 V (one pink in EQCN 6807-0) Voltage or criticate per un series Assigned mother percent at 1912 V (50 Hz. 1-phase) Assigned mother percent a		A600 (UL/CSA)
Wildow rating Assigned motor power at 150/20 / 00 Hz / 1-phase Assigned motor power at 150/20 / 00 Hz / 1-phase Assigned motor power at 200/20 W Hz / 1-phase Assigned motor power at 200/20 W Hz / 1-phase Assigned motor power at 200/20 W Hz / 1-phase Assigned motor power at 200/20 W Hz / 1-phase Assigned motor power at 200/20 W Hz / 1-phase Assigned motor power at 200/20 W Hz / 1-phase Assigned motor power at 200/20 W Hz / 1-phase Assigned motor power at 200/20 W Hz / 1-phase Assigned motor power at 200/20 W Hz / 1-phase Assigned motor power at 200/20 W Hz / 1-phase Assigned motor power at 200/20 W Hz / 1-phase Assigned motor power at 200/20 W Hz / 1-phase Assigned motor power at 200/20 W Hz / 1-phase Assigned motor power at 200/20 W Hz / 1-phase Contact creat reliability Assigned motor power at 200/20 W Hz / 1-phase Contact reliability Assigned motor power at 200/20 W Hz / 1-phase Contact reliability Assigned motor power at 200/20 W Hz / 1-phase Contact reliability Assigned motor power at 200/20 W Hz / 1-phase Contact reliability Assigned motor power at 200/20 W Hz / 1-phase Contact reliability Assigned motor power at 200/20 W Hz / 1-phase Contact reliability Assigned motor power at 200/20 W Hz / 1-phase Contact creation of the contact (chinning) of power contacts) Actuator coin Actuator coin Actuator coin Actuator coin Actuator power Explained back adolesiation, current-dependent Pvid Actuator power Design variification Figurine variification Figurine variification Back designation, caurent for specified back discipation (prince power) Actuator coin Actuator power Actuator coin Actuator power Explained back adolesiation, current-dependent Pvid Back designation, caurent for specified back discipation (prince power) Back designation caurent for specified back discipation (prince power) Back designation caurent for specified back discipation (prince power) Back designation caurent for specified back discipation (prince power) Back designation caurent for specifi	Rated making canacity up to 690 V (cos phi to IEC/EN 60947-3)	
Motor rating Assigned motor power at 15/120 V, 50 Hz, 1-phase Assigned motor power at 200/200 V, 50 Hz, 1-phase Assigned motor power at 200/200 V, 50 Hz, 2-phase Assigned motor power at 200/200 V, 50 Hz, 2-phase Assigned motor power at 200/200 V, 50 Hz, 2-phase Assigned motor power at 200/200 V, 50 Hz, 2-phase Assigned motor power at 200/200 V, 50 Hz, 2-phase Assigned motor power at 400/200 V, 50 Hz, 2-phase Assigned motor power at 400/200 V, 50 Hz, 2-phase Assigned motor power at 400/200 V, 50 Hz, 2-phase Assigned motor power at 400/200 V, 50 Hz, 2-phase Assigned motor power at 470/200 V		
Assigned motor power at 115/120 V, 66 Hz, 1-phase Assigned motor power at 2009/28 V 68 Hz, 1-phase Assigned motor power at 2009/28 V 68 Hz, 1-phase Assigned motor power at 2009/28 V 68 Hz, 2-phase Assigned motor power at 2009/28 V 68 Hz, 3-phase Assigned motor power at 2009/28 V 68 Hz, 3-phase Assigned motor power at 2009/28 V 68 Hz, 3-phase Assigned motor power at 2009/28 V 68 Hz, 3-phase Assigned motor power at 2009/28 V 68 Hz, 3-phase Assigned motor power at 4009/28 V 68 Hz, 3-phase Contract Contract Contract circuit reliability I failure per 100,000 switching operations statistically determined, at 24 V 5C, 10 m/s. Assigned motor power at 570,000 V 68 Hz, 3-phase Contract circuit reliability I failure per 100,000 switching operations statistically determined, at 24 V 5C, 10 m/s. Assigned motor power at 570,000 V 68 Hz, 3-phase Contract Contract Contract circuit reliability I failure per 100,000 switching operations statistically determined, at 24 V 5C, 10 m/s. Number of assistiny contacts (name) v con		
Assigned mutur power at 200,200 W, 50 Mr. 1 phoses Assigned mutur power at 200,200 W, 50 Mr. 2 phoses Assigned mutur power at 200,200 W, 50 Mr. 3 phoses Assigned mutur power at 200,200 W, 50 Mr. 3 phose Assigned mutur power at 200,200 W, 50 Mr. 3 phose Assigned mutur power at 200,200 W, 50 Mr. 3 phose Assigned mutur power at 200,200 W, 50 Mr. 3 phose Assigned mutur power at 200,200 W, 50 Mr. 3 phose Contacts Contract circuit reliability Mumber of auxiliary contacts (change-over contacts) Number of aux		FUR
Assigned motor power at 2000/26 V 50 Pt.; I-phase Assigned motor power at 2000/26 V 50 Pt.; I-phase Assigned motor power at 2000/26 V 50 Pt.; I-phase Assigned motor power at 2000/26 V 50 Pt.; I-phase Assigned motor power at 2000/26 V 50 Pt.; I-phase Assigned motor power at 2000/26 V 50 Pt.; I-phase Assigned motor power at 575500	<u> </u>	
Assigned motor power at 2002-09 V, 60 Hz, 3-phase 25 HP Assigned motor power at 2002-09 V, 60 Hz, 3-phase 29 HP Assigned motor power at 2002-09 V, 60 Hz, 3-phase 99 HP Assigned motor power at 2002-09 V, 60 Hz, 3-phase 99 HP Assigned motor power at 2002-09 V, 60 Hz, 3-phase 99 HP Assigned motor power at 2002-09 V, 60 Hz, 3-phase 99 HP Assigned motor power at 2002-09 V, 60 Hz, 3-phase 99 HP Assigned motor power at 2002-09 V, 60 Hz, 3-phase 99 HP Assigned motor power at 2002-09 V, 60 Hz, 3-phase 99 HP Assigned motor power at 2002-09 V, 60 Hz, 3-phase 99 HP Assigned motor power at 2002-09 V, 60 Hz, 3-phase 99 HP Assigned motor power at 2002-09 V, 60 Hz, 3-phase 99 HP Assigned motor power at 2002-09 V, 60 Hz, 3-phase 99 HP Assigned motor power at 2002-09 V, 60 Hz, 3-phase 99 Hz, 40 Hz, 4		
Assigned motor power at 230/240 V, 60 Hz, 3-phase Assigned motor power at 230/240 V, 60 Hz, 3-phase Assigned motor power at 230/240 V, 60 Hz, 3-phase Assigned motor power at 575600 V, 60 Hz, 3-phase Control circuit reliability Number of auxiliary contacts (change over contacts) Number of auxil		
Assigned motor power at \$95,900 V, 60 Hz, 3-phase Assigned motor power at \$95,900 V, 60 Hz, 3-phase Control circuit reliability Number of auxiliary contacts (change-over contacts) Actuator color Actuator to dazoliary contacts (change-over contacts) Actuator to for Actuator to for Actuator to for Actuator to for Actuator type Doiry coupling retary drive Dor coupli		
Assigned motor power at 575,000 V, 60 Hz, 3-phase Central circuit reliability Number of auxiliary contacts (change-over contacts) Number of auxiliary contacts (change-over contacts) Number of auxiliary contacts (change-over contacts) Number of auxiliary contacts (normally closed contacts) Number of auxiliary contacts (normally open contacts) Actuator Actuator Actuator Actuatory Design verificaction Equipment head dissipation, current-dependent Pvid Head dissipation capacity Pdias Head dissipation open pole, current-dependent Pvid Particular dissipation, on-current-dependent Pvid Particular dissi		
Control circuit reliability Control circuit reliability Rumber of auxiliary contacts (change-over contacts) Rumber of auxiliary contacts (change-over contacts) Rumber of auxiliary contacts (normally closed contects) Red Actuator color Actuator color Actuator type Does coupling rotary drive Design verification Equipment bead dissipation, current-dependent Pvid Pleast dissipation capacity Pdiss Head dissipation per pole, current-dependent Pvid Pleast dissipation on probe, current-dependent Pvid Pleast dissipation on probe, current-dependent Pvid Pleast dissipation on on-current cependent Pvid Pleast dis		
Control circuit reliability 1 failure per 100,000 awtiching operations statistically determined, at 24 V DC, 10 nnA) Number of auxiliary contacts (hormally closed contacts) 0 Number of auxiliary contacts (normally closed contacts) 0 Number of auxiliary contacts (normally open contacts) 0 Actuator very contacts (normally open contacts) 0 Bad 0 Actuator very contacts (normally open contacts) 0 Actuator very contacts (normally open contacts) 0 Bad 0 Actuator very contacts (normally open contacts) 0 Actuator very contacts (normally open contacts) 0 Bad 0 Actuator very contacts (normally open contacts) 0 Bad 0 Actuator very contacts (normally open contacts) 0 Bad 0 Actuator very contacts (normally open contacts) 0 Bad 0 Actuator very contacts (normally open contacts) 0 Bad 0 Bad 0 Actuator very contacts (normally open contacts) 0 Bad 0 Bad 0 Contacts (normally of very contacts) 0 Bad 0 Bad 0 Bad 0 Contacts (normally of very contacts) 0 Bad 0		75 HP
Number of auxiliary contacts (change-over contacts) Number of auxiliary contacts (normally closed contacts) O Cactuator Actuator of Auxiliary contacts (normally open contacts) Actuator type Design verification Equipment heat dissipation, current-dependent Pvid Heat dissipation capacity Pdiss Rated operational current for specified heat dissipation (nurrent-dependent Pvid Rated operational current for specified heat dissipation (nurrent-dependent Pvid Rated operational current for specified heat dissipation (nurrent-dependent Pvid Rated operational current for specified heat dissipation (nurrent-dependent Pvid Rated operational current for specified heat dissipation (n) Rated operational current for specified heat of the operation of specified heat of the operation of specified heat of specified hea	Contacts	
Number of auxiliary contacts (normally closed contacts) Number of auxiliary contacts (normally open contacts) Actuator Actuator over Actuator type Design verification Equipment heat dissipation, current-dependent Pvid Not dissipation or prolix, current-de		mA)
Number of auxiliary contacts (normally open contacts) Actuator Color Actuator color Actuator type Door coupling rotary drive Design verification Equipment heat dissipation, current-dependent Pvid Heat dissipation, current-dependent Pvid Heat dissipation per pole, current-dependent Pvid Actuator type Door Coupling rotary drive Design verification Equipment heat dissipation, current-dependent Pvid Heat dissipation per pole, current-dependent Pvid Actuator (Pvid Heat dissipation data for equirements. Wees the product standard's requirements. Wees the product standard's requirements. Wees the product standard's requirements. 102.5 Heat heat value (UV) radiation UV resistance only in connection with protective shield. 102.5 Horosportation of assamblies Does not apply, since the entire switchpear needs to be evaluated. 103.6 Horosportation of assamblies Does not apply, since the entire switchpear needs to be evaluated. 104.1 Inernal electrical circuits and connections 105.6 Protection aga		
Actuator color Actuator type Design verification Equipment heat dissipation, current-dependent Pvid Heat dissipation, current-dependent Pvid Heat dissipation apacity Pdiss Heat dissipation per pole, current dependent Pvid Heat dissipation per pole, current dependent Pvid Heat dissipation per pole, current dependent Pvid Heat dissipation per pole, current-dependent Pvid Heat dissipation per pole, current-dependent Pvid Heat dissipation, non-current-dependent Pvid Heat dissipation of thermal stability of enclosures Heat the product standard's requirements. Heats the product standard's requirements. Lip 2.3 Verification of turta-violet (UV) radiation Heats the product standard's requirements. Lip 2.5 Lifting Does not apply, since the entire switchgear needs to be evaluated. Lip 2.5 Inscriptions Heats the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Lip 2.5 Inscriptions Heats the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Lip 2.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. Lip 2.5 Protection of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. Lip 2.5 Protection against electric advices and components Lip 2.5 Protection against electric advices and components Lip 2.5 Protection against electric advices and components Lip 3.5 Protection against electric advices and components Lip 4.5 Protection against electric advices and components Lip 4.5 Protection against electric advices and components Lip 4.5 Protection		
Actuator color Actuator type Design verification Equipment heat dissipation, current-dependent Pvid Heat dissipation apparely Pdiss OW Heat dissipation per pole, current-dependent Pvid Rated operational current for specified heat dissipation (In) Straic heat dissipation, non-current-dependent Pvid Rated operational current for specified heat dissipation (In) OW Rated operational current for specified heat dissipation (In) OW Rated operational current for specified heat dissipation (In) OW Rated operational current for specified heat dissipation (In) OW Rated operational current for specified heat dissipation (In) OW Rated operational current for specified heat dissipation (In) OU Rated operational current for specified heat dissipation (In) OU Rated operational current for specified heat dissipation (In) OU Rest the product standard's requirements. Meets the product standard's requirements. OU Resistance to ultra-violet (IV) radiation OU Resistance only in connection with protective shield. Oues not apply, since the entire switchgear needs to be evaluated. Oues not apply, since the entire switchgear needs to be evaluated. Oues not apply, since the entire switchgear needs to be evaluated. Oues not apply, since the entire switchgear needs to be evaluated. Oues not apply, since the entire switchgear needs to be evaluated. Oues not apply, since the entire switchgear needs to be evaluated. Oues not apply, since the entire switchgear needs to be evaluated. Oues not apply, since the entire switchgear needs to be evaluated. Oues not apply, since the entire switchgear needs to be evaluated. Oues not apply, since the entire switchgear needs to be evaluated. Oues not apply, since the entire switchgear needs to be evaluated. Oues not apply, since the entire switchgear needs to be evaluated. Oues not apply, since the entire switchgear needs to be evaluated. Oues not apply, since the entire switchgear needs to be evaluated. Oues not apply, since the entire switchgear needs to be evaluated. Oues no		0
Design verification Equipment heat dissipation, current-dependent Pvid Heat dissipation capacity Pdiss OW Heat dissipation capacity Pdiss OW Heat dissipation per pole, current-dependent Pvid 7.5 W Rated operational current for specified heat dissipation (In) Static heat dissipation, non-current-dependent Pvs OW 10.2.2 Corrosion resistance Meets the product standard's requirements. 10.2.3.1 Verification of thermal stability of enclosures Meets the product standard's requirements. 10.2.3.2 Verification of resistance of insulating materials to normal heat 10.2.3.3 Resists. of insul. mat. to abnormal heat/fire by internal elect. effects 10.2.4 Resistance to ultra-violat (IUV) radiation 10.2.5 Lifting Obes not apply, since the entire switchgear needs to be evaluated. 10.2.7 Inscriptions Meets the product standard's requirements. 10.2.8 Mechanical impact Obes not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and creepage distances Meets the product standard's requirements. 10.5 Protoction against electric shock Obes not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections In the panel builder's responsibility. 10.8 Connections for external conductors Is the panel builder's responsibility. 10.9 Protoction against electric shock In the panel builder's responsibility. 10.9 Protoction subtracting devices and of insulating material 10.1 Short-circuit rating Step panel builder's responsibility. 10.2 Internal electrical circuits and connections Is the panel builder's responsibility. 10.3 Impulse withstand voltage In panel builder's responsibility. 10.4 Electromapnetic compatibility 10.5 Electromapnetic compatibility In panel builder's responsibility. 10.5 The panel builder's responsibility. 10.6 Electromapnetic compatibility In the panel builder's responsibility. 10.7 The panel builder's responsibility. 10.8 The panel builder's responsibili	Actuator	
Equipment heat dissipation, current-dependent Pvid 0W Heat dissipation, capacity Pdiss 0W Heat dissipation per pole, current-dependent Pvid 7.5 W Heat dissipation per pole, current-dependent Pvid 7.5 W Rated operational current for specified heat dissipation (In) 100 A Static heat dissipation, non-current-dependent Pvis 0W 10.22 Corrosion resistance Meets the product standard's requirements. 10.23.1 Verification of thermal stability of enclosures Meets the product standard's requirements. 10.23.2 Verification of resistance of insulating materials to normal heat 10.23.2 Verification of resistance of ultra-violet (UV) radiation Weets the product standard's requirements. 10.24 Resistance to ultra-violet (UV) radiation UV resistance enably in connection with protective shield. 10.25 Lifting Does not apply, since the entire switchgear needs to be evaluated. 10.26 Inscriptions Meets the product standard's requirements. 10.27 Inscriptions Does not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and creepage distances Meets the product standard's requirements. 10.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. 10.7 Internal electrical circuits and connections Section of the entire switchgear needs to be evaluated. 10.8 Connections for external conductors Section of the entire switchgear needs to be evaluated. 10.9 Prover-frequency electric strength Section of external conductors Section of external conductors Section of the entire switchgear needs to be evaluated. 10.9 Prover-frequency electric strength Section of external conductors Section Section Section Section Section Section Section Section Section Se	Actuator color	Red
Equipment heat dissipation, current-dependent Pvid Heat dissipation capacity Pdiss Rated operational current for specified heat dissipation (In) Rated operational current for specified heat dissipation (In) 100 A Static heat dissipation, non-current-dependent Pvid 102.2 Corrosion resistance Meets the product standard's requirements. 102.3.1 Verification of thermal stability of enclosures Meets the product standard's requirements. 102.3.2 Verification of resistance of insulating materials to normal heat 102.3.3 Resist of insul. mat. to abnormal heat/fire by internal elect. effects 102.4 Resistance to ultra-violet (UV) radiation 102.5 Lifting Does not apply, since the entire switchgarn needs to be evaluated. 102.5 Inscriptions Meets the product standard's requirements. We standard's requirements. UV resistance only in connection with protective shield. 102.5 Inscriptions Meets the product standard's requirements. Meets the product standard's requirements. 102.5 Lifting Does not apply, since the entire switchgarn needs to be evaluated. 102.6 Mechanical impact Does not apply, since the entire switchgarn needs to be evaluated. 103.1 Portoction against electric shock Does not apply, since the entire switchgarn needs to be evaluated. 104.1 Clearances and creepage distances Meets the product standard's requirements. Does not apply, since the entire switchgarn needs to be evaluated. 105.1 Internal electrical circuits and connections In the panel builder's responsibility. 108.2 Power-fraquency electric strongth Some of the panel builder's responsibility. 109.3 Tenternal conductors In panel builder's responsibility. 109.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.10 Temperature rise 10.11 Short-circuit rating Some panel builder's responsibility. In panel builder's responsibility. In panel builder's responsibility. In the panel	Actuator type	Door coupling rotary drive
Heat dissipation capacity Pdiss Heat dissipation per pole, current-dependent Pvid 7.5 W Rated operational current for specified heat dissipation (In) 100 A Static heat dissipation, non-current-dependent Pvs 0 W Meets the product standard's requirements. 102.3.1 Verification of thermal stability of enclosures 102.3.3 Verification of resistance of insulating materials to normal heat 102.3.3 Verification of resistance of insulating materials to normal heat 102.3.3 Resists. of insul. mat. to abnormal heat/fire by internal elect. effects 102.4 Resistance to ultra-violet (UV) radiation 102.5 Lifting 102.6 Mechanical impact 102.6 Mechanical impact 102.7 Inscriptions 102.8 Dees not apply, since the entire switchgear needs to be evaluated. 102.7 Inscriptions 102.8 Dees not apply, since the entire switchgear needs to be evaluated. 104.4 Clearances and creepage distances 105.4 Protection against electric shock 106.5 Incorporation of switching devices and components 107.7 Internal electric circuits and connections 108.1 Connections for external conductors 109.3 Impulse withstand voltage 109.4 Testing of enclosures made of insulating material 109.4 Testing of enclosures made of insulating material 109.5 Top over-frequency electric strength 109.4 Testing of enclosures made of insulating material 109.5 The panel builder's responsibility. 109.6 The panel builder's responsibility. 109.7 The panel builder's responsibility. 109.8 The panel builder's responsibility. 109.9 The panel builder's responsibility. 109.1 The panel builder's responsibility. 109.2 The panel builder's responsibility. 109.3 The panel builder's responsibility. The specifications for the switchgear must be observed. 10.11 Short-circuit rating 10.13 Mechanical function 10.13 Mechanical function	Design verification	
Heat dissipation per pole, current-dependent Pvid Rated operational current for specified heat dissipation (In) 100 A Static heat dissipation, non-current-dependent Pvs 10.2.2 Corrosion resistance Meets the product standard's requirements. 102.3.1 Verification of tremal stability of enclosures Meets the product standard's requirements. 102.3.2 Verification of resistance of insulating materials to normal heat 102.3.3 Resist. of insul. mat. to abnormal heatffrie by internal elect. effects 102.4 Resistance to ultra-violet (UV) radiation 102.5 Lifting Does not apply, since the entire switchgear needs to be evaluated. 102.5 Inscriptions Meets the product standard's requirements. 102.6 Mechanical impact Does not apply, since the entire switchgear needs to be evaluated. 102.7 Inscriptions Meets the product standard's requirements. 103.2 Degree of protection of assemblies Does not apply, since the entire switchgear needs to be evaluated. 104.4 Testing and creepage distances Meets the product standard's requirements. 105.4 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 106.6 Incorporation of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. 106.7 Internal electrical circuits and connections Is the panel builder's responsibility. 108.2 Power-frequency electric strength Is the panel builder's responsibility. 109.3 Impulse withstand voltage Is the panel builder's responsibility. 109.4 Testing of enclosures made of insulating material 10.10 Temperature rise The panel builder's responsibility. 10.11 Short-circuit rating 10.11 Short-circuit rating 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	Equipment heat dissipation, current-dependent Pvid	0 W
Rated operational current for specified heat dissipation (In) Static heat dissipation, non-current-dependent Pvs 0 W 10.22 Corrosion resistance Meets the product standard's requirements. 10.23.1 Verification of thermal stability of enclosures Meets the product standard's requirements. 10.23.2 Verification of resistance of insulating materials to normal heat 10.23.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects 10.24 Resistance to ultra-violet (UV) radiation 10.25 Lifting Does not apply, since the entire switchgear needs to be evaluated. 10.27 Inscriptions Does not apply, since the entire switchgear needs to be evaluated. 10.24 Clearances and creepage distances 10.3 Perotection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.6 Internal electrical circuits and connections 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9 Romeer-frequency electric strength 10.9 Romeer-frequency electric strength 10.9 Internal electrical circuits and connections 10.9 Protection against electric strength 10.9 Internal electrical circuits and connections 1 sthe panel builder's responsibility. 10.9 Tennel publication for external conductors 1 sthe panel builder's responsibility. 10.9 Tennel publication for external conductors 1 sthe panel builder's responsibility. 1 sthe panel builder's responsibility. The specifications for the switchgear must be observed. 10.11 Short-circuit rating 1 sthe panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	Heat dissipation capacity Pdiss	0 W
Static heat dissipation, non-current-dependent Pvs 10.2.2 Corrosion resistance 10.2.3.1 Verification of thermal stability of enclosures 10.2.3.2 Verification of resistance of insulating materials to normal heat 10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects 10.2.4 Resistance to ultra-violet (UV) radiation 10.2.5 Lifting 10.2.6 Mechanical impact 10.2.7 Inscriptions 10.3 Degree of protection of assemblies 10.4 Clearances and creepage distances 10.5 Frotection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9 Power-frequency electric strength 10.9 A Testing of enclosures made of insulating material 10.10 Electromagnetic compatibility 10.11 Short-circuit rating 10.13 Mechanical function 10.13 Mechanical function 10.14 Mechanical function 10.15 Mechanical function 10.16 Incorporation of switching devices and components 10.17 Internal electric strength 10.18 Lepanel builder's responsibility. 10.19 Internal electric strength 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.14 Mechanical function 10.15 Mechanical function 10.16 Mechanical function 10.17 Internal electrical circuits and connections 10.18 Lepanel builder's responsibility. 10.19 A Testing of enclosures made of insulating material 10.10 Temperature rise 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.14 Mechanical function 10.15 Mechanical function 10.16 Mechanical function 10.17 Mechanical function 10.18 Mechanical function 10.19 Meets the product standard's requirements. 10.10 Meets the product standard's requirements. 10.10 Meets the product standard's requirements. 10.10 Meets the product standard's requirements. 10.11 Meets the product standard's requirements. 10.12 Meets the product standard's requirements. 10.14	Heat dissipation per pole, current-dependent Pvid	7.5 W
10.2.2 Corrosion resistance 10.2.3.1 Verification of thermal stability of enclosures 10.2.3.2 Verification of resistance of insulating materials to normal heat 10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects 10.2.4 Resistance to ultra-violet (UV) radiation 10.2.5 Lifting 10.2.6 Mechanical impact 10.2.7 Inscriptions 10.3 Degree of protection of assemblies 10.4 Clearances and creepage distances 10.4 Clearances and creepage distances 10.5 Protection against electric shock 10.5 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9 Ower-frequency electric strength 10.9 In Paper Builder's responsibility. 10.9 The panel builder's responsibility. 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.13 Mechanical function 10.14 Mechanical function 10.15 Protection of insulations of the switchgear must bobserved. 10.16 Incorporation of switching devices and components 10.17 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9 Internal electric strength 10.9 Internal electric strength 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.13 Mechanical function 10.14 Electromagnetic compatibility 10.15 Electromagnetic compatibility 10.16 Short-circuit rating 10.17 Electromagnetic compatibility 10.18 Let panel builder's responsibility. The specifications for the switchgear must bobserved. 10.19 Electromagnetic compatibility 10.19 Electromagnetic compatibility 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function	Rated operational current for specified heat dissipation (In)	100 A
Meets the product standard's requirements. 10.2.3.2 Verification of thermal stability of enclosures 10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects 10.2.4 Resistance to ultra-violet (UV) radiation 10.2.5 Lifting 10.2.6 Mechanical impact 10.2.7 Inscriptions 10.3.0 Begree of protection of assemblies 10.4 Clearances and creepage distances 10.4 Clearances and creepage distances 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9 Power-frequency electric strength 10.9.1 Design of enclosures made of insulating material 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.13 Mechanical function Meets the product standard's requirements. Meets the product standard's requirements. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Is the panel builder's responsibility. It is the panel builder's responsibility. The specifications for the switchgear must be observed. In the panel builder's responsibility. The specifications for the switchgear must be observed.	Static heat dissipation, non-current-dependent Pvs	0 W
102.3.2 Verification of resistance of insulating materials to normal heat 102.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects 102.4 Resistance to ultra-violet (UV) radiation 102.5 Lifting 102.5 Lifting 102.6 Mechanical impact 102.7 Inscriptions 103.0 Begree of protection of assemblies 104.0 Clearances and creepage distances 105.4 Protection against electric shock 105.6 Incorporation of switching devices and components 105.7 Internal electrical circuits and connections 105.8 Connections for external conductors 106.8 Connections for external conductors 107.1 Internal electrical circuits and connections 108.4 Clearances and creepage distances 109.5 Protection against electric shock 109.6 Incorporation of switching devices and components 109.7 Internal electrical circuits and connections 109.7 Internal electrical circuits and connections 109.7 Internal electrical circuits and connections 109.8 Connections for external conductors 109.9 Power-frequency electric strength 109.9 Power-frequency electric strength 109.9 Testing of enclosures made of insulating material 109.4 Testing of enclosures made of insulating material 109.4 Testing of enclosures made of insulating material 109.6 Incorporation of switching devices 109.7 Electromagnetic compatibility 109.8 Testing of enclosures made of insulating material 109.9 Temperature rise 109.1 Step panel builder's responsibility. 109.1 Step panel builder's responsibility. 109.2 Power-frequency electric strength 109.4 Testing of enclosures made of insulating material 109.5 The panel builder's responsibility. 109.6 The panel builder's responsibility. The specifications for the switchgear must be observed. 109.12 Electromagnetic compatibility 109.13 Mechanical function 109.13 Mechanical function	10.2.2 Corrosion resistance	Meets the product standard's requirements.
10.2.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects 10.2.4 Resistance to ultra-violet (UV) radiation 10.2.5 Lifting 10.2.6 Mechanical impact 10.2.7 Inscriptions 10.3 Dees not apply, since the entire switchgear needs to be evaluated. 10.2.7 Inscriptions 10.4 Clearances and creepage distances 10.5 Protection against electric shock 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9.2 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.10 Temperature rise 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.13 Mechanical function Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Is the panel builder's responsibility. Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.2.3.1 Verification of thermal stability of enclosures	Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation 10.2.5 Lifting 10.2.6 Mechanical impact 10.2.6 Mechanical impact 10.2.7 Inscriptions 10.3 Degree of protection of assemblies 10.4 Clearances and creepage distances 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9.2 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.1 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.13 Mechanical function 10.14 Clearances and creepage distances 10.25 Protection against electric shock 10.26 not apply, since the entire switchgear needs to be evaluated. 10.5 Protection against electric shock 10.6 nor apply, since the entire switchgear needs to be evaluated. 10.6 nor apply, since the entire switchgear needs to be evaluated. 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9 Power-frequency electric strength 10.9 Power-frequency electric strength 10.9 Is the panel builder's responsibility. 10.9 The panel builder's responsibility. 10.10 Temperature rise 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.13 Mechanical function 10.14 Residence on the product standard's requirements, provided the information in the instruction	10.2.3.2 Verification of resistance of insulating materials to normal heat	Meets the product standard's requirements.
10.2.5 Lifting Does not apply, since the entire switchgear needs to be evaluated. 10.2.6 Mechanical impact Does not apply, since the entire switchgear needs to be evaluated. 10.2.7 Inscriptions Meets the product standard's requirements. 10.3 Degree of protection of assemblies Does not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and creepage distances Meets the product standard's requirements. 10.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. 10.7 Internal electrical circuits and connections Is the panel builder's responsibility. 10.8 Connections for external conductors Is the panel builder's responsibility. 10.9.2 Power-frequency electric strength Is the panel builder's responsibility. 10.9.3 Impulse withstand voltage Is the panel builder's responsibility. 10.10 Temperature rise The panel builder's responsibility. 10.10 Temperature rise The panel builder's responsibility. 10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects	Meets the product standard's requirements.
10.26 Mechanical impact 10.27 Inscriptions Meets the product standard's requirements. 10.3 Degree of protection of assemblies 10.4 Clearances and creepage distances Meets the product standard's requirements. 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.13 Mechanical function 10.13 Mechanical function 10.13 Mechanical function 10.14 Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Is the panel builder's responsibility. Is the panel builder's responsibility. The panel builder is responsibility. The specifications for the switchgear must be observed. Is the panel builder's responsibility. The specifications for the switchgear must be observed. The device meets the requirements, provided the information in the instruction of the device of the switchgear must be observed.	10.2.4 Resistance to ultra-violet (UV) radiation	UV resistance only in connection with protective shield.
10.2.7 Inscriptions Meets the product standard's requirements. 10.3 Degree of protection of assemblies Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. 10.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. 10.7 Internal electrical circuits and connections Is the panel builder's responsibility. 10.8 Connections for external conductors Is the panel builder's responsibility. 10.9.2 Power-frequency electric strength Is the panel builder's responsibility. 10.9.3 Impulse withstand voltage Is the panel builder's responsibility. 10.10 Temperature rise The panel builder's responsibility. 10.10 Temperature rise The panel builder is responsibility. The specifications for the switchgear must be observed. 10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility The device meets the requirements, provided the information in the instruction.	10.2.5 Lifting	Does not apply, since the entire switchgear needs to be evaluated.
Does not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and creepage distances Meets the product standard's requirements. 10.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. 10.7 Internal electrical circuits and connections Is the panel builder's responsibility. 10.8 Connections for external conductors Is the panel builder's responsibility. 10.9.1 Testing of enclosures made of insulating material 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise The panel builder's responsibility. 10.11 Short-circuit rating Is the panel builder's responsibility. 10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.2.6 Mechanical impact	Does not apply, since the entire switchgear needs to be evaluated.
Meets the product standard's requirements. 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9 Power-frequency electric strength 10.9.1 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Is the panel builder's responsibility. Is the panel builder is responsibility. The panel builder is responsibility. The specifications for the switchgear must be observed. In the panel builder's responsibility. The specifications for the switchgear must be observed. In the device meets the requirements, provided the information in the instruction.	10.2.7 Inscriptions	Meets the product standard's requirements.
10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9.2 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.13 Mechanical function 10.14 Education of switching devices and components 10.15 Protection against electric sto be evaluated. 10.16 Incorporation of switching devices and components 10.17 Internal electrical circuits and connections 10.18 the panel builder's responsibility. 10.19 Is the panel builder's responsibility. 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.14 Electromagnetic reports in the instruction of the device meets the requirements, provided the information in the instruction	10.3 Degree of protection of assemblies	Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 1s the panel builder's responsibility. 10.8 Connections for external conductors 1s the panel builder's responsibility. 10.9.2 Power-frequency electric strength 10.9.3 Impulse withstand voltage 1s the panel builder's responsibility. 1s the panel builder's responsibility. The specifications for the switchgear must be observed. 1s the panel builder's responsibility. The specifications for the switchgear must be observed. 1s the panel builder's responsibility. The specifications for the switchgear must be observed. 1s the panel builder's responsibility. The specifications for the switchgear must be observed. 1s the panel builder's responsibility. The specifications for the switchgear must be observed. 1s the panel builder's responsibility. The specifications for the switchgear must be observed.	10.4 Clearances and creepage distances	Meets the product standard's requirements.
10.7 Internal electrical circuits and connections 1s the panel builder's responsibility. 10.8 Connections for external conductors 1s the panel builder's responsibility. 10.9.2 Power-frequency electric strength 1s the panel builder's responsibility. 10.9.3 Impulse withstand voltage 1s the panel builder's responsibility. 1o.9.4 Testing of enclosures made of insulating material 1s the panel builder's responsibility. 1o.10 Temperature rise The panel builder is responsibile for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. 1o.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 1o.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 1o.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.5 Protection against electric shock	Does not apply, since the entire switchgear needs to be evaluated.
10.8 Connections for external conductors 10.9.2 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.18 the panel builder's responsibility. The specifications for the switchgear must be observed. 10.19 Mechanical function 10.10 Temperature rise calculation in the instruction	10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.9.2 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function Is the panel builder's responsibility. Is the panel builder's responsibility. The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.13 Mechanical function Is the panel builder's responsibility. The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. 10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.10 Temperature rise The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. 10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
provide heat dissipation data for the devices. 10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
observed. 10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must b observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.10 Temperature rise	
observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must b observed.
	10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must b observed.
	10.13 Mechanical function	· · · · · ·

Technical data ETIM 9.0

Low-voltage industrial components (EG000017) / Switch disconnector (low voltage) (EC000216)

3/4

Electric engineering, automation, process control engineering / Low-voltage switch technolog [AKF060018])	y / Off-load s	witch, circuit breaker, control switch / Switch disconnector (ecl@ss13-27-37-14-03
Version as main switch		Yes
Version as maintenance-/service switch		Yes
Version as safety switch		No
Version as emergency stop installation		Yes
Version as reversing switch		No
Number of switches		1
Max. rated operation voltage Ue AC	V	690
Rated operating voltage	V	690 - 690
Rated permanent current lu	Α	100
Rated permanent current at AC-23, 400 V	Α	100
Rated permanent current at AC-21, 400 V	Α	100
Rated operation power at AC-3, 400 V	kW	37
Rated short-time withstand current lcw	kA	2
Rated operation power at AC-23, 400 V	kW	55
Switching power at 400 V	kW	55
Conditioned rated short-circuit current Iq	kA	80
Number of poles		4
Number of auxiliary contacts as normally closed contact		0
Number of auxiliary contacts as normally open contact		0
Number of auxiliary contacts as change-over contact		0
Motor drive optional		No
Motor drive integrated		No
Voltage release optional		No
Device construction		Built-in device fixed built-in technique
Suitable for floor mounting		No
Suitable for front mounting 4-hole		No
Suitable for front mounting centre		No
Suitable for distribution board installation		No
Suitable for intermediate mounting		No
Colour control element		Red
Type of control element		Door coupling rotary drive
Interlockable		Yes
Type of electrical connection of main circuit		Screw connection
With pre-assembled cabling		No
Degree of protection (IP), front side		IP65
Degree of protection (NEMA)		12
Width	mm	90
Height	mm	114
Depth	mm	150
Width in number of modular spacings		