DATASHEET - XN-2A0-I(0/4...20MA)



Analog output module XI/ON, 24 V DC, 2AO (0/4 to 20mA)

Part no. XN-2A0-I(0/4...20MA)
Catalog No. 140146

EL-Nummer (Norway) 4520643



Delivery program

- correct production	
Function	XI/ON I/O modules
Function	XN Slice module
Short Description	2 Analog outputs 0/4 to 20 mA
For use with	XN-S3T-SBB XN-S3S-SBB

Technical data

_				
14	n	Δ	rs	al

Standards			EN 61000-6-2 EN 61000-6-4 EN 61131-2
Potential isolation			Yes, through optocoupler
Ambient temperature			
Ambient temperature, operation		°C	0 - +55
Storage, transport	8	°C	-25 - +85
Relative humidity			
Relative humidity			5 - 95 % (indoor), Level RH-2, no condensation (for storage at 45°C)
Ambient conditions, mechanical			
Degree of Protection			IP20
Harmful gases		ppm	SO_2 : 10 (rel. humidity < 75%, no condensation) H ₂ S: 1.0 (rel. humidity < 75 %,no condensation)
Vibration resistance, operating conditions			according to IEC/EN 60068-2-6
Mechanical shock resistance		g	according to IEC 60068-2-27
Continuous shock resistance (IEC/EN 60068-2-29)			According to IEC 60068-2-29
Drop and topple			According to IEC 60068-2-31, free fall according to IEC 60068-2-32
Electromagnetic compatibility (EMC)			
ESD	Air/contact discharge	kV	EN 61000-4-2
Electromagnetic fields	(0.081) / (1,42) / (2 2,7) GHz	V/m	EN 61100-4-2
Burst			EN 61100-4-4
Surge			EN 61100-4-5
Radiated RFI		V	EN 61100-4-6
Emitted interference (radiated, high frequency)	(30230 MHz) / (2301000 MHz)	dB	EN 55016-2-3
Voltage fluctuations/voltage dips			EN 61131-2
Type test			to EN 61131-2
Approvals			CE, cULus
Other technical data (sheet catalogue)			Technical Data
Analog input modules			
Managed variables			Current

Measured variables		Current
Channels	Number	2

Detection the continue to a series of			04 V DC
Rated voltage through supply terminal	UL		24 V DC
Rated current consumption from supply terminal	IL	mA	50
Rated current consumption from module bus	I _{MB}	mA	≤ 40
Heat dissipation		W	normally 1
Offset error		%	0.1
Basic error limit at 23 °C		%	0.2
Temperature coefficient			150 ppm/°C of full scale
Measured value representation			16-bit signed integer 12-bit full range left-justified
Analog output modules			
Measured variables			Current
Channels		Number	2
Rated voltage through supply terminal	U_{L}		24 V DC
Rated current consumption from supply terminal	IL	mA	50
Rated current consumption from module bus	I _{MB}	mA	≤ 40
Heat dissipation		W	normally 1
Output current		mA	0/4 - 20
Load resistance			
Resistive load		Ω	< 450
Inductive load		h	< 0.001
Transfer frequency		Hz o/	200
Offset error		%	0.1
Basic error limit at 23 °C		%	0.2
Temperature coefficient			150 ppm/°C of full scale
Settling time			
Resistive load		ms	2
Inductive load		ms	2
Capacitive load		ms	0.5
		1115	0.5
Measured value representation		IIIS	0.5 16-bit signed integer 12-bit full range left-justified
		1115	16-bit signed integer
Measured value representation		Number	16-bit signed integer 12-bit full range left-justified
Measured value representation Digital outputs	U _L		16-bit signed integer 12-bit full range left-justified
Measured value representation Digital outputs Channels	U _L		16-bit signed integer 12-bit full range left-justified 2
Measured value representation Digital outputs Channels Rated voltage through supply terminal Rated current consumption from the supply terminal (at load current = 0 mA)	IL	Number	16-bit signed integer 12-bit full range left-justified 2 24 V DC
Measured value representation Digital outputs Channels Rated voltage through supply terminal Rated current consumption from the supply terminal (at load current = 0 mA) Rated current consumption from module bus	I _L	Number mA mA	16-bit signed integer 12-bit full range left-justified 2 24 V DC 50 ≤ 40
Measured value representation Digital outputs Channels Rated voltage through supply terminal Rated current consumption from the supply terminal (at load current = 0 mA) Rated current consumption from module bus Power loss	IL	Number mA mA W	16-bit signed integer 12-bit full range left-justified 2 24 V DC 50 ≤ 40 Normally 1
Measured value representation Digital outputs Channels Rated voltage through supply terminal Rated current consumption from the supply terminal (at load current = 0 mA) Rated current consumption from module bus Power loss Resistive load	I _L	Number mA mA V	16-bit signed integer 12-bit full range left-justified 2 24 V DC 50 ≤ 40 Normally 1 < 450
Measured value representation Digital outputs Channels Rated voltage through supply terminal Rated current consumption from the supply terminal (at load current = 0 mA) Rated current consumption from module bus Power loss Resistive load Inductive load	I _L	Number mA mA W	16-bit signed integer 12-bit full range left-justified 2 24 V DC 50 ≤ 40 Normally 1
Measured value representation Digital outputs Channels Rated voltage through supply terminal Rated current consumption from the supply terminal (at load current = 0 mA) Rated current consumption from module bus Power loss Resistive load	I _L	Number mA mA V	16-bit signed integer 12-bit full range left-justified 2 24 V DC 50 ≤ 40 Normally 1 < 450 < 0.001
Measured value representation Digital outputs Channels Rated voltage through supply terminal Rated current consumption from the supply terminal (at load current = 0 mA) Rated current consumption from module bus Power loss Resistive load Inductive load Digital inputs Channels	I _L I _{MB} P	Number mA mA V Ω h	16-bit signed integer 12-bit full range left-justified 2 24 V DC 50 ≤ 40 Normally 1 < 450 < 0.001
Measured value representation Digital outputs Channels Rated voltage through supply terminal Rated current consumption from the supply terminal (at load current = 0 mA) Rated current consumption from module bus Power loss Resistive load Inductive load Digital inputs Channels Rated voltage through supply terminal	I _L I _{MB} P	Number mA mA V Ω h	16-bit signed integer 12-bit full range left-justified 2 24 V DC 50 ≤ 40 Normally 1 < 450 < 0.001 2 24 V DC
Measured value representation Digital outputs Channels Rated voltage through supply terminal Rated current consumption from the supply terminal (at load current = 0 mA) Rated current consumption from module bus Power loss Resistive load Inductive load Digital inputs Channels Rated voltage through supply terminal Rated current consumption from supply terminal	I _L I _{MB} P U _L	Number mA mA V Ω h Number	16-bit signed integer 12-bit full range left-justified 2 24 V DC 50 ≦ 40 Normally 1 < 450 < 0.001 2 24 V DC 50
Measured value representation Digital outputs Channels Rated voltage through supply terminal Rated current consumption from the supply terminal (at load current = 0 mA) Rated current consumption from module bus Power loss Resistive load Inductive load Digital inputs Channels Rated voltage through supply terminal Rated current consumption from supply terminal Rated current consumption from module bus	I _L I _{MB} P	Mumber mA mA γ Ω h Number mA mA mA	16-bit signed integer 12-bit full range left-justified 2 24 V DC 50 ≤ 40 Normally 1 < 450 < 0.001 2 24 V DC 50 ≤ 40 40 10 10 10 11 11 12 13 14 15 16 16 16 17 18 18 18 18 18 18 18 18 18
Measured value representation Digital outputs Channels Rated voltage through supply terminal Rated current consumption from the supply terminal (at load current = 0 mA) Rated current consumption from module bus Power loss Resistive load Inductive load Digital inputs Channels Rated voltage through supply terminal Rated current consumption from supply terminal Rated current consumption from module bus Heat dissipation	I _L I _{MB} P U _L	Number mA mA V Ω h Number	16-bit signed integer 12-bit full range left-justified 2 24 V DC 50 ≦ 40 Normally 1 < 450 < 0.001 2 24 V DC 50
Measured value representation Digital outputs Channels Rated voltage through supply terminal Rated current consumption from the supply terminal (at load current = 0 mA) Rated current consumption from module bus Power loss Resistive load Inductive load Digital inputs Channels Rated voltage through supply terminal Rated current consumption from supply terminal Rated current consumption from module bus Heat dissipation Relay modules	I _L I _{MB} P U _L I _L	Mumber mA mA γ Ω h Number mA mA mA	16-bit signed integer 12-bit full range left-justified 2 24 V DC 50 ≤ 40 Normally 1 < 450 < 0.001 2 24 V DC 50 ≤ 40 normally 1
Measured value representation Digital outputs Channels Rated voltage through supply terminal Rated current consumption from the supply terminal (at load current = 0 mA) Rated current consumption from module bus Power loss Resistive load Inductive load Digital inputs Channels Rated voltage through supply terminal Rated current consumption from supply terminal Rated current consumption from module bus Heat dissipation Relay modules Rated voltage through supply terminal	I _L I _{MB} P U _L I _L I _{MB}	Number mA mA V Ω h Number mA w W	16-bit signed integer 12-bit full range left-justified 2 24 V DC 50 ≤ 40 Normally 1 < 450 < 0.001 2 24 V DC 50 ≤ 40 normally 1
Measured value representation Digital outputs Channels Rated voltage through supply terminal Rated current consumption from the supply terminal (at load current = 0 mA) Rated current consumption from module bus Power loss Resistive load Inductive load Digital inputs Channels Rated voltage through supply terminal Rated current consumption from supply terminal Rated current consumption from module bus Heat dissipation Relay modules Rated voltage through supply terminal Rated current consumption from supply terminal	I _L I _{MB} P U _L I _L	Mumber mA mA γ Ω h Number mA mA mA	16-bit signed integer 12-bit full range left-justified 2 24 V DC 50 ≤ 40 Normally 1 < 450 < 0.001 2 24 V DC 50 ≤ 40 normally 1 24 V DC 50 ≤ 40
Measured value representation Digital outputs Channels Rated voltage through supply terminal Rated current consumption from the supply terminal (at load current = 0 mA) Rated current consumption from module bus Power loss Resistive load Inductive load Digital inputs Channels Rated voltage through supply terminal Rated current consumption from supply terminal Rated current consumption from module bus Heat dissipation Relay modules Rated voltage through supply terminal	I _L I _{MB} P U _L I _L I _{MB}	Number mA mA V Ω h Number mA w W	16-bit signed integer 12-bit full range left-justified 2 24 V DC 50 ≤ 40 Normally 1 < 450 < 0.001 2 24 V DC 50 ≤ 40 normally 1
Measured value representation Digital outputs Channels Rated voltage through supply terminal Rated current consumption from the supply terminal (at load current = 0 mA) Rated current consumption from module bus Power loss Resistive load Inductive load Digital inputs Channels Rated voltage through supply terminal Rated current consumption from supply terminal Rated current consumption from module bus Heat dissipation Relay modules Rated voltage through supply terminal Rated current consumption from supply terminal Rated current consumption from supply terminal Rated current consumption from module bus Power loss	IL IMB P UL IL IL	Number mA w Ω h Number mA w mA mA mA w mA	16-bit signed integer 12-bit full range left-justified 2 24 V DC 50 ≤ 40 Normally 1 < 450 < 0.001 2 24 V DC 50 ≤ 40 normally 1 24 V DC 50 ≤ 40
Measured value representation Digital outputs Channels Rated voltage through supply terminal Rated current consumption from the supply terminal (at load current = 0 mA) Rated current consumption from module bus Power loss Resistive load Inductive load Digital inputs Channels Rated voltage through supply terminal Rated current consumption from supply terminal Rated current consumption from module bus Heat dissipation Relay modules Rated voltage through supply terminal Rated current consumption from supply terminal Rated current consumption from module bus Power loss Power supply module	IL IMB P UL IMB UL IL IMB	Mumber mA w Ω h Number mA w mA mA mA w	16-bit signed integer 12-bit full range left-justified 2 24 V DC 50 ≤ 40 Normally 1 < 450 < 0.001 2 24 V DC 50 ≤ 40 normally 1 24 V DC 50 ≤ 40 Normally 1
Measured value representation Digital outputs Channels Rated voltage through supply terminal Rated current consumption from the supply terminal (at load current = 0 mA) Rated current consumption from module bus Power loss Resistive load Inductive load Digital inputs Channels Rated voltage through supply terminal Rated current consumption from supply terminal Rated current consumption from module bus Heat dissipation Relay modules Rated voltage through supply terminal Rated current consumption from supply terminal Rated current consumption from supply terminal Rated current consumption from module bus Power loss	IL IMB P UL IMB UL IL IMB	Mumber mA w Ω h Number mA w mA mA mA w	16-bit signed integer 12-bit full range left-justified 2 24 V DC 50 ≤ 40 Normally 1 < 450 < 0.001 2 24 V DC 50 ≤ 40 normally 1 24 V DC 50 ≤ 40
Measured value representation Digital outputs Channels Rated voltage through supply terminal Rated current consumption from the supply terminal (at load current = 0 mA) Rated current consumption from module bus Power loss Resistive load Inductive load Digital inputs Channels Rated voltage through supply terminal Rated current consumption from supply terminal Rated current consumption from module bus Heat dissipation Relay modules Rated voltage through supply terminal Rated current consumption from supply terminal Rated current consumption from module bus Power loss Power supply module	IL IMB P UL IMB UL IL IMB	Mumber mA w Ω h Number mA w mA mA mA w	16-bit signed integer 12-bit full range left-justified 2 24 V DC 50 ≤ 40 Normally 1 < 450 < 0.001 2 24 V DC 50 ≤ 40 normally 1 24 V DC 50 ≤ 40 Normally 1
Measured value representation Digital outputs Channels Rated voltage through supply terminal Rated current consumption from the supply terminal (at load current = 0 mA) Rated current consumption from module bus Power loss Resistive load Inductive load Digital inputs Channels Rated voltage through supply terminal Rated current consumption from supply terminal Rated current consumption from module bus Heat dissipation Relay modules Rated voltage through supply terminal Rated current consumption from supply terminal Rated current consumption from supply terminal Rated current consumption from module bus Power loss Power supply module Rated voltage through supply terminal	IL IMB P UL IMB UL IMB P	Mumber mA w Ω h Number mA w mA w w w w w w w w m M w w	16-bit signed integer 12-bit full range left-justified 2 24 V DC 50 ≤ 40 Normally 1 < 450 < 0.001 2 24 V DC 50 ≤ 40 normally 1 24 V DC 50 ≤ 40 Normally 1 24 V DC 50 ≤ 40 Normally 1
Digital outputs Channels Rated voltage through supply terminal Rated current consumption from the supply terminal (at load current = 0 mA) Rated current consumption from module bus Power loss Resistive load Inductive load Digital inputs Channels Rated voltage through supply terminal Rated current consumption from supply terminal Rated current consumption from module bus Heat dissipation Relay modules Rated voltage through supply terminal Rated current consumption from supply terminal Rated current consumption from module bus Power loss Power supply module Rated voltage through supply terminal Rated current consumption from module bus Power loss Power supply module Rated voltage through supply terminal	IL IMB P UL IL IMB UL IL IMB P	Mumber mA W Ω h Number mA W mA W mA W mA mA mA mA mA m	16-bit signed integer 12-bit full range left-justified 2 24 V DC 50 ≤ 40 Normally 1 < 450 < 0.001 2 24 V DC 50 ≤ 40 normally 1 24 V DC 50 ≤ 40 Normally 1 24 V DC 50 ≤ 40 Normally 1
Digital outputs Channels Rated voltage through supply terminal Rated current consumption from the supply terminal (at load current = 0 mA) Rated current consumption from module bus Power loss Resistive load Inductive load Digital inputs Channels Rated voltage through supply terminal Rated current consumption from supply terminal Rated current consumption from module bus Heat dissipation Relay modules Rated current consumption from supply terminal Rated current consumption from module bus Power loss Power supply module Rated voltage through supply terminal Rated current consumption from module bus Power loss Power supply module Rated current consumption from supply terminal Rated current consumption from supply terminal	IL IMB P UL IMB UL IMB P UL IL IMB	Mumber mA w Ω h Number mA w mA w w mA w mA mA mA mA w	16-bit signed integer 12-bit full range left-justified 2 24 V DC 50 ≤ 40 Normally 1 < 450 < 0.001 2 24 V DC 50 ≤ 40 normally 1 24 V DC 50 ≤ 40 Normally 1 24 V DC 50 ≤ 40 Normally 1
Digital outputs Channels Rated voltage through supply terminal Rated current consumption from the supply terminal (at load current = 0 mA) Rated current consumption from module bus Power loss Resistive load Inductive load Digital inputs Channels Rated voltage through supply terminal Rated current consumption from supply terminal Rated current consumption from module bus Heat dissipation Relay modules Rated voltage through supply terminal Rated current consumption from module bus Power loss Power supply module Rated voltage through supply terminal Rated current consumption from supply terminal Rated current consumption from supply terminal Rated current consumption from supply terminal	IL IMB P UL IMB UL IMB P UL IL IMB	Mumber mA w Ω h Number mA w mA w w mA w mA mA mA mA w	16-bit signed integer 12-bit full range left-justified 2 24 V DC 50 ≤ 40 Normally 1 < 450 < 0.001 2 24 V DC 50 ≤ 40 normally 1 24 V DC 50 ≤ 40 Normally 1 24 V DC 50 ≤ 40 Normally 1

Rated voltage through supply terminal	U_{L}		24 V DC
Rated current consumption from supply terminal	IL	mA	50
Rated current consumption from module bus	I _{MB}	mA	≦ 40
Heat dissipation		W	normally 1
Measuring modes			
Temperature coefficient			150 ppm/°C of full scale
Number of parameter bits			3 (per channel)
Interfaces			
Rated voltage through supply terminal	U_{L}		24 V DC
Rated current consumption from supply terminal	IL	mA	50
Rated current consumption from module bus	I _{MB}	mA	≦ 40
Power loss	P	W	Normally 1
Number of parameter bytes			3 (per channel)

Design verification as per IEC/EN 61439

3			
Technical data for design verification			
Rated operational current for specified heat dissipation	In	Α	0
Heat dissipation per pole, current-dependent	P _{vid}	W	0
Equipment heat dissipation, current-dependent	P _{vid}	W	0
Static heat dissipation, non-current-dependent	P _{vs}	W	1
Heat dissipation capacity	P _{diss}	W	0
Operating ambient temperature min.		°C	0
Operating ambient temperature max.		°C	55
Degree of Protection			IP20
IEC/EN 61439 design verification			
10.2 Strength of materials and parts			
10.2.2 Corrosion resistance			Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures			Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat			Meets the product standard's requirements.
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects			Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation			Meets the product standard's requirements.
10.2.5 Lifting			Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact			Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions			Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES			Meets the product standard's requirements.
10.4 Clearances and creepage distances			Meets the product standard's requirements.
10.5 Protection against electric shock			Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components			Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections			Is the panel builder's responsibility.
10.8 Connections for external conductors			Is the panel builder's responsibility.
10.9 Insulation properties			
10.9.2 Power-frequency electric strength			Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage			Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material			Is the panel builder's responsibility.
10.10 Temperature rise			The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating			Is the panel builder's responsibility.
10.12 Electromagnetic compatibility			Is the panel builder's responsibility.
10.13 Mechanical function			The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 7.0

PLC's (EG000024) / Fieldbus, decentr. periphery - analogue I/O module (EC001596)

Electric engineering, automation, process control engineering / Control / Field bus, decentralized peripheral / Field bus, decentralized peripheral - analogue I/O module (ecl@ss10.0.1-27-24-26-01 [BAA061014])

Supply voltage AC 50 Hz	V	0 - 0
Supply voltage AC 60 Hz	V	0 - 0
Supply voltage DC	V	20.4 - 28.8
Voltage type of supply voltage		DC
Input, current		No
Input, voltage		No
Input, resistor		No
Input, resistance thermometer		No
Input, thermocouple		No
Input signal, configurable		No
Resolution of the analogue inputs	Bit	0
Output, current		Yes
Output, voltage		No
Output signal configurable		Yes
Resolution of the analogue outputs	Bit	16
Number of analogue inputs		0
Number of analogue outputs		2
Analogue inputs configurable		Yes
Analogue outputs configurable		Yes
Number of HW-interfaces industrial Ethernet		0
Number of interfaces PROFINET		0
Number of HW-interfaces RS-232		0
Number of HW-interfaces RS-422		0
Number of HW-interfaces RS-485		0
Number of HW-interfaces serial TTY		0
Number of HW-interfaces parallel		0
Number of HW-interfaces Wireless		0
Number of HW-interfaces USB		0
Number of HW-interfaces other		1
Supporting protocol for TCP/IP		No
Supporting protocol for PROFIBUS		No
Supporting protocol for CAN		No
Supporting protocol for INTERBUS		No
Supporting protocol for ASI		No
Supporting protocol for KNX		No
Supporting protocol for MODBUS		No
Supporting protocol for Data-Highway		No
Supporting protocol for DeviceNet		No
Supporting protocol for SUCONET		No
Supporting protocol for LON		No
Supporting protocol for PROFINET IO		No
Supporting protocol for PROFINET CBA		No
Supporting protocol for SERCOS		No
Supporting protocol for Foundation Fieldbus		No
Supporting protocol for EtherNet/IP		No
Supporting protocol for AS-Interface Safety at Work		No
Supporting protocol for DeviceNet Safety		No
Supporting protocol for INTERBUS-Safety		No
Supporting protocol for PROFIsafe		No
Supporting protocol for SafetyBUS p		No
Supporting protocol for other bus systems		No
Radio standard Bluetooth		No
Radio standard WLAN 802.11		No
Radio standard GPRS		No
Radio standard GSM		No

Radio standard UMTS		No
10 link master		No
System accessory		Yes
Degree of protection (IP)		IP20
Degree of protection (NEMA)		
Type of electric connection		Screw-/spring clamp connection
Fieldbus connection over separate bus coupler possible		Yes
Rail mounting possible		Yes
Wall mounting/direct mounting		No
Front build in possible		No
Rack-assembly possible		No
Suitable for safety functions		No
Category according to EN 954-1		
SIL according to IEC 61508		None
Performance level acc. EN ISO 13849-1		None
Appendant operation agent (Ex ia)		No
Appendant operation agent (Ex ib)		No
Explosion safety category for gas		None
Explosion safety category for dust		None
Width	mm	12.6
Height	mm	74
Depth	mm	55.4

Approvals

Approvato	
Product Standards	UL 508; CSA-C22.2 No. 142; IEC/EN 6113-2; CE marking
UL File No.	E205091
UL Category Control No.	NRAQ, NRAQ7
CSA File No.	UL report applies to both US and Canada
CSA Class No.	2252-01, 2252-81
North America Certification	UL recognized, certified by UL for use in Canada
Specially designed for North America	No
Current Limiting Circuit-Breaker	No
Degree of Protection	IEC: IP20, UL/CSA Type: -

Dimensions 12.6 17.7

Additional product information (links)

Dimensions

Manual XI/ON analog I/O modules MN05002011Z			
Handbuch XI/ON analoge E/A-Module MN05002011Z - Deutsch	https://es-assets.eaton.com/DOCUMENTATION/AWB_MANUALS/MN05002011Z_DE.pdf		
Manual XI/ON analog I/O modules MN05002011Z - English	https://es-assets.eaton.com/DOCUMENTATION/AWB_MANUALS/MN05002011Z_EN.pdf		
Technical Data	http://ecat.moeller.net/flip-cat/?edition=HPLEN&startpage=14.111		