



EMS three-phase current connector, 3 devices

Part no. EMS-XBR-3
Catalog No. 171269
Alternate Catalog No. EMS-XBR-3
EL-Number (Norway) 4110019

Delivery program

Product range			Electronic motor starter
Basic function			Accessories
Pole			3
Devices		Number	3
For use with			EMS-D... EMS-D...-SWD-... EMS-R... EMS-R...-SWD-...
Conductor cross-section		mm ²	1.5

Technical data

General

Ambient temperature			-25 - +60
---------------------	--	--	-----------

Design verification as per IEC/EN 61439

Technical data for design verification			
Rated operational current for specified heat dissipation	I _n	A	12
Heat dissipation per pole, current-dependent	P _{vid}	W	3.9
Equipment heat dissipation, current-dependent	P _{vid}	W	11.7
Static heat dissipation, non-current-dependent	P _{vs}	W	0
Heat dissipation capacity	P _{diss}	W	0
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	60
IEC/EN 61439 design verification			
10.2 Strength of materials and parts			
10.2.2 Corrosion resistance			Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures			Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat			Meets the product standard's requirements.
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects			Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation			Meets the product standard's requirements.
10.2.5 Lifting			Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact			Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions			Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES			Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances			Meets the product standard's requirements.
10.5 Protection against electric shock			Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components			Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections			Is the panel builder's responsibility.
10.8 Connections for external conductors			Is the panel builder's responsibility.
10.9 Insulation properties			
10.9.2 Power-frequency electric strength			Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage			Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material			Is the panel builder's responsibility.
10.10 Temperature rise			The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.

10.11 Short-circuit rating		Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility		Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function		The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 7.0

Low-voltage industrial components (EG000017) / Accessories for electronic motor control and protection device (EC002615)		
Electric engineering, automation, process control engineering / Low-voltage switch technology / Electronic motor control and motor protection device / Electronic motor control and motor protection unit (accessories) (ecl@ss10.0.1-27-37-08-92 [AC0035011])		
Type of accessory		Connecting cable

Additional product information (links)

IL03407198Z Electronic motor starter EMS		
IL03407198Z Electronic motor starter EMS		ftp://ftp.moeller.net/DOCUMENTATION/AWA_INSTRUCTIONS/IL03407198Z2018_04.pdf
IL120002ZU Electronic motor starter with SWD connection		
IL120002ZU Electronic motor starter with SWD connection		ftp://ftp.moeller.net/DOCUMENTATION/AWA_INSTRUCTIONS/IL120002ZU2018_04.pdf