



**Reset remote, 110-125VAC/DC**

**Part no.** IZMX-RR110AD-40-1  
**Catalog No.** 184126  
**Alternate Catalog No.** 68D2806G61  
**EL-Nummer (Norway)** 0004398489

**Delivery program**

Product range			Accessories
Accessories			Trip indication / Reset options
Accessories			Remote reset
			The circuit-breaker is equipped with a mechanical trip indicator (red pin). After the remote reset coil is electrically actuated, the reclosing lockout can be reset. Cannot be combined with remote reset.
Rated control voltage	U <sub>s</sub>	V	110 - 127 V AC 50/60 Hz 110 - 125 V DC
For use with			IZMX40...W IZMX40...F
<b>Instructions</b>			The retrofit kit includes the required SEC control cable terminals.

**Design verification as per IEC/EN 61439**

Technical data for design verification			
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	70

**Technical data ETIM 7.0**

Low-voltage industrial components (EG000017) / Shunt release (for power circuit breaker) (EC001023)			
Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Full load current trip (ecl@ss10.0.1-27-37-04-18 [AKF016013])			
Rated control supply voltage U <sub>s</sub> at AC 50HZ		V	110 - 127
Rated control supply voltage U <sub>s</sub> at AC 60HZ		V	110 - 127
Rated control supply voltage U <sub>s</sub> at DC		V	110 - 125
Voltage type for actuating			AC/DC
Initial value of the undelayed short-circuit release - setting range		A	0
End value adjustment range undelayed short-circuit release		A	0
Type of electric connection			Flat plug-in connection
Number of contacts as normally open contact			0
Number of contacts as normally closed contact			0
Number of contacts as change-over contact			0
Suitable for power circuit breaker			Yes
Suitable for off-load switch			Yes
Suitable for motor safety switch			No
Suitable for overload relay			No