Circuit-breaker, 3p, 25A

Part no. NZMC1-A25 283294



General specifications	
Product name	Eaton Moeller series NZM molded case circuit breaker thermo-magnetic
Part no.	NZMC1-A25
EAN	4015082832940
Product Length/Depth	84.5 millimetre
Product height	145 millimetre
Product width	90 millimetre
Product weight	1.046 kilogram
Compliances	RoHS conform
Certifications	IEC/EN 60947 IEC
Product Tradename	NZM
Product Type	Molded case circuit breaker
Product Sub Type	Thermo-magnetic
Delivery program	
Application	Use in unearthed supply systems at 690 V
Туре	Circuit breaker
Circuit breaker frame type	NZM1
Number of poles	Three-pole
Amperage Rating	25 A
Release system	Thermomagnetic release
Features	Protection unit
Special features	Maximum back-up fuse, if the expected short-circuit currents at the installation location exceed the switching capacity of the circuit breaker (Rated short-circuit breaking capacity Icn) Rated current = rated uninterrupted current: 25 A Terminal capacity hint: Up to 95 mm² can be connected depending on the cable manufacturer.
Technical Data - Electrical	
Voltage rating	690 V - 690 V
Rated insulation voltage (Ui)	690 V AC
Rated impulse withstand voltage (Uimp) at auxiliary contacts	6000 V
Rated impulse withstand voltage (Uimp) at main contacts	6000 V
Instantaneous current setting (li) - min	350 A
Instantaneous current setting (li) - max	350 A
Overload current setting (Ir) - min	20 A
Overload current setting (Ir) - max	25 A
Short delay current setting (Isd) - min	0 A
Short delay current setting (Isd) - max	0 A
Short-circuit release non-delayed setting - min	350 A
Short-circuit release non-delayed setting - max	350 A
Rated short-circuit breaking capacity Ics (IEC/EN 60947) at 230 V, 50/60 Hz	55 kA
Rated short-circuit breaking capacity Ics (IEC/EN 60947) at 400/415 V, 50/60 Hz	36 kA
Rated short-circuit breaking capacity Ics (IEC/EN 60947) at 440 V, 50/60 Hz	22.5 kA
Rated short-circuit breaking capacity Ics (IEC/EN 60947) at 525 V, 50/60 Hz	6 kA
Rated short-circuit breaking capacity Ics (IEC/EN 60947) at 690 V, 50/60 Hz	4 kA
Rated short-circuit making capacity Icm at 240 V, 50/60 Hz	121 kA
Rated short-circuit making capacity Icm at 400/415 V, 50/60 Hz	76 kA
Rated short-circuit making capacity Icm at 440 V, 50/60 Hz	63 kA
Rated short-circuit making capacity Icm at 525 V, 50/60 Hz	24 kA
Rated short-circuit making capacity Icm at 690 V, 50/60 Hz	14 kA

Short-circuit total breaktime	< 10 ms
Electrical connection type of main circuit	Frame clamp
Isolation	300 V AC (between the auxiliary contacts) 500 V AC (between auxiliary contacts and main contacts)
Number of operations per hour - max	120
Handle type	Rocker lever
Utilization category	A (IEC/EN 60947-2)
Overvoltage category	III
Pollution degree	3
Lifespan, electrical	10000 operations at 415 V AC-1 5000 operations at 690 V AC-1 10000 operations at 400 V AC-1
Direction of incoming supply	As required
Technical Data - Mechanical	
Mounting Method	DIN rail (top hat rail) mounting optional Built-in device fixed built-in technique Fixed
Degree of protection	IP20 (basic degree of protection, in the operating controls area) IP20
Degree of protection (IP), front side	IP40 (with insulating surround) IP66 (with door coupling rotary handle)
Degree of protection (terminations)	IP10 (tunnel terminal) IP00 (terminations, phase isolator and strip terminal)
Protection against direct contact	Finger and back-of-hand proof to DIN EN 50274/VDE 0106 part 110
Shock resistance	20 g (half-sinusoidal shock 20 ms)
Number of auxiliary contacts (change-over contacts)	0
Number of auxiliary contacts (normally closed contacts)	0
Number of auxiliary contacts (normally open contacts)	0
Position of connection for main current circuit	Front side
Climatic proofing	Damp heat, constant, to IEC 60068-2-78 Damp heat, cyclic, to IEC 60068-2-30
Special features	Maximum back-up fuse, if the expected short-circuit currents at the installation location exceed the switching capacity of the circuit breaker (Rated short-circuit breaking capacity Icn) Rated current = rated uninterrupted current: 25 A Terminal capacity hint: Up to 95 mm² can be connected depending on the cable manufacturer.
Lifespan, mechanical	20000 operations
Technical Data - Mechanical - Terminals	
Standard terminals	Box terminal
Optional terminals	Connection on rear. Screw terminal. Tunnel terminal
Terminal capacity (control cable)	0.75 mm ² - 2.5 mm ² (1x) 0.75 mm ² - 1.5 mm ² (2x)
Terminal capacity (aluminum solid conductor/cable)	10 mm ² - 16 mm ² (2x) direct at switch rear-side connection 10 mm ² - 16 mm ² (1x) direct at switch rear-side connection 16 mm ² (1x) at tunnel terminal
Terminal capacity (aluminum stranded conductor/cable)	$25~\text{mm}^2$ - $35~\text{mm}^2$ (2x) direct at switch rear-side connection $25~\text{mm}^2$ - $35~\text{mm}^2$ (1x) direct at switch rear-side connection $25~\text{mm}^2$ - $95~\text{mm}^2$ (1x) at tunnel terminal
Terminal capacity (copper busbar)	Max. 16 mm x 5 mm direct at switch rear-side connection Min. 12 mm x 5 mm direct at switch rear-side connection M6 at rear-side screw connection
Terminal capacity (copper solid conductor/cable)	10 mm ² - 16 mm ² (1x) at box terminal 16 mm ² (1x) at tunnel terminal 6 mm ² - 16 mm ² (2x) direct at switch rear-side connection 10 mm ² - 16 mm ² (1x) direct at switch rear-side connection 6 mm ² - 16 mm ² (2x) at box terminal
Terminal capacity (copper stranded conductor/cable)	25 mm² (2x) direct at switch rear-side connection 6 mm² - 25 mm² (2x) at box terminal 10 mm² - 70 mm² (1x) direct at switch rear-side connection 25 mm² - 95 mm² (1x) at 1-hole tunnel terminal 10 mm² - 70 mm² (1x) at box terminal
Terminal capacity (copper strip)	Min. 2 segments of 9 mm x 0.8 mm at box terminal Max. 9 segments of 9 mm x 0.8 mm at box terminal
Design verification as per IEC/EN 61439 - technical data	
Rated operational current for specified heat dissipation (In)	25 A
Equipment heat dissipation, current-dependent	8.78 W

Ambient operating temperature - min	-25 °C
Ambient operating temperature - max	70 °C
Ambient storage temperature - min	-40 °C
Ambient storage temperature - max	70 °C
Design verification as per IEC/EN 61439	
10.2.2 Corrosion resistance	Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures	Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat	Meets the product standard's requirements.
10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects	Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation	Meets the product standard's requirements.
10.2.5 Lifting	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions	Meets the product standard's requirements.
10.3 Degree of protection of assemblies	Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances	Meets the product standard's requirements.
10.5 Protection against electric shock	Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.
Additional information	
Functions	System and cable protection

Technical data ETIM 9.0

Low-voltage industrial components (EG000017) / Power circuit-breaker for trafo/generator/installation protection (EC000228)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Circuit breaker for power transformer, generator and system protection (ecl@ss13-27-37-04-09 [AJZ716018])

Rated voltage Rated short-circuit breaking capacity lcu at 400 V, 50 Hz Rated short-circuit breaking capacity lcu at 400 V, 50 Hz Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit rele			
Rated short-circuit breaking capacity Icu at 400 V, 50 Hz Overload release current setting Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit release Www. 8.8 Built-in device fixed built-in technique No Frame clamp No Ves Ves Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact With switched-off indicator With switched-off indicator With integrated under voltage release Number of poles Position of connection for main current circuit Na Position of connection for main current circuit Pront side	Rated permanent current lu	Α	25
Overload release current setting Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit release Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-intechnique Built-in device fixed built-in technique Adjustment range undelay	Rated voltage	V	690 - 690
Adjustment range short-term delayed short-circuit release Adjustment range undelayed s	Rated short-circuit breaking capacity Icu at 400 V, 50 Hz	kA	36
Adjustment range undelayed short-circuit release Power loss W 8.8 Built-in device fixed built-in technique No Type of electrical connection of main circuit Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact With switched-off indicator With integrated under voltage release Number of poles Position of connection for main current circuit A 350 - 350 Built-in device fixed built-in technique No Frame clamp No Yes 0 0 0 0 0 No No No No No No	Overload release current setting	А	20 - 25
Power loss Device construction Integrated earth fault protection Type of electrical connection of main circuit Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact With switched-off indicator With integrated under voltage release Number of poles Position of connection for main current circuit With available of the connection of main current circuit With switched-off main current circuit With switched-off main current circuit Front side	Adjustment range short-term delayed short-circuit release	Α	0 - 0
Device construction Integrated earth fault protection No Type of electrical connection of main circuit Frame clamp Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Output of auxiliary contacts as normally open contact Output of auxiliary contacts as change-over contact Output of auxiliary contacts as normally open contact Output of auxiliary contacts as normally	Adjustment range undelayed short-circuit release	Α	350 - 350
Integrated earth fault protection Type of electrical connection of main circuit Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional No DIN rail (top hat rail) mounting optional No No No Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact No With switched-off indicator No With integrated under voltage release No No No No No No No No No N	Power loss	W	8.8
Type of electrical connection of main circuit Suitable for DIN rail (top hat rail) mounting No DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact No With switched-off indicator With integrated under voltage release No Number of poles Position of connection for main current circuit Frame clamp No Yes O No No No No Frame clamp	Device construction		Built-in device fixed built-in technique
Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Yes Number of auxiliary contacts as normally closed contact 0 Number of auxiliary contacts as normally open contact 0 Number of auxiliary contacts as change-over contact 0 Number of auxiliary contacts as change-over contact 0 With switched-off indicator No With integrated under voltage release No Number of poles 3 Position of connection for main current circuit Front side	Integrated earth fault protection		No
DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact 0 Number of auxiliary contacts as normally open contact 0 Number of auxiliary contacts as change-over contact 0 With switched-off indicator No With integrated under voltage release No Number of poles Position of connection for main current circuit Yes No No Front side	Type of electrical connection of main circuit		Frame clamp
Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact No With switched-off indicator No With integrated under voltage release No Number of poles Position of connection for main current circuit Tront side	Suitable for DIN rail (top hat rail) mounting		No
Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact O With switched-off indicator No With integrated under voltage release No Number of poles Position of connection for main current circuit O Front side	DIN rail (top hat rail) mounting optional		Yes
Number of auxiliary contacts as change-over contact With switched-off indicator No With integrated under voltage release No Number of poles Position of connection for main current circuit No Front side	Number of auxiliary contacts as normally closed contact		0
With switched-off indicator With integrated under voltage release No Number of poles Position of connection for main current circuit No Front side	Number of auxiliary contacts as normally open contact		0
With integrated under voltage release No Number of poles 3 Position of connection for main current circuit Front side	Number of auxiliary contacts as change-over contact		0
Number of poles 3 Position of connection for main current circuit Front side	With switched-off indicator		No
Position of connection for main current circuit Front side	With integrated under voltage release		No
	Number of poles		3
Type of control element Rocker lever	Position of connection for main current circuit		Front side
	Type of control element		Rocker lever

Complete device with protection unit	Yes
Motor drive integrated	No
Motor drive optional	No
Degree of protection (IP)	IP20