DATASHEET - DM1-327D8EB-S20S-EM



Variable frequency drive, 230 V AC, 3-phase, 7.8 A, 1.5 kW, IP20/NEMA0, Radio interference suppression filter, 7-digital display assembly, Setpoint potentiometer, Brake chopper, STO (Safe Torque Off, SIL2, PLd Cat 3)

Powering Business Worldwide



Part no. DM1-327D8EB-S20S-EM

Catalog No. 3-5001-008A

EL-Nummer (Norway)

4132218

Delivery program			
Product range			Variable frequency drives
Part group reference (e.g. DIL)			DM1
			IE2 ✓
Rated operational voltage	U _e		230 V AC, 3-phase 240 V AC, 3-phase
Output voltage with V_{e}	U ₂		230 V AC, 3-phase 240 V AC, 3-phase
Mains voltage (50/60Hz)	U_{LN}	V	208 (-10%) - 240 (+10%)
Rated operational current			
At 150% overload	I _e	Α	7.8
At 110% overload	I _e	Α	11
Note			Rated operational current for a switching frequency of 1 - 16 kHz and an ambient temperature of +50 °C for a 150% overload and +40 °C for a 110% overload
Assigned motor rating			
Note			for normal internally and externally ventilated 4 pole, three-phase asynchronous motors with 1500 rpm ⁻¹ at 50 Hz or 1800 min ⁻¹ at 60 Hz for PM motors
Note			Overload cycle for 60 s every 600 s
Note			at 230 V, 50 Hz
150 % Overload	P	kW	1.5
110 % Overload	Р	kW	2.2
150 % Overload	I _M	Α	6.3
110 % Overload	I _M	Α	8.7
Note			at 230 V, 60 Hz
150 % Overload	Р	HP	2
110 % Overload	Р	HP	3
150 % Overload	I _M	Α	6.8
110 % Overload	I _M	Α	9.6
Degree of Protection			IP20/NEMA0
Interface/field bus (built-in)			Modbus RTU Modbus TCP BACnet MS/TP Ethernet IP BACnet TCP
Fieldbus connection (optional)			Profibus, CAN, DeviceNet, SmartwireDT
Fitted with			Radio interference suppression filter 7-digital display assembly Setpoint potentiometer Brake chopper
Parameterization			Keypad Fieldbus Power Xpert inControl
Frame size			FS1
Connection to SmartWire-DT			yes in conjunction with DXG-NET-SWD SmartWire DT module

Technical data General

General			
Standards			General requirements: IEC/EN 61800-2 EMV requirements: IEC/EN 61800-3 Safety requirements: IEC/EN 61800-5-1:2007/A1:2017; UL 61800-5-1:2012 (Rev. 2018), CSA C22.2 No. 274-17:2017
Certifications			CE, UL, cUL, c-Tick, UkrSEPRO, EAC
Production quality			RoHS, ISO 9001
Climatic proofing	ρ_{W}	%	< 95%, average relative humidity (RH), non-condensing, non-corrosive
Air quality			3C2, 3S2
Ambient temperature			
Operating ambient temperature min.		°C	-10
, , ,		°C	+ 50
Operating ambient temperature max.	9	°C	
operation (110 % overload)	U	C	-10 - +40 (max. +55 with 1 % derating per Kelvin temperature rise) °C
			Operation with 110 % overload (1 min./10 min.): -10 to +40 (max. +55 with 1% derating per Kelvin above limit) Operation with 150% overload (1 min./10 min.): -10 to +50 (max. +60 with 1% derating per Kelvin above limit) -20 with cold-weather mode
Storage	9	°C	-40 - +70
Overvoltage category			III
Pollution degree			2
Radio interference level			
Radio interference class (EMC)			C1 (with external filter, for conducted emissions only), C2, C3, depending on the motor cable length, the connected load, and ambient conditions. External radio interference suppression filters (optional) may be necessary.
Environment (EMC)			1st and 2nd environments as per EN 61800-3
maximum motor cable length	1	m	C2 ≤ 5 m C3 ≤ 25 m
Mechanical shock resistance		g	EN 61800-5-1, EN 60068-2-6: 10 - 150 Hz Amplitude: 0,75 mm (peak) bei 10 - 57 Hz
u			Maximum acceleration amplitude: 1 g at 57 – 150 Hz
Mounting position			Vertical
Altitude		m	0 - 1000 m above sea level Above 1000 m: 1% derating for every 100 m max. 3000 m (2000 m for Corner Grounded TN Systems)
Degree of Protection			IP20/NEMA0
Protection against direct contact			BGV A3 (VBG4, finger- and back-of-hand proof)
Main circuit			
Supply			
Rated operational voltage	U _e	.,	230 V AC, 3-phase 240 V AC, 3-phase
Mains voltage (50/60Hz)	U _{LN}	V	208 (-10%) - 240 (+10%)
Input current (150% overload)	I _{LN}	Α	9.4
Input current (110% overload)	I _{LN}	Α	13.2
System configuration			TN-S, TN-C, TN-C-S, TT, IT
Supply frequency	f_{LN}	Hz	50/60
Frequency range	f_{LN}	Hz	45-66 (± 0%)
Mains switch-on frequency			Maximum of one time every 60 seconds
Mains current distortion	THD	%	40
Rated conditional short-circuit current	Iq	kA	<100
Power section	ч		
Function			Variable frequency drive with internal DC link, DC link choke and IGBT inverter
Overload current (150% overload)	IL	Α	11.7
Overload current (110% overload)		A	12.1
Overioda carretir (110/0 overioda)	I _L		
many stanting compact (High Co. 1 . 1)		%	200
max. starting current (High Overload)	I _H		and the second s
Note about max. starting current			for 2 seconds every 20 seconds
Note about max. starting current $\label{eq:output_voltage} \text{Output voltage with V}_e$	U ₂		230 V AC, 3-phase 240 V AC, 3-phase
Note about max. starting current		Hz kHz	230 V AC, 3-phase

Operation Mode			U/f control Speed control with slip compensation sensorless vector control (SLV) Torque regulation PM motors
Frequency resolution (setpoint value)	Δf	Hz	0.01
Rated operational current			
At 150% overload	I _e	Α	7.8
At 110% overload	I _e	Α	11
Note			Rated operational current for a switching frequency of 1 - 16 kHz and an ambient temperature of +50 °C for a 150% overload and +40 °C for a 110% overload
Motor current limit	I	Α	0.1 - 2 x I _H (CT)
Power loss			
Heat dissipation at rated operational current $\rm I_{e}$ =150 $\%$	P_{V}	W	75
Heat dissipation at rated operational current $\rm I_{\rm e}$ =110%	P_{V}	W	99
Heat dissipation at current/speed [%]			
Current = 100%			
Speed = 0 %	P_{V}	W	71
Speed = 50 %	P_{V}	W	47
Speed = 90 %	P_{V}	W	112
Current = 50 %			
Speed = 0 %	P_V	W	92
Speed = 50 %	P_V	W	58
Speed = 90 %	P_V	W	69
Current = 50 %			
Speed = 0 %	P _V	W	40
Speed = 50 %	P _V	W	48
Fan	•		temperature controlled
Internal fan delivery rate		m ³ /h	26
Fitted with		111 /11	Radio interference suppression filter
riueu wiiii			7-digital display assembly Setpoint potentiometer Brake chopper
Safety function			STO (Safe Torque Off, SIL2, PLd Cat 3)
Frame size			FS1
Motor feeder			
Note			for normal internally and externally ventilated 4 pole, three-phase asynchronous motors with 1500 rpm ⁻¹ at 50 Hz or 1800 min ⁻¹ at 60 Hz for PM motors
Note			Overload cycle for 60 s every 600 s
Note			at 230 V, 50 Hz
150 % Overload	P	kW	1.5
110 % Overload	P	kW	2.2
Note			at 230 V, 60 Hz
150 % Overload	P	HP	2
110 % Overload	Р	HP	3
Braking function			000/ M
Standard braking torque			max. 30 % M _N
DC braking torque			adjustable to 150 %
Braking torque with external braking resistance			Max. 100% of rated operational current I _e with external braking resistor
minimum external braking resistance	R _{min}	Ω	36
DC braking	%	I/I _e	≦ 150, adjustable
Control section External control voltage	U _c	V	24 V DC (max. 100 mA options incl.)
-			10 V DC (max. 10 mA)
Reference voltage	U _s	V	
Analog inputs			1, can be parameterized, 0–10 V DC, 2–10 V DC, 0/4–20 mA 1, parameterizable, 0 - 10 V
Analog outputs			

Interface/field bus (built-in)		Modbus RTU Modbus TCP BACnet MS/TP Ethernet IP BACnet TCP
Expansion slots		1
Assigned switching and protective elements		
Power Wiring		
Safety device (fuse or miniature circuit-breaker)		
IEC (Type B, gG), 150 %		PKZM0-10
IEC (Type B, gG), 110 %		PKZM0-12
UL (Class CC or J)	А	16
Mains contactor		
150 % overload (CT/I _H , at 50 °C)		DILM7-10 (230V50HZ,240V60HZ)
110 % overload (VT/I _L , at 40 °C)		DILM7-10 (230V50HZ,240V60HZ)
Main choke		
150 % overload (CT/I _H , at 50 °C)		DX-LN3-010
110 % overload (VT/I _L , at 40 °C)		DX-LN3-016
Radio interference suppression filter (external, 150 %)		DX-EMC34-016
Radio interference suppression filter (external, 110 %)		DX-EMC34-016
Radio interference suppression filter, low leakage currents (external, 150 %)		DX-EMC34-016-L
Radio interference suppression filter, low leakage currents (external, 110 %)		DX-EMC34-016-L
Note regarding radio interference suppression filter		Optional external radio interference suppression filter for longer motor cable lengths and for use in different EMC environments
DC link connection		
Braking resistance		
10 % duty factor (DF)		DX-BR050-0K4
20 % duty factor (DF)		DX-BR050-0K8
40 % duty factor (DF)		DX-BR050-0K8
Notes concerning braking resistances:		The brake resistors are assigned based on the maximum rated power of the variable frequency drive. Additional brake resistors and designs (e.g. different duty cycles) are available upon request.
Motor feeder		
motor choke		
150 % overload (CT/I _H , at 50 °C)		DX-LM3-008
110 % overload (VT/I _L , at 40 °C)		DX-LM3-011
Sine filter		
150 % overload (CT/I _H , at 50 °C)		DX-SIN3-010
110 % overload (VT/I _L , at 40 °C)		DX-SIN3-016
All-pole sine filter		
150 % overload (CT/I _H , at 50 °C)		DX-SIN3-013-A
110 % overload (VT/I _L , at 40 °C)		DX-SIN3-013-A

2, parameterizable, 1 changeover contacts and 1 N/O, 3 A (240 VAC) / 3 A (24 VDC)

Design verification as per IEC/EN 61439

Relay outputs

Technical data for design verification			
Rated operational current for specified heat dissipation	In	Α	11
Equipment heat dissipation, current-dependent	P _{vid}	W	99
Operating ambient temperature min.		°C	-10
Operating ambient temperature max.		°C	50
IEC/EN 61439 design verification			
10.2 Strength of materials and parts			
10.2.2 Corrosion resistance			Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures			Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat			Meets the product standard's requirements.
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects			Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation			Meets the product standard's requirements.

10.2.5 Lifting	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions	Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances	Meets the product standard's requirements.
10.5 Protection against electric shock	Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9 Insulation properties	
10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 8.0

Commour data Errivi 6.0			
Low-voltage industrial components (EG000017) / Frequency converter =< 1 kV (E	C001857)		
Electric engineering, automation, process control engineering / Electrical drive /	Static frequency con-	rerter / Static frequency converte	r = < 1 kV (ecl@ss10.0.1-27-02-31-01 [AKE177014])
Mains voltage	V	200 - 240	
Mains frequency		50/60 Hz	
Number of phases input		3	
Number of phases output		3	
Max. output frequency	Hz	400	
Max. output voltage	V	240	
Nominal output current I2N	А	7.8	
Max. output at quadratic load at rated output voltage	kW	2.2	
Max. output at linear load at rated output voltage	kW	1.5	
Relative symmetric net frequency tolerance	%	10	
Relative symmetric net voltage tolerance	%	10	
Number of analogue outputs		1	
Number of analogue inputs		1	
Number of digital outputs		0	
Number of digital inputs		4	
Nith control element		Yes	
Application in industrial area permitted		Yes	
Application in domestic- and commercial area permitted		Yes	
Supporting protocol for TCP/IP		Yes	
Supporting protocol for PROFIBUS		Yes	
Supporting protocol for CAN		Yes	
Supporting protocol for INTERBUS		No	
Supporting protocol for ASI		No	
Supporting protocol for KNX		No	
Supporting protocol for Modbus		Yes	
Supporting protocol for Data-Highway		No	
Supporting protocol for DeviceNet		No	
Supporting protocol for SUCONET		No	
Supporting protocol for LON		No	
Supporting protocol for PROFINET IO		No	
Supporting protocol for PROFINET CBA		No	
Supporting protocol for SERCOS		No	

Supporting protocol for Foundation Fieldbus		No
Supporting protocol for EtherNet/IP		Yes
Supporting protocol for AS-Interface Safety at Work		No
Supporting protocol for DeviceNet Safety		No
Supporting protocol for INTERBUS-Safety		No
Supporting protocol for PROFIsafe		No
Supporting protocol for SafetyBUS p		No
Supporting protocol for BACnet		Yes
Supporting protocol for other bus systems		Yes
Number of HW-interfaces industrial Ethernet		1
Number of interfaces PROFINET		0
Number of HW-interfaces RS-232		0
Number of HW-interfaces RS-422		0
Number of HW-interfaces RS-485		1
Number of HW-interfaces serial TTY		0
Number of HW-interfaces USB		0
Number of HW-interfaces parallel		0
Number of HW-interfaces other		1
With optical interface		No
With PC connection		Yes
Integrated breaking resistance		Yes
4-quadrant operation possible		Yes
Type of converter		U converter
Degree of protection (IP)		IP20
Degree of protection (NEMA)		Other
Height	mm	152
Width	mm	72
Depth	mm	180

Approvals

•••	
Product Standards	UL508C, CSA-C22.2 No. 274-13; IEC/EN61800-3; IEC/EN61800-5; CE marking
UL File No.	E134360
UL Category Control No.	NMMS, NMMS7
CSA File No.	UL report applies to both US and Canada
North America Certification	UL listed, certified by UL for use in Canada
Suitable for	Branch circuits
Max. Voltage Rating	3~240 V AC IEC: TN-S UL/CSA: 'Y' (Solidly Grounded Wey)
Degree of Protection	IP20/NEMA0

Dimensions





