

**Radio interference suppression filter, three-phase, low leakage current,
ULN= max. 520 + 10% V, 16 A, For use with: DE1, DE11, DC1, DA1, DM1,
DG1**

**Part no. DX-EMC34-016-L
184507**

General specifications	
Product name	Eaton DX Radio interference suppression filter - low
Part no.	DX-EMC34-016-L
EAN	4015081785469
Product Length/Depth	250 millimetre
Product height	75 millimetre
Product width	45 millimetre
Product weight	1.2 kilogram
Certifications	Certified by UL for use in Canada UL 1283 UL EN 50178 IEC/EN 61800-3 UL File No.: E192040
Product Tradename	DX
Product Type	Accessory
Product Sub Type	Radio interference suppression filter - low
Catalog Notes	low leakage current
Features & Functions	
Number of phases	3
General information	
Accessory/spare part type	Filter
Degree of protection	IP20
Product Category	Accessories
Used with	DE1 DE11 DC1 DA1 DM1 DG1
Climatic environmental conditions	
Altitude	Max. 2000 m At higher altitudes observe derating
Ambient operating temperature - max	50 °C
Ambient operating temperature - min	-25 °C
Connection	
Connection type	Screw terminal, PE stud
Electrical rating	
Rated operational current (Ie) - max	16 A
Design verification	
Heat dissipation capacity Pdiss	0 W
Rated operational current for specified heat dissipation (In)	16 A
10.2.2 Corrosion resistance	Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures	Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat	Meets the product standard's requirements.
10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects	Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation	Meets the product standard's requirements.
10.2.5 Lifting	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions	Meets the product standard's requirements.
10.3 Degree of protection of assemblies	Does not apply, since the entire switchgear needs to be evaluated.

10.4 Clearances and creepage distances			Meets the product standard's requirements.
10.5 Protection against electric shock			Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components			Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections			Is the panel builder's responsibility.
10.8 Connections for external conductors			Is the panel builder's responsibility.
10.9.2 Power-frequency electric strength			Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage			Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material			Is the panel builder's responsibility.
10.10 Temperature rise			The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating			Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility			Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function			The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 9.0

Low-voltage industrial components (EG000017) / Accessories/spare parts for frequency controller (EC002025)			
Electric engineering, automation, process control engineering / Electrical drive / Static frequency converter / Static frequency converter (accessories) (ecl@ss13-27-02-31-92 [AFR303008])			
Type of accessory/spare part			Filter
Accessory			Yes
Spare part			No