## **DATASHEET - NZM1-XSR-R**

Main switch assembly kit, on the right side, red, size 1



Part no.	
----------	--

NZM1-XSR-R 266656

General specifications	
Product name	Eaton Moeller series NZM operating element
Part no.	NZM1-XSR-R
EAN	4015082666569
Product Length/Depth	190 millimetre
Product height	100 millimetre
Product width	100 millimetre
Product weight	0.881 kilogram
Compliances	UL/CSA IEC RoHS conform
Certifications	CSA (File No. 22086) CSA-C22.2 No. 5-09 CSA (Class No. 1437-01) UL (File No. E140305) CSA certified CE marking UL489 IEC60947 UL (Category Control Number DIHS) UL listed
Product Tradename	NZM
Product Type	Accessories
Product Sub Type	Operating element
Delivery program	
Туре	Accessory Main switch assembly kit for side panel mounting
Features	Red-yellow for emergency switching off Lockable Actuation of the switch on the control panel side wall Switch mounting on mounting plate
Special features	External warning plate/designation label can be clipped on. For enhanced busbar tag shroud on the incomer side, please order IP2X protection against contact with a finger. Kit for use as a main switch
Frame	NZM1
Fitted with:	Extension shaft Door coupling rotary handle NZMXV4 extension shaft Black and yellow lightning symbol External warning plate/marking plate in German/English Padlock
Suitable for	Switch disconnector Power circuit breaker Emergency stop
Used with	N(S)1(-4) NZM1(-4) PN1(-4)
Technical Data - Mechanical	
Color	Red
Cover/door type	Door interlock lockable in the 0 position using up to 3 padlocks on the handle
Degree of protection / NEMA enclosure type	IP66 4X. 12
Activation type	Actuation on the right
Special features	External warning plate/designation label can be clipped on. For enhanced busbar tag shroud on the incomer side, please order IP2X protection against contact with a finger. Kit for use as a main switch
Design verification as per IEC/EN 61439	
10.2.2 Corrosion resistance	Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures	Meets the product standard's requirements.

10.2.3.2 Verification of resistance of insulating materials to normal heat/   Meets the product standard's requirements.     10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects   Meets the product standard's requirements.     10.2.4 Resistance to ultra-violet (UV) radiation   Meets the product standard's requirements.     10.2.5 Lifting   Dees not apply, since the entire switchgear needs to be evaluated.     10.2.6 Mechanical impact   Meets the product standard's requirements.     10.2.7 Inscriptions   Meets the product standard's requirements.     10.3 Degree of protection of assemblies   Meets the product standard's requirements.     10.4.6 Learances and creepage distances   Meets the product standard's requirements.     10.6 Incorporation of switching devices and components   Dees not apply, since the entire switchgear needs to be evaluated.     10.8 Connections for external conductors   Is the panel builder's requirements.     10.8.1 Conception of switching devices and components   Is the panel builder's requirements.     10.8.2 Power-frequency electric strength   Is the panel builder's requirements.     10.8.3 Inpulse withstand voltage   Is the panel builder's responsibility.     10.8.4 Testing of enclosures made of insulating material   Is the panel builder's responsibility. The specifications for the switchgear must be abserved.     10.8.2 Fower-frequency		
10.2.4 Resistance to ultra-violet (UV) radiationMeets the product standard's requirements.10.2.5 LiftingDoes not apply, since the entire switchgear needs to be evaluated.10.2.6 Mechanical impactDoes not apply, since the entire switchgear needs to be evaluated.10.3.1 Degree of protection of assembliesDoes not apply, since the entire switchgear needs to be evaluated.10.4 Clearances and creepage distancesMeets the product standard's requirements.10.5 Protection against electric shockDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility.10.12 Electromagnetic compatibility.Is the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionIs the panel builder's responsibility. The specifications for the switchgear must be observed.	10.2.3.2 Verification of resistance of insulating materials to normal heat	Meets the product standard's requirements.
10.2.5 LiftingDoes not apply, since the entire switchgear needs to be evaluated.10.2.6 Mechanical inpactDoes not apply, since the entire switchgear needs to be evaluated.10.2.7 InscriptionsMeets the product standard's requirements.10.3 Degree of protection of assembliesDoes not apply, since the entire switchgear needs to be evaluated.10.4 Clearances and creepage distancesMeets the product standard's requirements.10.5 Protection against electric shockDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibility.Is the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionIs the panel builder's responsibility. The specifications for the switchgear must be observed.	10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects	Meets the product standard's requirements.
102.8 Mechanical impact   Does not apply, since the entire switchgear needs to be evaluated.     102.7 Inscriptions   Meets the product standard's requirements.     10.4 Clearances and creepage distances   Does not apply, since the entire switchgear needs to be evaluated.     10.5 Protection against electric shock   Does not apply, since the entire switchgear needs to be evaluated.     10.6 Incorporation of switching devices and components   Does not apply, since the entire switchgear needs to be evaluated.     10.7 Internal electric strength   Is the panel builder's responsibility.     10.9.2 Power-frequency electric strength   Is the panel builder's responsibility.     10.9.4 Testing of enclosures made of insulating material   Is the panel builder's responsibility.     10.10 Temperature rise   Is the panel builder's responsibility.     10.11 Short-circuit rating   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.12 Electromagnetic compatibility   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.13 Mechanical function   The device meets the requirements, provided the information in the instruction	10.2.4 Resistance to ultra-violet (UV) radiation	Meets the product standard's requirements.
10.2.7 Inscriptions   Meets the product standard's requirements.     10.3 Degree of protection of assemblies   Does not apply, since the entire switchgear needs to be evaluated.     10.4 Clearances and creepage distances   Meets the product standard's requirements.     10.5 Protection against electric shock   Does not apply, since the entire switchgear needs to be evaluated.     10.6 Incorporation of switching devices and components   Does not apply, since the entire switchgear needs to be evaluated.     10.7 Internal electrical circuits and connections   Is the panel builder's responsibility.     10.8 Connections for external conductors   Is the panel builder's responsibility.     10.9.2 Power-frequency electric strength   Is the panel builder's responsibility.     10.9.3 Impulse withstand voltage   Is the panel builder is responsibility.     10.10 Temperature rise   Is the panel builder is responsibility.     10.11 Short-circuit rating   Is the panel builder is responsibility. The specifications for the switchgear must be observed.     10.12 Electromagnetic compatibility   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.13 Mechanical function   The device meets the requirements, provided the information in the instruction	10.2.5 Lifting	Does not apply, since the entire switchgear needs to be evaluated.
10.3 Degree of protection of assemblies   Des not apply, since the entire switchgear needs to be evaluated.     10.4 Clearances and creepage distances   Does not apply, since the entire switchgear needs to be evaluated.     10.5 Protection against electric shock   Does not apply, since the entire switchgear needs to be evaluated.     10.6 Incorporation of switching devices and components   Does not apply, since the entire switchgear needs to be evaluated.     10.7 Internal electrical circuits and connections   Is the panel builder's responsibility.     10.8 Connections for external conductors   Is the panel builder's responsibility.     10.9.2 Power-frequency electric strength   Is the panel builder's responsibility.     10.9.3 Impulse withstand voltage   Is the panel builder's responsibility.     10.9.4 Testing of enclosures made of insulating material   Is the panel builder's responsibility.     10.10 Temperature rise   Is the panel builder's responsibility.     10.11 Short-circuit rating   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.13 Mechanical function   The device meets the requirements, provided the information in the instruction	10.2.6 Mechanical impact	Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances   Meets the product standard's requirements.     10.5 Protection against electric shock   Does not apply, since the entire switchgear needs to be evaluated.     10.6 Incorporation of switching devices and components   Does not apply, since the entire switchgear needs to be evaluated.     10.7 Internal electrical circuits and connections   Is the panel builder's responsibility.     10.8 Connections for external conductors   Is the panel builder's responsibility.     10.9.2 Power-frequency electric strength   Is the panel builder's responsibility.     10.9.3 Impulse withstand voltage   Is the panel builder's responsibility.     10.9.4 Testing of enclosures made of insulating material   Is the panel builder's responsibility.     10.10 Temperature rise   The panel builder's responsibility.     10.11 Short-circuit rating   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.12 Electromagnetic compatibility   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.13 Mechanical function   The device meets the requirements, provided the information in the instruction	10.2.7 Inscriptions	Meets the product standard's requirements.
10.5 Protection against electric shockDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.1 Temperature riseIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionIs the panel builder's responsibility. The specifications for the switchgear must be observed.	10.3 Degree of protection of assemblies	Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components   Does not apply, since the entire switchgear needs to be evaluated.     10.7 Internal electrical circuits and connections   Is the panel builder's responsibility.     10.8 Connections for external conductors   Is the panel builder's responsibility.     10.9.2 Power-frequency electric strength   Is the panel builder's responsibility.     10.9.3 Impulse withstand voltage   Is the panel builder's responsibility.     10.9.4 Testing of enclosures made of insulating material   Is the panel builder's responsibility.     10.10 Temperature rise   Is the panel builder's responsibility.     10.11 Short-circuit rating   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.12 Electromagnetic compatibility   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.13 Mechanical function   The device meets the requirements, provide the information in the instruction	10.4 Clearances and creepage distances	Meets the product standard's requirements.
10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.10 Temperature riseThe panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provided the information in the instruction	10.5 Protection against electric shock	Does not apply, since the entire switchgear needs to be evaluated.
10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.10 Temperature riseIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe panel builder's responsibility. The specifications for the switchgear must be observed.	10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.9.2 Power-frequency electric strength   16 the panel builder's responsibility.     10.9.3 Impulse withstand voltage   16 the panel builder's responsibility.     10.9.4 Testing of enclosures made of insulating material   16 the panel builder's responsibility.     10.10 Temperature rise   16 the panel builder's responsibility.     10.11 Short-circuit rating   16 the panel builder's responsibility. The specifications for the switchgear must be observed.     10.12 Electromagnetic compatibility   16 the panel builder's responsibility. The specifications for the switchgear must be observed.     10.13 Mechanical function   16 the panel builder's responsibility. The specifications for the switchgear must be observed.	10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage   Is the panel builder's responsibility.     10.9.4 Testing of enclosures made of insulating material   Is the panel builder's responsibility.     10.10 Temperature rise   The panel builder's responsibility.     10.11 Short-circuit rating   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.12 Electromagnetic compatibility   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.13 Mechanical function   The device meets the requirements, provide the information in the instruction	10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material   Is the panel builder's responsibility.     10.10 Temperature rise   Is the panel builder's responsibility.     10.11 Short-circuit rating   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.12 Electromagnetic compatibility   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.13 Mechanical function   The device meets the requirements, provided the information in the instruction	10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.10 Temperature rise   The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.     10.11 Short-circuit rating   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.12 Electromagnetic compatibility   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.13 Mechanical function   The device meets the requirements, provided the information in the instruction	10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.11 Short-circuit rating   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.12 Electromagnetic compatibility   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.13 Mechanical function   It the panel builder's responsibility. The specifications for the switchgear must be observed.	10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.12 Electromagnetic compatibility   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.13 Mechanical function   Image: Comparison of the switchgear must be observed.	10.10 Temperature rise	
10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.11 Short-circuit rating	
	10.12 Electromagnetic compatibility	
	10.13 Mechanical function	

## **Technical data ETIM 9.0**

Low-voltage industrial components (EG000017) / Handle for power circuit breaker (EC000229)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Handle for switch devices (ecl@ss13-27-37-04-14 [AKF012019])	
With restart blockage	No
With key lock	No
Padlock locking	Yes
Colour	Red
Suitable for emergency stop	Yes
With extension shaft	Yes
Suitable for power circuit breaker	Yes
Suitable for switch disconnector	Yes
Degree of protection (NEMA)	4X, 12