

**Control transformer, 3 kVA, Rated input voltage 50 – 950 ± 5 % V, Rated output voltage 12 – 1000 V**
**Part no.**                    **STZ3,0(\*/\*)**  
                                       **914776**

<b>General specifications</b>		
Product name		Eaton Moeller® series STZ Control transformer
Part no.		STZ3,0(*/*)
Product Length/Depth		172 millimetre
Product height		255 millimetre
Product width		230 millimetre
Product weight		26 kilogram
Certifications		UL report applies to both US and Canada IEC/EN 60204-1, ÖVE-EN 13 VDE 0113, VDE 0100 Part 410 VDE 0570 Part 2-4 (isolating transformer) UL Recognized UL File No.: E167225 CE CSA-C22.2 No. 66 Certified by UL for use in Canada VDE 0570 Part 2-6 (safety transformers) UL Category Control No.: XPTQ2, XPTQ8 VDE 0570 Part 2-2 UL 506 CSA-C22.2 No. 66.2-06 IEC/EN 61558-2-2 UL 5085-2 CSA-C22.2 No. 66.1-06 UL5085-1 IEC/EN 61558-2-2/2-4/2-6
Product Tradename		STZ
Product Type		Control transformer
Product Sub Type		None
Catalog Notes		Electrical characteristics: all details for no-load loss, short-circuit loss (copper losses), short-circuit voltage and efficiency values relate to a temperature of 20 °C
<b>Features &amp; Functions</b>		
Features		Separate windings Fully Vacuum-impregnated Reinforced insulation
<b>General information</b>		
Ambient operating temperature - min		-25 °C
Ambient operating temperature - max		40 °C
Connection lug		Yes for < 63 A
Connection type		Terminations, < 63 A
Degree of protection		IP00
Duty factor		100 %
Insulation class		B
Primary tapping		± 5 %
Product category		Single-phase control transformers ST
Suitable for		Branch circuits, (UL/CSA)
Type		Single-phase control, isolating and safety transformer
<b>Electrical rating</b>		
Efficiency		97 %
No-load losses		30 W
Rated frequency - min		50 Hz
Rated frequency - max		60 Hz
Rated power		3 V·A
Relative short-circuit voltage		2.1 %
Short-circuit losses		55 W
Short-time rating		11.5 kV·A

Voltage rating - max		600 V
<b>Design verification</b>		
Equipment heat dissipation, current-dependent Pvid		0 W
Heat dissipation capacity Pdis		0 W
Heat dissipation per pole, current-dependent Pvid		0 W
Rated operational current for specified heat dissipation (In)		0 A
Static heat dissipation, non-current-dependent Pvs		85 W
10.2.2 Corrosion resistance		Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures		Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat		Meets the product standard's requirements.
10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects		Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation		Meets the product standard's requirements.
10.2.5 Lifting		Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact		Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions		Meets the product standard's requirements.
10.3 Degree of protection of assemblies		Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances		Meets the product standard's requirements.
10.5 Protection against electric shock		Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components		Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections		Is the panel builder's responsibility.
10.8 Connections for external conductors		Is the panel builder's responsibility.
10.9.2 Power-frequency electric strength		Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage		Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material		Is the panel builder's responsibility.
10.10 Temperature rise		The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating		Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility		Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function		The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

## Technical data ETIM 9.0

Low-voltage industrial components (EG000017) / One-phase control transformer (EC002486)		
Electric engineering, automation, process control engineering / Transformer, converter, coil / Control transformer / One-phase control transformer (eci@ss13-27-03-13-02 [AAB620020])		
Built as safety transformer		Yes
Built as isolating transformer		Yes
Built as energy saving transformer		No
Primary voltage 1	V	50 - 950
Primary voltage 2	V	50 - 950
Primary voltage 3	V	50 - 950
Primary voltage 4	V	50 - 950
Primary voltage 5	V	50 - 950
Primary voltage 6	V	50 - 950
Primary voltage 7	V	0 - 0
Primary voltage 8	V	0 - 0
Primary voltage 9	V	0 - 0
Primary voltage 10	V	0 - 0
Secondary voltage 1	V	12 - 1000
Secondary voltage 2	V	12 - 1000
Secondary voltage 3	V	12 - 1000
Secondary voltage 4	V	12 - 1000
Secondary voltage 5	V	12 - 1000
Secondary voltage 6	V	12 - 1000
Secondary voltage 7	V	0 - 0
Secondary voltage 8	V	0 - 0

Secondary voltage 9	V	0 - 0
Secondary voltage 10	V	0 - 0
Rated apparent power	VA	3000
Power	W	
Power consumption in standby mode	W	17
Type of insulation material according to IEC 85		B
Short-circuit-proof		No
Relative short circuit voltage	%	2.1
Width	mm	230
Height	mm	255
Depth	mm	172
Degree of protection (IP)		IP00
Ring core		No
Suitable for mounting on PCB		No
Modular version		No
Conductor material		Copper