

Braking resistance, IP65, 50 Ω, 0.2 kW, For use with: DC1, DA1, DG1, SVX, SPX



Part no. DX-BR050-200
174235
EL Number 4110057
(Norway)

General specifications		
Product name		Eaton DX Braking resistor
Part no.		DX-BR050-200
EAN		4015081706976
Product Length/Depth		250 millimetre
Product height		20 millimetre
Product width		85 millimetre
Product weight		0.55 kilogram
Certifications		UL UL508 UL Category Control No.: NMTR2, NMTR8 Certified by UL for use in Canada C22.2 UL File No.: E300273 UL report applies to both US and Canada UL
Product Tradename		DX
Product Type		Accessory
Product Sub Type		Braking resistor
Features & Functions		
Fitted with:		Temperature monitoring switch Connection cables (approx. 0.5 m)
General information		
Accessory/spare part type		Braking resistance
Degree of protection		IP00 IP65
Product Category		Accessories
Suitable for		Branch circuits, (UL/CSA)
Type		Wire wound resistor in ceramic potting compound inside aluminum case
Electrical rating		
Voltage rating - max		1000 V
Design verification		
10.2.2 Corrosion resistance		Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures		Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat		Meets the product standard's requirements.
10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects		Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation		Meets the product standard's requirements.
10.2.5 Lifting		Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact		Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions		Meets the product standard's requirements.
10.3 Degree of protection of assemblies		Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances		Meets the product standard's requirements.
10.5 Protection against electric shock		Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components		Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections		Is the panel builder's responsibility.
10.8 Connections for external conductors		Is the panel builder's responsibility.
10.9.2 Power-frequency electric strength		Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage		Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material		Is the panel builder's responsibility.

10.10 Temperature rise			The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating			Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility			Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function			The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 9.0

Low-voltage industrial components (EG000017) / Accessories/spare parts for frequency controller (EC002025)			
Electric engineering, automation, process control engineering / Electrical drive / Static frequency converter / Static frequency converter (accessories) (ecl@ss13-27-02-31-92 [AFR303008])			
Type of accessory/spare part			Breaking resistance
Accessory			Yes
Spare part			No