Circuit-breaker, 3p, 160A



Part no. NZMN2-VE160-NA 271149

General specifications	
Product name	Eaton Moeller series NZM - Molded Case Circuit Breaker
Part no.	NZMN2-VE160-NA
EAN	4015082711498
Product Length/Depth	149 millimetre
Product height	195 millimetre
Product width	105 millimetre
Product weight	2.345 kilogram
Compliances	RoHS conform
Certifications	CE marking UL (File No. E31593) UL listed CSA certified CSA (File No. 22086) IEC/EN 60947 Specially designed for North America UL (Category Control Number DIVQ) UL 489 CSA (Class No. 1432-01) IEC IEC 60947-2 CSA-C22.2 No. 5-09 UL/CSA
Product Tradename	NZM
Product Type	Molded Case Circuit Breaker
Product Sub Type	None
Delivery program	
Application	Branch circuits, feeder circuits Use in unearthed supply systems at 690 V
Туре	Circuit breaker
Circuit breaker frame type	NZM2
Number of poles	Three-pole
Amperage Rating	160 A
Release system	Electronic release
Features	Protection unit Motor drive optional
Special features	Maximum back-up fuse, if the expected short-circuit currents at the installation location exceed the switching capacity of the circuit breaker (Rated short-circuit breaking capacity Icn) Rated current = rated uninterrupted current: 160 A Switches conform to UL/CSA as well as the IEC regulations. IEC switching performance values are contained on the rating plate. Adjustable overload releases Ir R.m.s. value measurement and "thermal memory" adjustable time delay setting to overcome current peaks tr: 2 – 20 s at 6 x Ir Adjustable delay time tsd: Steps: 0, 20, 60, 100, 200, 300, 500, 750, 1000 ms i²t constant function: fixed OFF
Technical Data - Electrical	
Voltage rating	690 V - 690 V
Rated operating voltage Ue (UL) - max	600Y/347 V, 480 V
Rated insulation voltage (Ui)	1000 V AC
Rated impulse withstand voltage (Uimp) at auxiliary contacts	6000 V
Rated impulse withstand voltage (Uimp) at main contacts	8000 V
Rated operational current	300 A (415 V AC-1, making and breaking capacity) 160 A (690 V AC-1, making and breaking capacity) 300 A (380/400 V AC-1, making and breaking capacity) 160 A (660-690 V AC-3, making and breaking capacity)
Rated short-time withstand current (t = 0.3 s)	1.9 kA
Rated short-time withstand current (t = 1 s)	1.9 kA
Instantaneous current setting (Ii) - min	1920 A

Instantaneous current setting (li) - max	1920 A
Overload current setting (Ir) - min	80 A
Overload current setting (Ir) - max	160 A
Short delay current setting (Isd) - min	160 A
Short delay current setting (Isd) - max	1600 A
Short-circuit release delayed setting - min	160 A
Short-circuit release delayed setting - max	1600 A
Short-circuit release non-delayed setting - min	1920 A
Short-circuit release non-delayed setting - max	1920 A
Rated short-circuit breaking capacity Ics (IEC/EN 60947) at 230 V, 50/60 Hz	85 kA
Rated short-circuit breaking capacity Ics (IEC/EN 60947) at 400/415 V, 50/60 Hz	50 kA
Rated short-circuit breaking capacity Ics (IEC/EN 60947) at 440 V, 50/60 Hz	35 kA
Rated short-circuit breaking capacity Ics (IEC/EN 60947) at 525 V, 50/60 Hz	25 kA
Rated short-circuit breaking capacity Ics (IEC/EN 60947) at 690 V, 50/60 Hz	5 kA
Rated short-circuit making capacity Icm at 240 V, 50/60 Hz	187 kA
Rated short-circuit making capacity Icm at 400/415 V, 50/60 Hz	105 kA
Rated short-circuit making capacity Icm at 440 V, 50/60 Hz	74 kA
Rated short-circuit making capacity Icm at 440 V, 50/60 Hz	53 kA
Rated short-circuit making capacity Icm at 525 V, 50/60 Hz	40 kA
Short-circuit total breaktime	< 10 ms
Low-voltage HBC fuse - max	355 A gG/gL
Electrical connection type of main circuit	Screw connection
Isolation	500 V AC (between auxiliary contacts and main contacts)
ISOIduUII	300 V AC (between the auxiliary contacts)
Number of operations per hour - max	120
Handle type	Rocker lever
Utilization category	A (IEC/EN 60947-2)
Overvoltage category	III
Pollution degree	3
Lifespan, electrical	7500 operations at 690 V AC-1 5000 operations at 690 V AC-3 6500 operations at 400 V AC-3 6500 operations at 415 V AC-3 10000 operations at 400 V AC-1
Direction of incoming supply	As required
Technical Data - Mechanical	
Mounting Method	Built-in device fixed built-in technique Fixed DIN rail (top hat rail) mounting optional
Degree of protection	IP20 (hasis degree of protection in the operating controls area)
Degree of protection (IP), front side	IP20 (basic degree of protection, in the operating controls area) IP40 (with insulating surround) IP66 (with door coupling rotary handle)
Degree of protection (terminations)	IP10 (tunnel terminal) IP00 (terminations, phase isolator and strip terminal)
Protection against direct contact	Finger and back-of-hand proof to DIN EN 50274/VDE 0106 part 110
Shock resistance	20 g (half-sinusoidal shock 20 ms)
Number of auxiliary contacts (change-over contacts)	0
Number of auxiliary contacts (normally closed contacts)	0
Number of auxiliary contacts (normally open contacts)	0
Position of connection for main current circuit	Front side
Climatic proofing	Damp heat, cyclic, to IEC 60068-2-30 Damp heat, constant, to IEC 60068-2-78
Special features	Maximum back-up fuse, if the expected short-circuit currents at the installation location exceed the switching capacity of the circuit breaker (Rated short-circuit breaking capacity Icn) Rated current = rated uninterrupted current: 160 A Switches conform to UL/CSA as well as the IEC regulations. IEC switching performance values are contained on the rating plate. Adjustable overload releases Ir R.m.s. value measurement and "thermal memory" adjustable time delay setting to overcome current peaks tr: 2 – 20 s at 6 x Ir Adjustable delay time tsd: Steps: 0, 20, 60, 100, 200, 300, 500, 750, 1000 ms i²t constant function: fixed OFF

Lifespan, mechanical	20000 operations
Technical Data - Mechanical - Terminals	
Standard terminals	Screw terminal
Terminal capacity (control cable)	16 mm ² - 18 mm ² (2x) 14 mm ² - 18 mm ² (1x)
Terminal capacity (aluminum solid conductor/cable)	16 mm² (1x) at tunnel terminal
Terminal capacity (copper busbar)	Min. 16 mm x 5 mm direct at switch rear-side connection M8 at rear-side screw connection Max. 20 mm x 5 mm direct at switch rear-side connection
Terminal capacity (copper solid conductor/cable)	6 mm² - 11 mm² (1x) direct at switch rear-side connection 16 mm² (1x) at tunnel terminal 6 mm² - 12 mm² (1x) at box terminal
Terminal capacity (copper stranded conductor/cable)	$4\ mm^2$ - $3/0\ mm^2$ (1x) direct at switch rear-side connection $4\ mm^2$ - $350\ mm^2$ (1x) at box terminal $4\ mm^2$ - $350\ mm^2$ (1x) at tunnel terminal
Terminal capacity (copper strip)	Max. 10 segments of 16 mm x 0.8 mm at rear-side connection (punched) Min. 2 segements of 16 mm x 0.8 mm at rear-side connection (punched) Min. 2 segments of 9 mm x 0.8 mm at box terminal Max. 10 segments of 16 mm x 0.8 mm at box terminal
Design verification as per IEC/EN 61439 - technical data	
Rated operational current for specified heat dissipation (In)	160 A
Equipment heat dissipation, current-dependent	21.12 W
Ambient operating temperature - min	-25 °C
Ambient operating temperature - max	70 °C
Ambient storage temperature - min	40 °C
Ambient storage temperature - max	70 °C
Design verification as per IEC/EN 61439	
10.2.2 Corrosion resistance	Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures	Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat	Meets the product standard's requirements.
10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects	Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation	Meets the product standard's requirements.
10.2.5 Lifting	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions	Meets the product standard's requirements.
10.3 Degree of protection of assemblies	Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances	Meets the product standard's requirements.
10.5 Protection against electric shock	Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must b observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must b observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.
Additional information	
Functions	Systems, cable, selectivity and generator protection Current limiting circuit breaker

Technical data ETIM 9.0

 $Low-voltage\ industrial\ components\ (EG000017)\ /\ Power\ circuit-breaker\ for\ trafo/generator/installation\ protection\ (EC000228)$

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Circuit breaker for power transformer, generator and system protection (ecl@ss13-27-37-04-09 [AJZ716018])

Rated short-circuit breaking capacity lou at 400 V, 50 Hz Overload release current setting Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-ci			
Overload release current setting Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit release Adjustment range lede shuit-in technique No	Rated voltage	V	690 - 690
Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit release Built-in device fixed built-in technique Adjustment range undelayed short-circuit release No Screw connection No Screw connection No Adjustment range undelayed short-circuit release No	Rated short-circuit breaking capacity Icu at 400 V, 50 Hz	kA	50
Adjustment range undelayed short-circuit release A 1920 - 1920	Overload release current setting	А	80 - 160
Power loss Device construction Device construction Integrated earth fault protection Integrated earth fault protection Type of electrical connection of main circuit Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional No DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as schange-over contact Number of auxiliary contacts as change-over contact Nith switched-off indicator Nith integrated under voltage release No	Adjustment range short-term delayed short-circuit release	А	160 - 1600
Device construction Integrated earth fault protection Type of electrical connection of main circuit Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact Number of poles No No With integrated under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional	Adjustment range undelayed short-circuit release	А	1920 - 1920
Integrated earth fault protection Type of electrical connection of main circuit Screw connection Screw connection No Screw connection No No DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Yes Number of auxiliary contacts as normally closed contact 0 Number of auxiliary contacts as normally open contact 0 Number of auxiliary contacts as change-over contact 0 With switched-off indicator No With integrated under voltage release No No Number of poles 1 Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional No	Power loss	W	21.12
Type of electrical connection of main circuit Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact No With switched-off indicator With switched-off indicator No With integrated under voltage release No No No No No No No No Connection for main current circuit Front side Rocker lever Complete device with protection unit Motor drive integrated Motor drive optional Screw connection No No No No Screw connection No No Ves	Device construction		Built-in device fixed built-in technique
Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of poles No	Integrated earth fault protection		No
DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact No With switched-off indicator With integrated under voltage release No Number of poles 3 Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional Yes Yes No No No No No No No No No N	Type of electrical connection of main circuit		Screw connection
Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact No With switched-off indicator With integrated under voltage release No No Number of poles Sale Position of connection for main current circuit Type of control element Complete device with protection unit Yes Motor drive integrated Motor drive optional No No No No No No No No No N	Suitable for DIN rail (top hat rail) mounting		No
Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact No With switched-off indicator With integrated under voltage release No Number of poles Solution of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional O O No No No No No Rocker lever No No Yes	DIN rail (top hat rail) mounting optional		Yes
Number of auxiliary contacts as change-over contact With switched-off indicator No With integrated under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional O No No No No No No Yes	Number of auxiliary contacts as normally closed contact		0
With switched-off indicator With integrated under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional No No No No No No Yes	Number of auxiliary contacts as normally open contact		0
With integrated under voltage release No Number of poles Some of connection for main current circuit Type of control element Complete device with protection unit Motor drive optional No No No No No No Yes	Number of auxiliary contacts as change-over contact		0
Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive optional 3 Front side Rocker lever Rocker lever Yes No Yes	With switched-off indicator		No
Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive optional Front side Rocker lever Yes No Yes	With integrated under voltage release		No
Type of control element Complete device with protection unit Motor drive optional Rocker lever Yes No Yes	Number of poles		3
Complete device with protection unit Yes Motor drive integrated No Motor drive optional Yes	Position of connection for main current circuit		Front side
Motor drive integrated No Motor drive optional Yes	Type of control element		Rocker lever
Motor drive optional Yes	Complete device with protection unit		Yes
·	Motor drive integrated		No
Degree of protection (IP) IP20	Motor drive optional		Yes
	Degree of protection (IP)		IP20