Three-phase control isolating safety transformer, 0.1 kVA, Rated input voltage 50 - 950 \pm 5 % V, Rated output voltage 18.5 - 1000 V



Part no. DTZ0,1(*/*)* 914799

| Product name | Eaton Moeller® series DTZ Control transformer |
|--|---|
| Part no. | DTZ0,1(*/*)* |
| Product Length/Depth | 65 millimetre |
| Product height | 134 millimetre |
| Product width | 125 millimetre |
| Product weight | 1.9 kilogram |
| Certifications | UL 5085-2 |
| | UL 506 CE IEC/EN 61558-2-2 UL Recognized UL report applies to both US and Canada CSA-C22.2 No. 66.2-06 Certified by UL for use in Canada UL Category Control No.: XPTQ2, XPTQ8 UL5085-1 CSA-C22.2 No. 66.1-06 UL File No.: E167225 CSA-C22.2 No. 66 |
| Product Tradename | DTZ |
| Product Type | Control transformer |
| Product Sub Type | None |
| eneral information | |
| Ambient operating temperature - min | -25 °C |
| Ambient operating temperature - max | 40 °C |
| Degree of protection | IP00 NEMA Other |
| Product category | Three-phase DTZ control transformers |
| Suitable for | Branch circuits, (UL/CSA) |
| lectrical rating | |
| Rated power | 100 V-A |
| Relative short-circuit voltage | 15 % |
| Short-time rating | 0.2 kV·A |
| Voltage rating - max | 600 V |
| esign verification | |
| Equipment heat dissipation, current-dependent Pvid | 0 W |
| Heat dissipation capacity Pdiss | 0 W |
| Heat dissipation per pole, current-dependent Pvid | 0 W |
| Rated operational current for specified heat dissipation (In) | 0 A |
| Static heat dissipation, non-current-dependent Pvs | 33 W |
| 10.2.2 Corrosion resistance | Meets the product standard's requirements. |
| 10.2.3.1 Verification of thermal stability of enclosures | Meets the product standard's requirements. |
| 10.2.3.2 Verification of resistance of insulating materials to normal heat | Meets the product standard's requirements. |
| 10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects | Meets the product standard's requirements. |
| 10.2.4 Resistance to ultra-violet (UV) radiation | Meets the product standard's requirements. |
| 10.2.5 Lifting | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.2.6 Mechanical impact | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.2.7 Inscriptions | Meets the product standard's requirements. |
| 10.3 Degree of protection of assemblies | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.4 Clearances and creepage distances | Meets the product standard's requirements. |
| 10.5 Protection against electric shock | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.6 Incorporation of switching devices and components | Does not apply, since the entire switchgear needs to be evaluated. |

| 10.7 Internal electrical circuits and connections | Is the panel builder's responsibility. |
|--|--|
| 10.8 Connections for external conductors | Is the panel builder's responsibility. |
| 10.9.2 Power-frequency electric strength | Is the panel builder's responsibility. |
| 10.9.3 Impulse withstand voltage | Is the panel builder's responsibility. |
| 10.9.4 Testing of enclosures made of insulating material | Is the panel builder's responsibility. |
| 10.10 Temperature rise | The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. |
| 10.11 Short-circuit rating | Is the panel builder's responsibility. The specifications for the switchgear must be observed. |
| 10.12 Electromagnetic compatibility | Is the panel builder's responsibility. The specifications for the switchgear must be observed. |
| 10.13 Mechanical function | The device meets the requirements, provided the information in the instruction leaflet (IL) is observed. |

Technical data ETIM 9.0

| Technical data ETIM 9.0 | | | | | |
|---|--|----|-------------|--|--|
| Low-voltage industrial components (EG000017) / Three-phase control transformer (EC002485) | | | | | |
| Electric engineering, automation, process control engineering / Transformer, converter, coil / Control transformer / Three-phase control transformer (ecl@ss13-27-03-13-01 [AAB619020]) | | | | | |
| Built as safety transformer | | | Yes | | |
| Built as isolating transformer | | | Yes | | |
| Built as energy saving transformer | | | No | | |
| Primary voltage 1 | | V | 50 - 950 | | |
| Primary voltage 2 | | V | 50 - 950 | | |
| Primary voltage 3 | | V | 50 - 950 | | |
| Primary voltage 4 | | V | 50 - 950 | | |
| Primary voltage 5 | | V | 50 - 950 | | |
| Primary voltage 6 | | V | 50 - 950 | | |
| Primary voltage 7 | | V | 0 - 0 | | |
| Primary voltage 8 | | V | 0 - 0 | | |
| Primary voltage 9 | | V | 0 - 0 | | |
| Primary voltage 10 | | V | 0 - 0 | | |
| Secondary voltage 1 | | V | 18.5 - 1000 | | |
| Secondary voltage 2 | | V | 18.5 - 1000 | | |
| Secondary voltage 3 | | V | 18.5 - 1000 | | |
| Secondary voltage 4 | | V | 18.5 - 1000 | | |
| Secondary voltage 5 | | V | 18.5 - 1000 | | |
| Secondary voltage 6 | | V | 18.5 - 1000 | | |
| Secondary voltage 7 | | V | 0 - 0 | | |
| Secondary voltage 8 | | V | 0 - 0 | | |
| Secondary voltage 9 | | V | 0 - 0 | | |
| Secondary voltage 10 | | V | 0 - 0 | | |
| Wiring system | | | Other | | |
| Rated power | | VA | 100 | | |
| Type of insulation material according to IEC 85 | | | В | | |
| Short-circuit-proof | | | No | | |
| Relative short circuit voltage | | % | 15 | | |
| Conductor material | | | Copper | | |
| Width | | mm | 125 | | |
| Height | | mm | 134 | | |
| Depth | | mm | 65 | | |
| Degree of protection (IP) | | | IP00 | | |
| Degree of protection (NEMA) | | | Other | | |