



Connection width extension, 4p, 2 studs

Part no. NZM4-4-XKV95-2KB
Catalog No. 132674

Delivery program

Accessories			Connection width extension
Description			Two M12 threaded studs
Number of conductors			4 pole
Rated current	I_n	A	1600
For use with			NZM4-4, N4-4

Terminal capacities

Type of conductor			
Cu/Al cable			Cu cable lugs
Terminal capacities			
flexible		mm ²	4 x 95-300
AWG/kcmil		mm ²	4 x 500

Terminal capacities

Cu strip (number of segments x width x segment thickness)		mm ²	(2x) 10 x 80 x 1.0
Copper busbar width x thickness	Width	mm	(2 x) 10 x 80

Notes

- Type contains parts for 3 to 4-pole switches on top or bottom of switch.
- Double stud bolts M12 for e. g. up to 4 cable lugs 300 mm² per phase.
- For fitting to switches with screw connection.
- Distance between pole centers if 95 mm
- Can be fitted to current transformers up to 130 mm in width and with a bar width of 80 mm.
- 4 mm drilling dimensions for control circuit terminal available.
- Hole for large cover NZM4(-4)-XKSAV included.

Design verification as per IEC/EN 61439

IEC/EN 61439 design verification			
10.2 Strength of materials and parts			
10.2.2 Corrosion resistance			Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures			Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat			Meets the product standard's requirements.
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects			Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation			Meets the product standard's requirements.
10.2.5 Lifting			Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact			Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions			Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES			Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances			Meets the product standard's requirements.
10.5 Protection against electric shock			Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components			Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections			Is the panel builder's responsibility.
10.8 Connections for external conductors			Is the panel builder's responsibility.
10.9 Insulation properties			
10.9.2 Power-frequency electric strength			Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage			Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material			Is the panel builder's responsibility.

10.10 Temperature rise			The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating			Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility			Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function			The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 7.0

Low-voltage industrial components (EG000017) / Connection vane/phase spreader (EC002019)			
Electric engineering, automation, process control engineering / Low-voltage switch technology / Component for low-voltage switching technology / Connection vane/phase spreader (ecl@ss10.0.1-27-37-13-05 [ACN990012])			
Suitable for number of poles			4