### **DATASHEET - IZMX16B4-P16W-1**



Circuit-breaker, 4 pole, 1600A, 42 kA, P measurement, IEC, Withdrawable



Powering Business Worldwide

Part no. IZMX16B4-P16W-1 Catalog No. 183461

EL-Nummer

4398075

(Norway)

## **Delivery program**

| Delivery program                            |                        |    |  |
|---|------------------------|----|--|
| Product range                               |                        |    | Air circuit-breakers/switch-disconnectors  |
| Product range                               |                        |    | Open circuit-breakers  |
| Current Range                               |                        |    | Up to 4000 A   |
| Protective function                         |                        |    | P measurement  |
| Installation type                           |                        |    | Withdrawable   |
|   |                        |    | Cassette must be separately ordered.   |
|   |                        |    | IZMX-DTP-PTM external voltage measuring module required  |
| Construction size                           |                        |    | IZMX16   |
| Release system                              |                        |    | Electronic release   |
| Standard/Approval                           |                        |    | IEC  |
| Number of poles                             |                        |    | 4 pole   |
| Degree of Protection                        |                        |    | IP31 with door seals, IP55 with protective cover   |
|   |                        |    | suitable for zone selectivity suitable for communication with integrated system monitor with integrated test possibility With graphic LCD display optionally fittable by user with comprehensive accessories |
| Rated current = rated uninterrupted current | $I_n = I_u$            | Α  | 1600   |
| up to 440 V 50/60 Hz                        | I <sub>cu</sub>        | kA | 42   |
| up to 440 V 50/60 Hz                        | I <sub>cs</sub>        | kA | 42   |
| Overload release, min.                      | I <sub>r</sub>         | Α  | 640  |
| Overload release, max.                      | I <sub>r</sub>         | Α  | 1600   |
| Non-delayed                                 | $I_i = I_n x \dots$    |    | 2 - 15, OFF  |
| Delayed X >                                 | $I_{sd} = I_r x \dots$ |    | 1,5 - 10   |

### **Technical data**

#### General

| General              |   |    |   |
|----------------------|---|----|---|
| Standards            |   |    | IEC/EN 60947  |
| Ambient temperature  |   |    |   |
| Storage              | 9 | °C | -20 - +70   |
| Ambient temperature  |   | °C | -20 - +70   |
| Mounting position    |   |    | 30° 30°   |
| Utilization category |   |    | 30° 30°   |
| Degree of Protection |   |    | IP31 with door seals, IP55 with protective cover      |
| Dogree of Frotection |   |    | ii oi witti tooi settis, ii sa witti proteetive covei |

| Direction of incoming supply  |                                  |      | as required |
|---|----------------------------------|------|-------------|
| Main conducting paths   |                                  |      | as required |
| Rated current = rated uninterrupted current   | $I_n = I_u$                      | Α    | 1600        |
| Rated uninterrupted current at 50 °C  | I <sub>u</sub>                   | Α    | 1500        |
| Rated uninterrupted current at 60 °C  | I <sub>u</sub>                   | A    | 1400        |
| Rated uninterrupted current at 70 °C  | I <sub>u</sub>                   | Α    | 1350        |
| Rated impulse withstand voltage   | U <sub>imp</sub>                 | V AC | 12000       |
| Rated operational voltage   | U <sub>e</sub>                   | V AC | 690         |
|   | U                                | V    |             |
| Use in IT electrical power networks up to   | U                                | V    | 440         |
| Overvoltage category/pollution degree   |                                  | V    | 1100        |
| Rated insulation voltage  Switching capacity  | Ui                               | V    | 1000        |
| Rated short-circuit making capacity   | I <sub>cm</sub>                  |      |             |
| up to 440 V 50/60 Hz  | I <sub>cm</sub>                  | kA   | 88          |
|   |                                  |      |             |
| up to 690 V 50/60 Hz  | I <sub>cm</sub>                  | kA   | 88          |
| Rated short-time withstand current 50/60 Hz   |                                  |      |             |
| t=1s  | I <sub>cw</sub>                  | kA   | 42          |
| Rated short-circuit breaking capacity I <sub>cn</sub>   | I <sub>cn</sub>                  |      |             |
| IEC/EN 60947 operating sequence I <sub>cu</sub> 0-t-C0  |                                  |      |             |
| up to 240 V 50/60 Hz  | I <sub>cu</sub>                  | kA   | 42          |
| up to 440 V 50/60 Hz  | I <sub>cu</sub>                  | kA   | 42          |
| up to 690 V 50/60 Hz  | I <sub>cu</sub>                  | kA   | 42          |
| IEC/EN 60947 operating sequence I <sub>cs</sub> O-t-CO-t-CO   |                                  |      |             |
| up to 240 V 50/60 Hz  | I <sub>cs</sub>                  | kA   | 42          |
| up to 440 V 50/60 Hz  | I <sub>cs</sub>                  | kA   | 42          |
| up to 690 V 50/60 Hz  | I <sub>cs</sub>                  | kA   | 42          |
| Operating times   | 63                               |      |             |
| Closing delay via spring release  |                                  | ms   | 30          |
| Total opening delay via shunt release   |                                  | ms   | 30          |
| Total opening delay via undervoltage release  |                                  | ms   | 50          |
| ical spennig doley the discontinues in the control of the control |                                  | 0    |             |
| Total opening delay on non-delayed short-circuit release (up to complete arc quenching)   |                                  | ms   | 27          |
| Lifespan  |                                  | S    |             |
| Lifespan, mechanical  | Switching cycles (ON/ OFF)       |      | 12500       |
| Lifespan, mechanical with maintenance   | Switching cycles (ON/ OFF)       |      | 25000.      |
| Lifespan, electrical  | Switching<br>cycles (ON/<br>OFF) |      | 10000       |
| Lifespan, electrical with maintenance   | Switching<br>cycles (ON/<br>OFF) |      | 20000.      |
| Maximum operating frequency   | Operations/h                     |      | 60          |
| Heat dissipation at rated current I <sub>n</sub>  |                                  |      |             |
| Withdrawable units (switch with cassette)   |                                  | W    | 320         |
| Weight  |                                  |      |             |
| Withdrawable  |                                  |      |             |
| 4-pole  |                                  | kg   | 33          |
| Cassette  |                                  |      |             |
| 4 pole  |                                  | kg   | 21          |
| Terminal capacities   |                                  |      |             |
| Copper bar  |                                  |      |             |
| Withdrawable units  |                                  |      | 2           |
| Black   |                                  | mm   | 2 x 5 x 100 |

|       | These are values used in separate switchgear. The actual val<br>the temperature around the circuit-breaker, which is influenc<br>temperature, the degree of protection (IP), the mounting heigl<br>any external ventilation. Depending on the specific switchgear<br>result in derating, which can then be compensated for by inconsectional area. Temperature rise tests in the specific switchg<br>specific and detailed information. | ed by the ambient<br>nt, the partitions, and<br>or design, this may<br>reasing the cross- |
|-------|---|---|
|       | Permissible continuous current for circuit-breakers operating at various internal ambient temperatures. The switchboard's i temperature should be estimated using the calculation metho   | nternal ambient   |
| Notes | External IZMX-DTP-PTM-1 voltage measuring module require suitable for 16 circuit-breakers)  | d (1 module is  |

## Design verification as per IEC/EN 61439

| Technical data for design verification   |                  |    |  |
|--|------------------|----|--|
| Rated operational current for specified heat dissipation   | In               | Α  | 1600   |
| Equipment heat dissipation, current-dependent  | P <sub>vid</sub> | W  | 320  |
| Operating ambient temperature min.   |                  | °C | -20  |
| Operating ambient temperature max.   |                  | °C | 70   |
| IEC/EN 61439 design verification   |                  |    |  |
| 10.2 Strength of materials and parts   |                  |    |  |
| 10.2.2 Corrosion resistance  |                  |    | Meets the product standard's requirements.   |
| 10.2.3.1 Verification of thermal stability of enclosures   |                  |    | Meets the product standard's requirements.   |
| 10.2.3.2 Verification of resistance of insulating materials to normal heat   |                  |    | Meets the product standard's requirements.   |
| 10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects |                  |    | Meets the product standard's requirements.   |
| 10.2.4 Resistance to ultra-violet (UV) radiation   |                  |    | Meets the product standard's requirements.   |
| 10.2.5 Lifting   |                  |    | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.2.6 Mechanical impact   |                  |    | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.2.7 Inscriptions  |                  |    | Meets the product standard's requirements.   |
| 10.3 Degree of protection of ASSEMBLIES  |                  |    | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.4 Clearances and creepage distances   |                  |    | Meets the product standard's requirements.   |
| 10.5 Protection against electric shock   |                  |    | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.6 Incorporation of switching devices and components   |                  |    | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.7 Internal electrical circuits and connections  |                  |    | Is the panel builder's responsibility.   |
| 10.8 Connections for external conductors   |                  |    | Is the panel builder's responsibility.   |
| 10.9 Insulation properties   |                  |    |  |
| 10.9.2 Power-frequency electric strength   |                  |    | Is the panel builder's responsibility.   |
| 10.9.3 Impulse withstand voltage   |                  |    | Is the panel builder's responsibility.   |
| 10.9.4 Testing of enclosures made of insulating material   |                  |    | Is the panel builder's responsibility.   |
| 10.10 Temperature rise   |                  |    | The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. |
| 10.11 Short-circuit rating   |                  |    | Is the panel builder's responsibility. The specifications for the switchgear must be observed.                                   |
| 10.12 Electromagnetic compatibility  |                  |    | Is the panel builder's responsibility. The specifications for the switchgear must be observed.                                   |
| 10.13 Mechanical function  |                  |    | The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.                         |

### **Technical data ETIM 7.0**

Low-voltage industrial components (EG000017) / Power circuit-breaker for trafo/generator/installation protection (EC000228)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Circuit breaker for power transformer, generator and system protection (ecl@ss10.0.1-27-37-04-09 [AJZ716013])

| protection (ect@5510.0.1-27-37-04-03 [A02710013])         |    |                 |
|---|----|-----------------|
| Rated permanent current lu                                | Α  | 1600            |
| Rated voltage   | V  | 690 - 690       |
| Rated short-circuit breaking capacity Icu at 400 V, 50 Hz | kA | 42              |
| Overload release current setting                          | Α  | 800 - 1600      |
| Adjustment range short-term delayed short-circuit release | Α  | 3200 - 16000    |
| Adjustment range undelayed short-circuit release          | Α  | 3200 - 19200    |
| Integrated earth fault protection                         |    | No              |
| Type of electrical connection of main circuit             |    | Rail connection |

| Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional No   |   |   |
|--|---|---|
| No Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact  No Number of auxiliary contacts as change-over contact  Yes No No Number of poles No No Number of poles No No Number of connection for main current circuit No No Number of control element No No Number of poles No No Notor drive integrated No N   | Device construction                                     | Built-in device slide-in technique (withdrawable) |
| Number of auxiliary contacts as normally closed contact  Number of auxiliary contacts as normally open contact  Number of auxiliary contacts as change-over contact  Noth the switched-off indicator  Noth the switched-off indicator  Noth the switched off indicator | Suitable for DIN rail (top hat rail) mounting           | No  |
| Number of auxiliary contacts as normally open contact  Number of auxiliary contacts as change-over contact  Nith switched-off indicator  With under voltage release  No  Number of poles  Position of connection for main current circuit  No Back side  Push button  Complete device with protection unit  Notor drive optional  No  Yes  | DIN rail (top hat rail) mounting optional               | No  |
| Aumber of auxiliary contacts as change-over contact  Ves  Vith switched-off indicator  Vith under voltage release  No  Aumber of poles  Vosition of connection for main current circuit  Complete device with protection unit  Ves  Motor drive optional  2  Yes  Yes  No  Yes  No  Yes  No  Yes   | Number of auxiliary contacts as normally closed contact | 0   |
| Vith switched-off indicator  Vith under voltage release  Vith under voltage release  No  Number of poles  Variety of connection for main current circuit  Variety of control element  Complete device with protection unit  Variety of voltage release  No  No  Notor drive optional  Ves  | Number of auxiliary contacts as normally open contact   | 0   |
| No Number of poles 4 Position of connection for main current circuit Back side Type of control element Push button Complete device with protection unit Yes Motor drive optional No Yes  | Number of auxiliary contacts as change-over contact     | 2   |
| Aumber of poles  Aumber of poles  Aumber of poles  Australia Back side  August button  August button  August button  Yes  Autor drive optional  August button  Yes  August button  Yes  August button  Yes  August button  Yes  Yes  | With switched-off indicator                             | Yes   |
| Position of connection for main current circuit  Position of connection for main current circuit  Push button  Yes  Motor drive optional  Back side  Push button  Yes  Yes   | With under voltage release                              | No  |
| Type of control element Complete device with protection unit Motor drive optional  Push button Yes  No Yes   | Number of poles   | 4   |
| Complete device with protection unit  Yes  Motor drive optional  Yes  Yes  | Position of connection for main current circuit         | Back side   |
| Motor drive optional No Yes  | Type of control element                                 | Push button                                       |
| Motor drive optional Yes   | Complete device with protection unit                    | Yes   |
|  | Motor drive integrated                                  | No  |
| Degree of protection (IP)  | Motor drive optional                                    | Yes   |
|  | Degree of protection (IP)                               | IP31  |

# **Dimensions**

