

Control transformer, 0.5 kVA, Rated input voltage 208 – 600 V, Rated output voltage 2 x 115 V



Powering Business Worldwide™

Part no. **UTI0,5-115**
206926

Product name	Eaton Moeller® series UTI Control transformer
Part no.	UTI0,5-115
EAN	4015082069261
Product Length/Depth	120 millimetre
Product height	124 millimetre
Product width	121 millimetre
Product weight	6.8 kilogram
Certifications	UL5085-1 VDE 0550 CE UL report applies to both US and Canada UL Recognized VDE 0570 Part 2-2/2-6 (safety transformer) VDE 0570 Part 2-4 (isolating transformer) CSA-C22.2 No. 66 UL 506 IEC/EN 61558-2-2/2-4/2-6 IEC/EN 61558-2-2 UL File No.: E167225 UL 5085-2 CSA-C22.2 No. 66.2-06 Certified by UL for use in Canada UL Category Control No.: XPTQ2, XPTQ8 IEC/EN 60204-1, ÖVE-EN 13 VDE 0113, VDE 0100 Part 410 CSA-C22.2 No. 66.1-06
Product Tradename	UTI
Product Type	Control transformer
Product Sub Type	None
Catalog Notes	Electrical characteristics: all details for no-load loss, short-circuit loss (copper losses), short-circuit voltage and efficiency values relate to a temperature of 20 °C
Features	Separate windings Fully Vacuum-impregnated Reinforced insulation
Ambient operating temperature - min	-25 °C
Ambient operating temperature - max	40 °C
Connection type	Terminations
Degree of protection	IP00
Duty factor	100 %
Insulation class	B
Primary tapping	± 20 %
Product category	Single-phase UTI multi-winding transformers
Suitable for	Branch circuits, (UL/CSA)
Efficiency	91.8 %
No-load losses	26 W
Rated frequency - min	50 Hz
Rated frequency - max	60 Hz
Rated power	0.5 V-A
Relative short-circuit voltage	3.5 %
Short-circuit losses	23 W
Voltage rating - max	600 V
Equipment heat dissipation, current-dependent P _{vid}	0 W

Heat dissipation capacity P _{diss}		0 W
Heat dissipation per pole, current-dependent P _{vid}		0 W
Rated operational current for specified heat dissipation (I _n)		0 A
Static heat dissipation, non-current-dependent P _{vs}		49 W
10.2.2 Corrosion resistance		Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures		Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat		Meets the product standard's requirements.
10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects		Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation		Meets the product standard's requirements.
10.2.5 Lifting		Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact		Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions		Meets the product standard's requirements.
10.3 Degree of protection of assemblies		Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances		Meets the product standard's requirements.
10.5 Protection against electric shock		Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components		Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections		Is the panel builder's responsibility.
10.8 Connections for external conductors		Is the panel builder's responsibility.
10.9.2 Power-frequency electric strength		Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage		Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material		Is the panel builder's responsibility.
10.10 Temperature rise		The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating		Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility		Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function		The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 8.0

Low-voltage industrial components (EG000017) / One-phase control transformer (EC002486)		
Electric engineering, automation, process control engineering / Transformer, converter, coil / Control transformer / One-phase control transformer (ecl@ss10.0.1-27-03-13-02 [AAB620015])		
Built as safety transformer		Yes
Built as isolating transformer		Yes
Built as energy saving transformer		No
Primary voltage 1	V	208 - 600
Primary voltage 2	V	0 - 0
Primary voltage 3	V	0 - 0
Primary voltage 4	V	0 - 0
Primary voltage 5	V	0 - 0
Primary voltage 6	V	0 - 0
Primary voltage 7	V	0 - 0
Primary voltage 8	V	0 - 0
Primary voltage 9	V	0 - 0
Primary voltage 10	V	0 - 0
Secondary voltage 1	V	115 - 115
Secondary voltage 2	V	115 - 115
Secondary voltage 3	V	0 - 0
Secondary voltage 4	V	0 - 0
Secondary voltage 5	V	0 - 0
Secondary voltage 6	V	0 - 0
Secondary voltage 7	V	0 - 0
Secondary voltage 8	V	0 - 0
Secondary voltage 9	V	0 - 0
Secondary voltage 10	V	0 - 0
Rated apparent power	VA	500

Type of insulation material according to IEC 85			B
Short-circuit-proof			No
Relative short circuit voltage		%	3.5
Width		mm	121
Height		mm	124
Depth		mm	120
Degree of protection (IP)			IP00
Ring core			No
Suitable for mounting on PCB			No
Modular version			No
Conductor material			Copper