### **DATASHEET - DILM12-XP1**



Paralleling link, for DILM7-12/MP20



Part no.DILM12-XP1Catalog No.281193Alternate CatalogXTCEXPLKBNo.EL-NummerKurren 4110350(Norway)

# **Delivery program**

Contact sequence	
Product range	Accessories
Accessories	Wiring accessories
For use with	DILM7 - DILM15 DILMP20
For use with	Paralleling links for DILM7 to DILM15 Paralleling links for DILMP20
Information about equipment supplied	consisting of 2 paralleling links
Instructions AC1 current carrying capacity of the open contactor increases by a factor of 2.5 Protected against accidental contact in accordance to VDE 0106 part 100	

4th pole can be broken off

#### Technical data Parallel link

	mm <sup>2</sup>	
	mm <sup>2</sup>	1 - 16
	mm <sup>2</sup>	1 x (0.5 - 25) 2 x (0.5 - 16)
	mm <sup>2</sup>	1 x (0.5 - 25) 2 x (0.5 - 16)
Lamellenzahl x Breite x Dicke	mm	6 x 9 x 0.8
	Nm	4
	Size	2
$I_{th} = I_e$	А	
I <sub>th</sub>	А	50
	x Breite x Dicke	mm²     mm² </td

## Design verification as per IEC/EN 61439

I <sub>n</sub>	А	50
P <sub>vid</sub>	W	0.2
P <sub>vid</sub>	W	0.2
P <sub>vs</sub>	W	0
P <sub>diss</sub>	W	0
	°C	-25
	°C	60
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Meets the product standard's requirements.
	P <sub>vid</sub> P <sub>vid</sub> P <sub>vs</sub>	P <sub>vid</sub> W P <sub>vid</sub> W P <sub>vs</sub> W P <sub>diss</sub> W °C

10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects	Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation	Meets the product standard's requirements.
10.2.5 Lifting	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions	Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances	Meets the product standard's requirements.
10.5 Protection against electric shock	Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9 Insulation properties	
10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

#### **Technical data ETIM 7.0**

Low-voltage industrial components (EG000017) / Accessories for low-voltage switch technology (EC002498)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Component for low-voltage switching technology / Component for low-voltage switch technology (accessories) (ecl@ss10.0.1-27-37-13-92 [AKN570013])

Type o	f accessory
--------	-------------

Connecting bridge

Approvals		
Product Standards	IEC/EN 60947-4-1; UL 508; CSA-C22.2 No. 14-05; CE marking	
UL File No.	E29096	
UL Category Control No.	NLDX	
CSA File No.	012528	
CSA Class No.	3211-03	
North America Certification	UL listed, CSA certified	
Specially designed for North America	No	

## Additional product information (links)

Motor starters and "Special Purpose Ratings" for the North American market	http://www.eaton.eu/ecm/groups/public/@pub/@europe/@electrical/documents/content/pct_3258146.pdf
Switchgear of Power Factor Correction Systems	http://www.moeller.net/binary/ver_techpapers/ver934en.pdf
X-Start - Modern Switching Installations Efficiently Fitted and Wired Securely	http://www.moeller.net/binary/ver_techpapers/ver938en.pdf
Mirror Contacts for Highly-Reliable Information Relating to Safety-Related Control Functions	http://www.moeller.net/binary/ver_techpapers/ver944en.pdf
Effect of the Cabel Capacitance of Long Control Cables on the Actuation of Contactors	http://www.moeller.net/binary/ver_techpapers/ver949en.pdf
Switchgear for Luminaires	http://www.moeller.net/binary/ver_techpapers/ver955en.pdf
Standard Compliant and Functionally Safe Engineering Design with Mechanical Auxiliary Contacts	http://www.moeller.net/binary/ver_techpapers/ver956en.pdf
The Interaction of Contactors with PLCs	http://www.moeller.net/binary/ver_techpapers/ver957en.pdf
Busbar Component Adapters for modern Industrial control panels	http://www.moeller.net/binary/ver_techpapers/ver960en.pdf