

# ROTARY CAM SWITCH 7GN SERIES, CHANGEOVER SWITCH 4 POLES 20A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 48X48MM

Product designation			Rotary cam switches
Product type designation			7GN20
General characteristics			
Switching diagram			75 - Changeover switch 4 poles
N° of elements			4
Mounting form			U - Front mounting with black handle
Contact characteristics			
Rated insulation voltage Ui			
	IEC/EN	V	690
	UL/CSA	V	600
Rated impulse withstand voltage Uimp		kV	6
Conventional free air thermal current Ith	JEO/EN		00
	IEC/EN UL/CSA	A A	20 20
Rated operational voltage	UL/C3A		480
Rated operational impulse voltage		kV	4
Maximum fuse size for short-circuit protection In (gG)			'
(90)	10kA	Α	20
	15kA	Α	16
	25kA	Α	16
Rated short time current lcw			
	1s	Α	250
Conductivity			10/5 mA/V
Operational current le IEC/EN			
AC1/AC21A		^	20
AC15		A	20
ACIS	110V	Α	10
	220/230V	Α	8
	380/400V	Α	6
	660/690V	Α	1.5
Rated operational power in AC			
Three-phase AC-3			
	220/230V	kW	3
	380/440V	kW	5.5
0:	500/690V	kW	5.5
Single-phase AC-3	110V	Iz\A/	0.8
	220/230V	kW kW	2.2
	380/440V	kW	3
Three-phase AC23A	300/440 V	17 4 4	<u> </u>
	220/230V	kW	5
	380/440V	kW	7.5
_	500/690V	kW	7.5
Single-phase AC23A			
	110V	kW	0.8
	220/230V	kW	2.5
Rated operational current in DC	380/440V	kW	3.7





# ROTARY CAM SWITCH 7GN SERIES, CHANGEOVER SWITCH 4 POLES 20A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 48X48MM


	D0044			
	DC21A	40\/	٨	20
		48V 60V	A	20
		110V	A	20 4
		220V	A	0.6
		220 V 440 V	A	0.6
	DC22A (nolog in poriog)	440 V	Α	0.25
	DC23A (poles in series)	0.41/	۸	00 (4)
		24V	A	20 (1)
		48V	A	20 (2)
		60V	A	20 (3)
		110V	A	10 (3)
	D040	220V	A	8 (4)
	DC13	0.41.7		00
		24V	A	20
		48V	Α	16
		60V	Α	12
		110V	Α	1
		220V	Α	0.4
·		440V	Α	0.15
Power dissipation			W	0.8
Mechanical features				
Terminals screw				M3
Tightening torque for te	erminals max		Nm	0.5
Conductor size				·
	AWG - Rigid cable			
	-	min	AWG	20
		Max	AWG	12
	AWG - Flexible cable			
		min	AWG	20
		Max	AWG	14
	Conductor size (IEC) - Flexible cable			
	()	min	mm²	0.5
		Max	mm²	2.5
	Conductor size (IEC) - Rigid cable			
	Conductor cizo (IEO) Trigia cable	min	mm²	0.5
		Max	mm²	2.5
Mechanical life		IVIOX	cycles	5x10 <sup>6</sup>
UL technical data			Cycles	3710
Motor power for direct-	on-line control			
wiotor power for direct				
	for three-phase motor	120V	HP	1.5
		120V 240V	HP	3
		480V	HP	3 7.5
	for almula alta a mater	600V	HP	10
	for single-phase motor	4001/	UD	0.75
		120V	HP	0.75
A mala i a mala a malitira mana		240V	HP	2
Ambient conditions				
Temperature				
	Operating temperature			
		min	°C	-25
		max	°C	+55
	Storage temperature			
		min	°C	-40




**ENERGY AND AUTOMATION** 

## ROTARY CAM SWITCH 7GN SERIES, CHANGEOVER SWITCH 4 POLES 20A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 48X48MM

	max	°C	+70	
Resistance & Protection				
Frontal IP degree			IP40	
Terminals IP degree			IP00	
Dimensions				






Standard drillings for 7GN125. Drillings on request for 4 screws fixing (4V version).

Carios	Dimensions								L Number of elements												
Series	□A	С	ØD	ØD1	ØD2	Е	ØG	□K	□N	1	2	3	4	5	6	7	8	9	10	11	12
7GN12	48	39.5	39	12	5	26.5	38	36	6	36.1	45.8	55.5	65.2	74.9	84.6	94.3	104	113.7	123.4	133.1	142.8
7GN20	48	39.5	39	12	5	26.5	38	36	6	36.1	45.8	55.5	65.2	74.9	84.6	94.3	104	113.7	123.4	133.1	142.8
7GN25	48	39.5	43	12	5	26.5	38	36	6	40.5	54.1	67.7	81.3	94.9	108.5	122.1	135.7	147.3	162.9	176.5	190.1
7GN32	65	53	58	14	5	34.5	58.5	48	7	46.5	61.6	76.7	91.8	106.9	122	137.1	152.2	167.3	182.4	197.5	212.6
7GN40	65	53	58	14	5	34.5	58.5	48	7	46.5	61.6	76.7	91.8	106.9	122	137.1	152.2	167.3	182.4	197.5	212.6
7GN63	65	53	62	14	5	34.5	58.5	48	7	50.3	68.4	86.5	104.6	122.7	140.8	158.9	177	195.1	213.2	231.3	249.4
7GN125	90	70.5	86	16	6	41.5	84	68	9	67.3	96.4	125.5	154.6	183.7	220.3	249.4	278.5	307.6	336.7	365.8	394.9

#### Wiring diagrams



### Certifications and compliance

Compliance

CSA C22.2 n° 14

IEC/EN/BS 60947-1

IEC/EN/BS 60947-3

IEC/EN/BS 60947-5-1

UL60947-4-1

Certificates

cCSAus

EAC

UL

ETIM classification

ETIM 8.0

EC001105 - Offload switch