



Electric Automation
Automation specialists

Reference: 1SDA037735R1

E4H/MS 3200 4p F F

Buy it at Electric Automation Network



C.BREAKER SWITCH-DISCONNECTOR E4H/MS 3200A FOUR-POLE FIXED WITH TERMINALES FRONT

Ordering

| | |
|-------------------------|---------------|
| EAN: | 8015644377359 |
| Minimum Order Quantity: | 1 piece |
| Customs Tariff Number: | 85362090 |

Dimensions

| | |
|---------------------|---------|
| Product Net Width: | 515 mm |
| Product Net Height: | 600 mm |
| Product Net Length: | 920 mm |
| Product Net Depth: | 0.302 m |
| Product Net Weight: | 113 kg |

Container Information

| | |
|-------------------------------|---------------|
| Package Level 1 Units: | 1 piece |
| Package Level 1 Height: | 600 mm |
| Package Level 1 Length: | 515 mm |
| Package Level 1 Gross Weight: | 135 kg |
| Package Level 1 EAN: | 8015644377359 |

Environmental

| | |
|--------------|-----------------------|
| RoHS Status: | No declaration needed |
|--------------|-----------------------|

Additional Information

| | |
|--|-------------------------------|
| Electrical Durability: | 7000 |
| IIT Publishing Status: | Level 0 - Information enabled |
| Number of Poles: | 4 |
| Power Loss: | 235 W |
| Product Main Type: | SACE Emax Old |
| Product Name: | Switch-disconnector |
| Product Type: | SD |
| Rated Current (I_n): | 3200 A |
| Rated Operational Voltage: | 600 V AC |
| Standards: | IEC-947-3 |
| Sub-type: | E4 |
| Suitable For: | Emax E4 |
| Suitable for Product Class: | Emax |
| Terminal Connection Type: | Front |
| Test Voltage at Industrial Frequency for 1 Minute: | 3500 V |
| Version: | Fixed |

Certificates and Declarations (Document Number)

| | |
|------------------------------------|-----------------|
| Data Sheet, Technical Information: | 1SDC200001D0201 |
| Declaration of Conformity - CE: | 1SDL000162R0044 |
| RoHS Information: | 1SDL000197R0001 |

Classifications

| | |
|-----------------------------|---|
| ETIM 4: | EC000228 - Power circuit-breaker for trafo/generator/ installation prot. |
| ETIM 5: | EC000228 - Power circuit-breaker for trafo/generator/ installation prot. |
| Object Classification Code: | Q |