

XLP1-6BC



XLP1-6BC Fuse Switch Disconnecter

General Information

Extended Product Type	XLP1-6BC
Product ID	1SEP101891R0002
EAN	7025840013730
Catalog Description	XLP1-6BC Fuse Switch Disconnecter
Long Description	XLP1,3-pole,250A, incl. 6 Bridge Clamps

Ordering

EAN	7025840013730
Minimum Order Quantity	1 piece
Customs Tariff Number	85389099

Dimensions

Product Net Width	185 mm
Product Net Height	270 mm
Product Net Depth / Length	116 mm
Product Net Weight	1.8 kg

Container Information

Package Level 1 Units	1 piece
Package Level 1 Width	185 mm
Package Level 1 Height	270 mm
Package Level 1 Depth / Length	116 mm
Package Level 1 Gross Weight	1.8 kg
Package Level 2 EAN	7025840013730

Additional Information

Degree of Protection	IP30
Frequency (f)	MainCircuit 50/60 Hz
Fuse Size	NH1
Fuse System	DIN
Fuse Type	NH

Fuse Protected Short-Circuit Making	MainCircuit 50 kiloampere rms
Fuse Protected Short-Circuit Withstand	MainCircuit 50 kiloampere rms
Handle Type	Front cover 3P
Mounting Type	Baseplate
Number of Poles	3
Order Multiple	1 piece
Product Main Type	XLP1
Product Name	Fuse Switch Disconnecter
Rated Current (I_n)	250 A
Rated Frequency (f)	Main Circuit 50/60 Hz
Rated Voltage (U_r)	500 V AC 690 V AC 800 V AC
Rated Impulse Withstand Voltage (U_{imp})	Main Circuit 8 kV
Rated Operational Current AC-21B (I_e)	(690 V) 200 A
Rated Operational Current AC-22B (I_e)	(500 V) 250 A
Rated Operational Voltage	500 V AC 690 V AC 800 V AC
Special Functions	Not Included
Suitable For	Baseplate
Terminal Type	Cable Clamp

Certificates and Declarations (Document Number)

Data Sheet, Technical Information	1SEC312012D0201
Declaration of Conformity - CE	1SEP500050P0001

Classifications

ETIM 4	EC001040 - Fuse switch disconnecter
ETIM 5	EC001040 - Fuse switch disconnecter
ETIM 6	EC001040 - Fuse switch disconnecter
ETIM 7	EC001040 - Fuse switch disconnecter
Object Classification Code	S
UNSPSC	39121600
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)

Categories

Low Voltage Products and Systems → Fusegear → Fuse Switch Disconnectors → EasyLine

