




Shunt release, up to 63A, 110-415V, 1HP

Part no. **FAZ-XAA-C-110-415VAC**  
 Catalog No. **278519**  
 Alternate Catalog No. **FAZ-XAA-C-110-415VAC**  
 EL-Nummer (Norway) **1695014**

Similar to illustration

## Delivery program

Basic function		Accessories for miniature circuit-breaker
Basic function accessories		Shunt release
Product range		Accessory
Contact sequence		

## Technical data

### Electrical

Voltage range		V AC	12 ... 110 110 ... 415
Rated frequency	f	Hz	50/60

### Mechanical

Standard front dimension		mm	45
Enclosure height		mm	80
Mounting width		mm	17.5 (1 space unit)
Mounting			IEC/EN 60715 top-hat rail
Degree of protection			
Integrated			IP40
Terminal protection			Protection against electric shock to IEC 536
Terminals			Twin-purpose terminals
Terminal capacities		mm <sup>2</sup>	
Solid		mm <sup>2</sup>	1 ... 2.5
flexible		mm <sup>2</sup>	1 ... 2.5
Tightening torque of terminal screws		Nm	2.4

## Design verification as per IEC/EN 61439

Technical data for design verification			
Operating ambient temperature min.		°C	-5
Operating ambient temperature max.		°C	40

## Technical data ETIM 7.0

Devices for distribution board-/surface mounting (EG000062) / Auxiliary device for distribution board devices (EC001286)			
Electric engineering, automation, process control engineering / Electrical installation, device / Breaker switch component / Auxiliary contact unit for distribution board (ecI@ss10.0.1-27-14-35-02 [AKE327013])			
Device fitting			Miniature circuit breaker (MCB)
Additional equipment			Shunt release (for power circuit breaker)
Attached at delivery			No

Assembly width (TE)		1
Number of contacts as normally open contact		1
Number of contacts as normally closed contact		1
Number of contacts as change-over contact		0
Number of fault-signal switches		0
Rated switch current	A	0
Rated voltage	V	110
Voltage type for actuating		AC
With auto test for earth leakage function		No
Suitable for max. number of poles main contact unit (total)		1
Suitable for max. current main contact unit	A	0

## Dimensions

