



505.M16864

PRESA INTERBLOCCATA

16A 3P+T 3h 380V 50Hz / 440V 60Hz 50Hz
60Hz 136X125MM_PAR Morsetti a vite Con
interblocco meccanico

Certificati

TECHDATA		NORME E LEGGI	
Tipologia prodotto	PRESA INTERBLOCCATA	EN 60309-1 (1999)	[European Standard] Plugs, socket-outlets and couplers for industrial purposes. Part 1: General requirements
Serie commerciale	Serie OMNIA	EN 60309-2 (1999)	[European Standard] Plugs, socket-outlets and couplers for industrial purposes. Part 2: Dimensional interchangeability requirements for pin and contact-tube accessories of harmonized configurations
Descrizione sintetica	PRESA INTERBLOCCATA		
Tipo installazione	PARETE		
Corrente nominale	16A	EN 60309-1/A1 (2007)	[European Standard] Plugs, socket-outlets and couplers for industrial purposes. Part 1: General requirements
Poli	3P+T	EN 60309-2/A1 (2007)	[European Standard] Plugs, socket-outlets and couplers for industrial purposes. Part 2: Dimensional interchangeability requirements for pin and contact-tube accessories of harmonized configurations
Riferimento Orario	3h		
Tensione nominale (range)	250-400V	EN 60309-4 (2007)	[European Standard] Plugs, socket-outlets and couplers for industrial purposes. Switched socket-outlets and connectors, with or without interlock
Tensione nominale	380V 50Hz / 440V 60Hz		
Frequenza d'impiego	50Hz	EN 60309-1/A2 (2012)	[European Standard] Plugs, socket-outlets and couplers for industrial purposes. Part 1: General requirements
Frequenza d'impiego	60Hz	EN 60309-2/A2 (2012)	[European Standard] Plugs, socket-outlets and couplers for industrial purposes. Part 2: Dimensional interchangeability requirements for pin and contact-tube accessories of harmonized configurations
Colore	ROSSO		
Materiale	TERMOPLASTICO		
Grado di protezione generico	Stagno all'immersione	DIRECTIVE LOW VOLTAGE 2014/35 /UE	[European Directives] Low Voltage Directive
Grado di protezione IP	IP66/IP67		
Grado di protezione IK	IK08		
Morsetti	Morsetti a vite		
Materiale di contatto	CuZn (ottone)		

Flangia	136X125MM_PAR
Opzioni	Con interblocco meccanico
Note	SENZA BASE PORTAFUSIBILI