



**Electric Automation**  
Automation specialists

Reference: E6H/MS6300  
Code: 1SDA059010R1

E6H/MS 6300 4p F HR new

Buy it at Electric Automation Network



SACE EMAX C.BREAKER SWITCH-DISCONNECTOR E6H/MS 6300A FOUR-POLE FIXED WITH TERMINALES REAR HORIZONTAL NEW

### Ordering

EAN:	8015644613693
Minimum Order Quantity:	1 piece
Customs Tariff Number:	85362090

### Dimensions

Product Net Width:	908 mm
Product Net Height:	418 mm
Product Net Depth:	302 mm
Product Net Weight:	128 kg

### Container Information

Package Level 1 Units:	1 piece
Package Level 1 Width:	515 mm
Package Level 1 Height:	600 mm
Package Level 1 Length:	1127 mm
Package Level 1 Gross Weight:	151 kg
Package Level 1 EAN:	8015644609139

### Additional Information

Electrical Durability:	2000 cycle 10 cycles per hour
Mechanical Durability:	12000 cycle 60 cycles per hour
Number of Poles:	4
Power Loss:	at Rated Operating Conditions per Pole 650 W
Product Main Type:	SACE Emax
Product Name:	Switch-disconnector
Product Type:	SD
Rated Current ( $I_n$ ):	6300 A
Rated Impulse Withstand Voltage ( $U_{imp}$ ):	12 kV
Rated Insulation Voltage ( $U_i$ ):	1000 V
Rated Operational Current ( $I_e$ ):	6300 A
Rated Operational Voltage:	690 V AC 250 V DC
Rated Short-time Withstand Current ( $I_{cw}$ ):	for 1 s 100 kA for 3 s 85 kA
Rated Uninterrupted Current ( $I_u$ ):	6300 A
Rated Voltage ( $U_r$ ):	690 V
Standards:	IEC 60947
Sub-type:	E6
Terminal Connection Type:	Fixed Circuit-Breakers Rear flat Horizontal
Version:	F

## Certificates and Declarations (Document Number)

Data Sheet, Technical Information:	1SDC200006D0209
Declaration of Conformity - CE:	1SDL000165R0017

## Classifications

ETIM 4:	EC000228 - Power circuit-breaker for trafo/generator/ installation prot.
ETIM 5:	EC000228 - Power circuit-breaker for trafo/generator/ installation prot.
Object Classification Code:	Q