



**Electric Automation**  
Automation specialists

Reference: Acc. E1.2  
Code: 1SDA073907R1

E1.2 W FP Iu=1600 3p HR HR

Buy it at Electric Automation Network



FIXED PART WITHDRAWABLE FOR C.BREAKER SACE EMAX2 E1.2 1600 THREE-POLE WITH REAR HORIZONTAL TERMINALS

### Ordering

EAN:	8015644778408
Minimum Order Quantity:	1 piece
Customs Tariff Number:	85389099

### Dimensions

Product Net Width:	278 mm
Product Net Height:	363.5 mm
Product Net Depth:	271 mm
Product Net Weight:	21.7 kg

### Container Information

Package Level 1 Units:	1 piece
Package Level 1 Gross Weight:	23 kg
Package Level 1 EAN:	8015644609139

### Additional Information

Current Type:	AC
Number of Poles:	3
Product Main Type:	SACE Emax 2
Product Name:	Fixed Part
Product Type:	FP
Rated Current ( $I_n$ ):	1600 A
Rated Impulse Withstand Voltage ( $U_{imp}$ ):	acc. to IEC 60947-2 12 kV
Rated Insulation Voltage ( $U_i$ ):	AC 1000 V
Rated Operational Voltage:	690 V AC
Rated Uninterrupted Current ( $I_u$ ):	1600 A
Rated Voltage ( $U_r$ ):	690 V
Standards:	IEC 60947
Sub-type:	E1.2
Terminal Connection Type:	Rear flat Horizontal
Version:	W FP

## Certificates and Declarations (Document Number)

Data Sheet, Technical Information:	1SDC200023D0204
Declaration of Conformity - CE:	1SDL000165R0019

## Classifications

ETIM 4:	EC000228 - Power circuit-breaker for trafo/generator/ installation prot.
ETIM 5:	EC000228 - Power circuit-breaker for trafo/generator/ installation prot.
Object Classification Code:	Q