



**Electric Automation**  
Automation specialists

Reference: FS401E-B13/0.03  
Code: 2CCL562111E0135

FS401E-B13/0,03 Residual Current  
Circuit Breaker with overcurrent  
Protection 2 Poles B Characteristic 13A  
6000 ~230V

Buy it at [Electric Automation Network](#)



FS401E-B13/0,03 Residual Current Circuit Breaker with overcurrent Protection 2 Poles  
B Characteristic 13A 6000 ~230/400V

### Ordering

EAN:	7612270108558
Minimum Order Quantity:	1 piece
Customs Tariff Number:	85362020

### Dimensions

Product Net Width:	36 mm
Product Net Height:	91 mm
Product Net Length:	72 mm
Product Net Depth:	75 mm
Product Net Weight:	0.250 kg

### Container Information

Package Level 1 Units:	2 piece
Package Level 1 Width:	100 mm
Package Level 1 Height:	90 mm
Package Level 1 Length:	75 mm

Package Level 1 Gross Weight:	0.058 kg
Package Level 1 EAN:	7612270108558

## Environmental

RoHS Status:	Following EU Directive 2002/95/EC August 18, 2005 and amendment
--------------	---

## Additional Information

IIT Publishing Status:	Level 0 - Information enabled
Number of Poles:	2
Power Loss:	3.33 W
Product Main Type:	FS401
Product Name:	FS401
Rated Current ( $I_n$ ):	13 A
Rated Operational Current ( $I_e$ ):	13 A
Rated Operational Voltage:	230 / 400 V AC
Rated Residual Current:	0.03 AMPx
Rated Short-Circuit Capacity ( $I_{cn}$ ):	10 kA
Standards:	EN61009-1
Tripping Characteristic:	B

## Certificates and Declarations (Document Number)

Data Sheet, Technical Information:	2CCC451059C0202
Declaration of Conformity - CE:	2CCY451110D0601
RoHS Information:	2CCC451021D0201

## Classifications

ETIM 4:	EC000003 - Residual current circuit breaker (RCCB)
ETIM 5:	EC000003 - Residual current circuit breaker (RCCB)
Object Classification Code:	FB